




Dell Touch USB-C Hub Monitor

P2424HT

User's Guide

Monitor Model: P2424HT
Regulatory Model: P2424HTc



-  **NOTE:** A NOTE indicates important information that helps you make better use of your computer.
-  **CAUTION:** A CAUTION indicates potential damage to hardware or loss of data if instructions are not followed.
-  **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.

© 2023 Dell Inc. or its subsidiaries. All rights reserved. Dell Technologies, Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

2023 – 08

Rev. A00



Contents

| | |
|--------------------------------------|----------|
| Safety instructions | 6 |
| About your monitor | 7 |
| Package contents | 7 |
| Product features | 9 |
| Identifying parts and controls | 10 |
| Front view | 10 |
| Top view | 10 |
| Back view | 11 |
| Side view | 12 |
| Bottom view | 13 |
| Monitor specifications | 15 |
| *Dell Display Manager | 17 |
| Touch | 18 |
| Resolution specifications | 18 |
| Supported video modes | 18 |
| Preset display modes | 19 |
| Physical characteristics | 22 |
| Environmental characteristics | 24 |
| Pin assignments | 25 |
| DisplayPort connector | 25 |
| HDMI connector | 26 |
| Universal Serial Bus (USB) interface | 27 |
| RJ45 port (connector side) | 30 |



| | |
|---|-----------|
| Plug and play capability | 39 |
| LCD monitor quality and pixel policy | 39 |
| Ergonomics. | 40 |
| Handling and moving your display | 41 |
| Maintenance guidelines | 43 |
| Cleaning your monitor. | 43 |
| Setting up the monitor | 44 |
| Attaching the stand | 44 |
| Routing the Cables. | 48 |
| Setting up the monitor. | 49 |
| Attaching the Cable Cover. | 50 |
| Using the Tilt, Swivel and Slant | 51 |
| Connecting your monitor | 53 |
| Connecting the USB-C (C-C) cable | 53 |
| Connecting the USB-C (C-A) cable | 54 |
| Connecting the DisplayPort (DisplayPort to DisplayPort) cable | 54 |
| Connecting the HDMI cable (optional) | 54 |
| Use Quick Access Ports | 56 |
| Dell Power Button Sync (DPBS). | 57 |
| Connecting the monitor for DPBS for the first time. | 60 |
| Using DPBS function | 61 |
| Connecting the monitor for USB-C. | 63 |
| Securing your monitor using Kensington lock (optional) | 66 |
| Removing the monitor stand | 67 |
| VESA wall mounting (optional) | 68 |




| | |
|--|------------|
| Operating the monitor | 69 |
| Power on the monitor | 69 |
| Using the joystick control | 70 |
| Using the On-Screen Display (OSD) menu | 71 |
| Accessing the Menu Launcher | 71 |
| Using the navigation keys | 72 |
| Accessing the menu system | 73 |
| Menu and Power button lock | 85 |
| OSD warning messages | 87 |
| Setting the maximum resolution | 93 |
| Troubleshooting | 94 |
| Self-Test | 94 |
| Built-in diagnostics | 95 |
| Common problems | 97 |
| Touchscreen Problems | 102 |
| Universal Serial Bus (USB) specific problems | 103 |
| Regulatory information | 105 |
| FCC notices (U.S. Only) and other regulatory information | 105 |
| EU product database for energy label and product information sheet | 105 |
| Contacting Dell | 105 |




Safety instructions

Use the following safety guidelines to protect your monitor from potential damage and to ensure your personal safety. Unless otherwise noted, each procedure included in this document assumes that you have read the safety information that shipped with your monitor.

 **NOTE: Before using the monitor, read the safety information that is shipped with your monitor and printed on the product. Keep the documentation at a secure location for future reference.**

 **WARNING: Use of controls, adjustments, or procedures other than those specified in this documentation may result in exposure to shock, electrical hazards, and/or mechanical hazards.**

 **WARNING: The possible long-term effect of listening to audio at high volume through the headphones (on monitor that support it) may cause damage to your hearing ability.**

- Place the monitor on a solid surface and handle it carefully. The screen is fragile and can be damaged if dropped or hit with a sharp object.
- Ensure that your monitor is electrically rated to operate with the AC power available in your location.
- Keep the monitor in room temperature. Excessive cold or hot conditions can have an adverse effect on the liquid crystal of the display.
- Connect the power cable from the monitor to a wall outlet that is near and accessible. See [Connecting your monitor](#).
- Do not place and use the monitor on a wet surface or near water.
- Do not subject the monitor to severe vibration or high impact conditions. For example, do not place the monitor inside a car trunk.
- Unplug the monitor when it is going to be left unused for an extended period.
- To avoid electric shock, do not attempt to remove any cover or touch the inside of the monitor.
- Read these instructions carefully. Keep this document for future reference. Follow all warnings and instructions marked on product.
- Certain monitors can be wall mounted using the VESA mount that is sold separately. Ensure to use the correct VESA specifications as mentioned in the wall mounting section of the *User's Guide*.

For information on safety instructions, see the *Safety, Environmental, and Regulatory Information (SERI)* document that is shipped with your monitor.







About your monitor

Package contents

The following table provides the list of components that are shipped with your monitor. If any component is missing, contact Dell. For more information, see [Contacting Dell](#).

 **NOTE: Some items may be optional and may not ship with your monitor. Some features may not be available in certain countries.**

| Component image | Component description |
|---|-----------------------|
|  | Display |
|  | Stand riser |
|  | Stand base |
|  | Cable cover |



| | |
|---|---|
|  | Power cable (varies by country) |
|  | HDMI* cable (1.8 meters) (**For selected countries only) |
|  | DP1.2 cable (DP to DP, 1.8 meters) |
|  | Super speed USB 10 Gbps (USB 3.2 Gen1) Type-C to Type-C upstream cable (C-C cable) (1.8 meter) |
|  | Super speed USB 5 Gbps (USB 3.2 Gen1) Type-C to Type-A upstream cable (C-A cable) (1.8 meters) |
|  | <ul style="list-style-type: none"> • Quick Setup Guide • Safety, Environmental and Regulatory Information |

HDMI* = Supports up to FHD 1920 x 1080 @ 60Hz as per specified in HDMI 1.4.

**Please check with the respective country sales representative.



Product features

The Dell P2424HT monitor has an active matrix, Thin-Film Transistor (TFT), Liquid Crystal Display (LCD) and LED backlight. The monitor features include:

- 60.47 cm (23.8 in.) viewable area display (measured diagonally).
- 1920 x 1080 resolution, with full-screen support for lower resolutions.
- Built-in Mono Speaker (3 W) x 1.
- 10-point Touch for Windows and MacOS, 3-point Touch for Linux.
- Color gamut of 99% sRGB (typical).
- Digital connectivity with DisplayPort, USB-C and HDMI.
- Single USB-C to supply power (PD 90 W) to a compatible notebook while receiving video & data signal.
- Articulating stand with tilt, swivel, height and slant adjustment capabilities.
- Ultra-thin bezel minimizes the bezel gap in multi-monitor usage, enabling easier setup with an elegant viewing experience.
- Removable stand and Video Electronics Standards Association (VESA™) 100 mm mounting holes for flexible mounting solutions.
- Equipped with 1 USB-C upstream port, 1 USB-C downstream port and 3 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream ports.
- USB-C and RJ45 ports enable a single-cable, network-connected experience.
- Plug and play capability if supported by your system.
- On-Screen Display (OSD) adjustments for ease of set-up and screen optimization.
- Power and joystick buttons lock.
- Security lock slot.
- Stand lock.
- Optimize eye comfort with a flicker-free screen and low blue light feature.
- The monitor use Low Blue Light panel and is in compliance with TUV Rheinland (Hardware Solution) at factory reset/default setting model (Preset mode: Standard).

⚠ WARNING: The possible long-term effects of blue light emission from the monitor may cause damage to the eyes, which includes but is not limited to eye fatigue and digital eye strain. ComfortView Plus feature is designed to reduce the amount of blue light emitted from the monitor to optimize eye comfort.



Identifying parts and controls

Front view



| Label | Description |
|-------|--|
| 1 | Power LED indicator Solid white light indicates that the monitor is turned on and functioning normally. Blinking white light indicates that the monitor is in Standby Mode. |


Top view



| Label | Description |
|-------|-------------------|
| 1 | Built-in speaker. |



Back view





Back View with monitor stand

| Label | Description | Use |
|-------|--|--|
| 1 | VESA mounting holes (100 mm x 100 mm - behind attached VESA Cover) | Wall-mount the monitor using VESA-compatible wall mount kit (100 mm x 100 mm). |
| 2 | Regulatory label | Lists the regulatory approvals. |
| 3 | Stand release button | Releases the stand from the monitor. |
| 4 | Joystick | Use to control the OSD menu. (For more Information, see Operating the monitor) |
| 5 | Power On/Off button | To turn the monitor on or off. |
| 6 | Barcode, serial number, and Service Tag label | Contains monitor details and support information. Refer to this label if you need to contact Dell for technical support. |
| 7 | Cable hook | Use to route cables. |
| 8 | Cable routing label | Shows how to route cables. |
| 9 | Quick Access Door | Push to open/Push to close the Quick Access Door. |
| 10 | Cable-management slot | Use to organize cables by inserting them through the slot. |




Side view




| Label | Description | Use |
|-------|-------------------------|--|
| 1 | USB 3.2 downstream port | Port with  battery icon supports BC 1.2. |
| 2 | USB-C downstream port | Connect the USB-C (C-C) or (C-A) cable that came with your monitor to the computer. The SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-C port supports 5 V/3 A. |







Bottom view



Bottom view without monitor stand

| Label | Description | Use |
|-------|---|---|
| 1 | Security lock slot (based on Kensington Security Slot) | Secure your monitor using a security lock (purchased separately) to prevent unauthorized movement of your monitor. |
| 2 | Power connector | Connect the power cable (shipped with your monitor). |
| 3 | Stand lock | Lock the stand to the monitor using a M3 x 6 mm screw (screw not included). |
| 4 | HDMI port | Connect to your computer using a HDMI cable (purchased separately). |
| 5 | DisplayPort | Connect your computer with the DisplayPort cable (shipped with your monitor). |
| 6 | USB-C upstream port | <p>Connect the USB-C (C-C) or (C-A) cable that came with your monitor to the computer. Once this cable is connected, you can use the USB downstream connectors on the monitor and the touch screen function on the monitor. This port supports USB Power Delivery, Data, and DisplayPort video signal. The SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-C port supports Alternate Mode DP1.2 with a maximum resolution of 1920 x 1080 @ 60 Hz, PD 20 V/4.5 A, 15 V/3 A, 9 V/3 A, 5 V/3 A.</p> <p> NOTE: USB-C is not supported on versions of Windows prior to Windows 10.</p> |



| | | |
|----|---|---|
| 7 | SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream port | <p>Connect your USB device.*</p> <p> NOTE: To use this port, you must connect the USB-C (C-C) or (C-A) cable (shipped with your monitor) to the USB-C upstream port on the monitor and to your computer.</p> |
| 8 | Audio line-out port | <p>Connect speakers to playback audio coming through HDMI or DP audio channels.</p> <p>Only supports 2-channel audio.</p> <p> NOTE: The audio line-out port does not support headphones.</p> <p> WARNING: Excessive sound pressure from earphones or headphones can cause hearing damage or loss.</p> |
| 9 | RJ45 port (10/100/1000 Mb) | <p>Connect the Internet. You can surf Internet via RJ45 only after you have connected the USB-C (C-C) or (C-A) cable (shipped with your monitor) from the computer to the monitor.</p> |
| 10 | SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream port | <p>Connect your USB device.*</p> <p> NOTE: To use this port, you must connect the USB-C (C-C) or (C-A) cable (shipped with your monitor) to the USB-C upstream port on the monitor and to your computer.</p> |
| 11 | Cushions x2 | <p>Protect the monitor and table when used at lower position.</p> |

*To avoid signal interference, when a wireless USB device has been connected to a USB downstream port, it is NOT recommended to connect any other USB devices to the adjacent port(s).



Monitor specifications

| | |
|------------------------------------|---|
| Screen type | Active matrix - TFT LCD |
| Panel type | In-Plane Switching Technology |
| Aspect ratio | 16:9 |
| Viewable image | |
| Diagonal | 604.70 mm (23.80 in.) |
| Horizontal, Active Area | 527.04 mm (20.75 in.) |
| Vertical, Active Area | 296.46 mm (11.67 in.) |
| Area | 156246.28 mm ² (242.15 in. ²) |
| Native resolution and refresh rate | 1920 x 1080 @ 60 Hz |
| Pixel pitch | 0.2745 mm x 0.2745 mm |
| Pixel per inch (PPI) | 93 |
| Viewing angle | |
| Horizontal | 178° (typical) |
| Vertical | 178° (typical) |
| Luminance output | 300 cd/m ² (typical) |
| Contrast ratio | 1000 to 1 (typical) |
| Display screen coating | Anti-glare treatment of the front polarizer (3H) hard coating |
| Backlight | LED edgelight system |
| Response time (Gray to Gray) | 5 ms (Fast mode) 8 ms (Normal mode) |
| Color depth | 16.78 million colors (6 bit+A-FRC) |
| Color gamut | sRGB 99% (typical) |



| | |
|--|---|
| Connectivity | <ul style="list-style-type: none"> • 1 x HDMI port version 1.4 (HDCP 1.4) (Supports up to FHD 1920 x 1080@60 Hz) • 1 x DisplayPort version 1.2 (HDCP 1.4) (Supports up to FHD 1920 x 1080@60 Hz) • 1 x USB-C 3.2 Gen1 upstream port (Alternate mode with DisplayPort 1.2, HBR, Power Delivery PD up to 90 W) • 2 x SuperSpeed USB 5 Gbps (USB 3.2 Gen1) downstream port • 1 x USB 3.2 Gen1 with BC 1.2 charging capability (up to 10W, 5V/2A) • 1 x USB-C 3.2 Gen1 downstream port (Power Delivery up to 15W, 5V/3A) • 1 x audio line out (3.5 mm jack) • 1 x RJ45 port |
| Bezel width (edge of monitor to active area) | |
| Top | 5.87 mm |
| Left/Right | 5.88 mm |
| Bottom | 18.65 mm |
| Adjustability | |
| Height adjustable stand | 110.52 mm |
| Tilt | -5° to 60° |
| Swivel | -30° to 30° |
| Slant Adjust | -4° to 4° |
| Cable management | Yes |
| Dell Display Manager 2.x compatibility* | This monitor is compatible with Dell Display Manager |
| Security | Security lock slot (sold separately) |
| Built-in Speaker | 3 W x1 |



*Dell Display Manager

Dell Display Manager is an application software that enhances the experience of your Dell monitor- ensuring more productivity and ease in customization.

With this application you can:


1. Adjust the monitor On Screen Display (OSD) settings such as brightness, contrast, input source setting and so on with ease. No need to toggle using the joystick on the monitor; simply use the DDM software.
2. Organize multiple applications on your screen, snapping them into a template of your choice with the Easy Arrange.
3. Assign applications or even files to the partitions of Easy Arrange, save the layout as a profile, and then restore the profile automatically using Easy Arrange Memory.
4. Connect your Dell Monitor to multiple input sources and manage these multiple video inputs using Input source.
5. Customize each application with different color mode using Color Preset.
6. Replicate the Dell Display Manager application settings from one monitor to another monitor of the same model with Import/export application settings

Moreover, this model comes with advanced remote management features for IT admins.

For more information on Dell Display Manager, visit

<https://www.dell.com/support/ddm>

You can download the software from this link and find detailed user guide of the software and knowledge base article under the documentation tab.



Dell Display Manager User Interface



Touch

| | |
|------------------------------------|--|
| Type | Projected Capacitive System |
| Panel Diagonal | 23.8 inch |
| Active Area | |
| Horizontal | 527.04 mm (20.75 inches) |
| Vertical | 296.46 mm (11.67 inches) |
| Area | 156246.28 mm ² (242.15 inches ²) |
| Touch point | Up to 10-point for Windows and MacOS and up to 3-point for Linux |
| Touch response time | 35 ms |
| Max supported resolution for touch | 32768 x 32768 |
| Touch method | Fingers, gloves (Latex) |
| Operating system | Windows 10 & 11, MacOS and Linux compatible. (iPadOS/iOS/Andriod OS are not supported) (Refer to https://www.dell.com/support/home for related drivers and OS compatibility guide) |

Resolution specifications

| Mode | |
|---------------------------|----------------------------|
| Horizontal scan range | 30 kHz to 88 kHz |
| Vertical scan range | 48 Hz to 75 Hz (automatic) |
| Maximum preset resolution | 1920 x 1080 @ 60 Hz |

Supported video modes

| Model | |
|---|--------------------------------------|
| Video display capabilities (HDMI & DisplayPort & USB-C DP alternate mode) | 480p, 576p, 720p, 1080i(HDMI), 1080p |



Preset display modes

| Display Mode | Horizontal Frequency (kHz) | Vertical Frequency (Hz) | Pixel Clock (MHz) | Sync Polarity (Horizontal / Vertical) |
|-------------------|----------------------------|-------------------------|-------------------|---------------------------------------|
| IBM, 720 x 400 | 31.50 | 70.10 | 28.30 | -/+ |
| VESA, 640 x 480 | 31.50 | 59.90 | 25.20 | -/- |
| VESA, 640 x 480 | 37.50 | 75.00 | 31.50 | -/- |
| VESA, 800 x 600 | 37.90 | 60.30 | 40.00 | +/+ |
| VESA, 800 x 600 | 46.90 | 75.00 | 49.50 | +/+ |
| VESA, 1024 x 768 | 48.40 | 60.00 | 65.00 | -/- |
| VESA, 1024 x 768 | 60.00 | 75.00 | 78.80 | +/+ |
| VESA, 1152 x 864 | 67.50 | 75.00 | 108.00 | +/+ |
| VESA, 1280 x 1024 | 64.00 | 60.00 | 108.00 | +/+ |
| VESA, 1280 x 1024 | 79.90 | 75.00 | 135.00 | +/+ |
| VESA, 1600 x 900 | 60.00 | 60.00 | 108.00 | +/+ |
| CTA, 1920 x 1080 | 67.50 | 60.00 | 148.50 | +/+ |

 **Note:** This monitor may work with other display resolutions not listed in the preset mode table above.



Electrical specifications

| Model | |
|------------------------------------|---|
| Video input signals | <ul style="list-style-type: none">• HDMI*/DisplayPort 1.2, 600 mV for each differential line, 100 ohm input impedance per differential pair• USB-C (with DP alternate mode) signal input support |
| AC input voltage/frequency/current | 100 VAC to 240 VAC / 50 Hz or 60 Hz \pm 3 Hz / 2 A (typical) |
| Inrush current | <ul style="list-style-type: none">• 120 V: 30 A (Max.) at 0°C (cold start)• 240 V: 60 A (Max.) at 0°C (cold start) |
| Power consumption | <ul style="list-style-type: none">• 0.3 W (Off mode)¹• 0.5 W (Standby Mode)¹• 18 W (On mode)¹• 190 W (Max.)²• 17.75 W (Pon)³• 58.98 kWh (TEC) |

HDMI* = Supports up to FHD 1920 x 1080 @ 60Hz as per specified in HDMI 1.4.

¹ As defined in EU 2019/2021 and EU 2019/2013.

² Max brightness and contrast setting with maximum power loading on all USB ports.

³ Pon: Power consumption of On Mode as defined in Energy Star 8.0 version.

TEC: Total energy consumption in kWh as defined in Energy Star 8.0 version.

This document is informational only and reflects laboratory performance. Your product may perform differently, depending on the software, components and peripherals you ordered and shall have no obligation to update such information.

Accordingly, the customer should not rely upon this information in making decisions about electrical tolerances or otherwise. No warranty as to accuracy or completeness is expressed or implied.






NOTE: This monitor is ENERGY STAR certified.



This product qualifies for ENERGY STAR in the factory default settings which can be restored by “Factory Reset” function in the OSD menu. Changing the factory default settings or enabling other features may increase power consumption that could exceed the ENERGY STAR specified limit.



Physical characteristics

| | |
|--|---|
| Signal cable type | <ul style="list-style-type: none">• Digital: DisplayPort, 20 pins• Digital: HDMI, 19 pins (cable not included)• Universal Series Bus: Type-C, 24 pins |
|  NOTE: Dell monitors are designed to work optimally with the video cables that are shipped with your monitor. As Dell does not have control over the different cable suppliers in the market, the type of material, connector and process used to manufacture these cables, Dell does not guarantee video performance on cables that are not shipped with your Dell monitor. | |
| Dimensions (with stand) | |
| Height (extended) | 431.50 mm (16.99 in.) |
| Height (compressed) | 320.98 mm (12.64 in.) |
| Width | 538.80 mm (21.21 in.) |
| Depth | 248.87 mm (9.80 in.) |
| Dimensions (without stand) | |
| Height | 320.98 mm (12.64 in.) |
| Width | 538.80 mm (21.21 in.) |
| Depth | 54.10 mm (2.13 in.) |
| Stand dimensions | |
| Height (extended) | 345.70 mm (13.61 in.) |
| Height (compressed) | 235.18 mm (9.26 in.) |
| Width | 310.00 mm (12.20 in.) |
| Depth | 248.87 mm (9.80 in.) |
| Base | 310.00 x 242.50 mm (12.20 in. x 9.55 in.) |



| Weight | |
|---|-----------------------------|
| Weight with packaging | 10.78 kg (23.77 lbs) |
| Weight with stand assembly and cables | 8.39 kg (18.50 lbs) |
| Weight without stand assembly (For wall mount or VESA mount considerations - no cables) | 3.86 kg (8.51 lbs) |
| Weight of stand assembly | 4.00 kg (8.82 lbs) |
| Front-frame gloss | Black frame 2-4 gloss units |



Environmental characteristics

| Compliant Standards | |
|--|--|
| <ul style="list-style-type: none">ENERGY STAR certified monitor.EPEAT registered where applicable. EPEAT registration varies by country. See www.epeat.net for registration status by country.RoHS-compliant.TCO Certified and TCO Certified Edge.BFR/PVC free monitor (excluding external cables).Meets NFPA 99 leakage current requirements.Arsenic-free glass and Mercury-free for the panel only. | |
| Temperature | |
| Operating | 0°C to 40°C (32°F to 104°F) |
| Non-operating | <ul style="list-style-type: none">Storage: -20°C to 60°C (-4°F to 140°F)Shipping: -20°C to 60°C (-4°F to 140°F) |
| Humidity | |
| Operating | 10% to 80% (non-condensing) |
| Non-operating | <ul style="list-style-type: none">Storage 5% to 90% (non-condensing)Shipping 5% to 90% (non-condensing) |
| Altitude | |
| Operating (maximum) | 5,000 m (16,400 ft) |
| Non-operating (maximum) | 12,192 m (40,000 ft) |
| Thermal dissipation | <ul style="list-style-type: none">648.464 BTU/hour (Maximum)61.433 BTU/hour (On Mode) |



Pin assignments


DisplayPort connector



| Pin number | 20-pin side of the connected signal cable |
|------------|---|
| 1 | ML3 (n) |
| 2 | GND |
| 3 | ML3 (p) |
| 4 | ML2 (n) |
| 5 | GND |
| 6 | ML2 (p) |
| 7 | ML1 (n) |
| 8 | GND |
| 9 | ML1 (p) |
| 10 | ML0 (n) |
| 11 | GND |
| 12 | ML0 (p) |
| 13 | GND |
| 14 | GND |
| 15 | AUX (p) |
| 16 | GND |
| 17 | AUX (n) |
| 18 | Hot Plug Detect |
| 19 | Re-PWR |
| 20 | +3.3 V DP_PWR |



HDMI connector



| Pin number | 19-pin side of the connected signal cable |
|------------|---|
| 1 | TMDS DATA 2+ |
| 2 | TMDS DATA 2 SHIELD |
| 3 | TMDS DATA 2- |
| 4 | TMDS DATA 1+ |
| 5 | TMDS DATA 1 SHIELD |
| 6 | TMDS DATA 1- |
| 7 | TMDS DATA 0+ |
| 8 | TMDS DATA 0 SHIELD |
| 9 | TMDS DATA 0- |
| 10 | TMDS CLOCK+ |
| 11 | TMDS CLOCK SHIELD |
| 12 | TMDS CLOCK- |
| 13 | CEC |
| 14 | Reserved (N.C. on device) |
| 15 | DDC CLOCK (SCL) |
| 16 | DDC DATA (SDA) |
| 17 | DDC/CEC Ground |
| 18 | +5 V POWER |
| 19 | HOT PLUG DETECT |



Universal Serial Bus (USB) interface

This section gives you information about the USB ports that are available on the monitor.

SuperSpeed USB 5 Gbps (USB 3.2 Gen1)

| Transfer speed | Data rate | Maximum power supported (each port) |
|----------------|-----------|-------------------------------------|
| SuperSpeed | 5 Gbps | 4.5 W |
| High speed | 480 Mbps | 4.5 W |
| Full speed | 12 Mbps | 4.5 W |

USB-C

| USB-C | Description |
|---------------------|--------------------------------------|
| Video | DisplayPort 1.2 |
| Data | SuperSpeed USB 5 Gbps (USB 3.2 Gen1) |
| Power Delivery (PD) | Up to 90 W |



USB downstream connector



| Pin number | 9-pin side of the connector |
|------------|-----------------------------|
| 1 | VCC |
| 2 | D- |
| 3 | D+ |
| 4 | GND |
| 5 | SSRX- |
| 6 | SSRX+ |
| 7 | GND |
| 8 | SSTX- |
| 9 | SSTX+ |



USB-C connector




| Pin number | Signal name | Pin number | Signal name |
|------------|-------------|------------|-------------|
| A1 | GND | B1 | GND |
| A2 | TX1+ | B2 | TX2+ |
| A3 | TX1- | B3 | TX2- |
| A4 | VBUS | B4 | VBUS |
| A5 | CC1 | B5 | CC2 |
| A6 | D+ | B6 | D+ |
| A7 | D- | B7 | D- |
| A8 | SBU1 | B8 | SBU1 |
| A9 | VBUS | B9 | VBUS |
| A10 | RX2- | B10 | RX1- |
| A11 | RX2+ | B11 | RX1+ |
| A12 | GND | B12 | GND |

USB ports


- 1 USB-C upstream - bottom
- 2 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream - bottom
- 1 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream - side
- 1 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-C downstream - side

 **NOTE: SuperSpeed USB 5 Gbps (USB 3.2 Gen1) functionality requires a SuperSpeed USB 5 Gbps (USB 3.2 Gen1)-capable computer.**

 **NOTE: The USB ports on the monitor work only when the monitor is turned On or in power save mode. If you turn Off the monitor and then turn it On, the attached peripherals may take a few seconds to resume normal functionality.**



RJ45 port (connector side)



| Pin number | Signal |
|------------|-------------|
| 1 | CT |
| 2 | TD1+ |
| 3 | TD1- |
| 4 | TD2+ |
| 5 | TD2- |
| 6 | TD3+ |
| 7 | TD3- |
| 8 | TD4+ |
| 9 | TD4- |
| 10 | GND |
| 11 | GREEN |
| 12 | GREEN |
| 13 | GREEN_AMBER |
| 14 | GREEN_AMBER |



Driver installation


Install the Realtek USB GBE Ethernet Controller Driver available for your system. This is available for download at www.dell.com/support under the **Driver and download** section.

Network (RJ45) data rate via USB-C max speed is 1000 Mbps.

NOTE: This LAN port is 1000Base-T IEEE 802.3az compliant, supporting Mac Address (Printed on model label) Pass-thru (MAPT), Wake-on-LAN (WOL) from standby mode (S3/S4/S5 only) and UEFI* PXE Boot function [UEFI PXE Boot is not supported on Dell Desktop PC's (except for OptiPlex 7090/3090 Ultra Desktop)], these 3 features depend on BIOS settings and version of the OS. Functionality may vary with Non Dell PC's.

*UEFI stands for Unified Extensible Firmware Interface.

RJ45 connector LED status



| Label | LED | Color | Description |
|-------|-----------|----------------|--|
| 1 | Left LED | Green | Link/Activity indicator: <ul style="list-style-type: none">• Blinking - Activity on the port.• Green On - Link is being established.• Off - Link is not established. |
| 2 | Right LED | Amber or Green | Speed indicator: <ul style="list-style-type: none">• Amber On - 1000 Mbps• Green On - 100 Mbps• Off - 10 Mbps |

NOTE: The RJ45 cable is non in-box standard accessory.



To support MacOS Multi-touch feature, please install the driver as below guide:

UPDD driver installation

Install Mac Multi Touch Driver available for your system. This is available for download at www.dell.com/support under the “Driver and download” section. UPDD Quick installation guide, please refer to the following link:
<https://support.touch-base.com/Documentation/50245/Quick-installation-guide?Keywords=quick+installation>

Wake On Touch (WOT) in S0 or modern standby (Hibernate) mode will only be supported with the use of the Touch Tool Utility in “mouse mode”.

The default Wake On Touch (WOT) support is for S3 or sleep mode.

Touch Tool Utility installation


To download utility in the Dell.com website. Please refer to the following link:
www.dell.com/support

The user guide for the utility as following information.

Touch Mode: 10 finger touch available.

Mouse Mode: touch within mouse pointer.


How to Use: If you want to switch the mode, the only thing you have to do is click the Mode change.




Multi Touch Monitor support touch identify and setting

Setting in Windows 10 and Windows 11:


1. Search for “Control Panel” in your laptop or Desktop tool bar.




2. Click “Hardware and Sound”.




3. Click “Tablet PC settings” – “Calibrate the screen for pen or touch input”.



4. Click "Setup".



5. Identify pen or touch input screens – Select → Touch input.



6. Follow the indication of your system to identify the multi touch.
 - a. If the monitor matches to the one you want, please use your finger touch the monitor.
 - b. If the monitor dose not match to the one you want, please press “enter” to bypass this monitor and repeat the action on the next monitor.

Tap this screen with a single finger to identify it as the touchscreen.

If this is not the Tablet PC screen, press Enter to move to the next screen. To close the tool, press Esc.

Setting in Mac


1. Search “Identify” in UPDD Daemon to identify multi touch monitors.



2. Identifying each touch monitors follow the indication. Touch and hold the cross until the circle turns blue. If this is not a touch screen click next with a mouse or type Option+x.



3. Click the **Console** in UPDD Daemon to select which P2424HT as main display to be a main controller.



Plug and play capability

You can connect the monitor to any Plug and Play-compatible system. The monitor automatically provides the computer system with its Extended Display Identification Data (EDID) using Display Data Channel (DDC) protocols so that the system can configure itself and optimize the monitor settings. Most monitor installations are automatic; you can select different settings as required. For more information about changing the monitor settings, see [Operating the monitor](#).

LCD monitor quality and pixel policy

During the LCD Monitor manufacturing process, it is not uncommon for one or more pixels to become fixed in an unchanging state which are hard to see and do not affect the display quality or usability. For more information on Dell Monitor Quality and Pixel Policy, see www.dell.com/pixelguidelines.



Ergonomics

 **CAUTION: Improper or prolonged usage of keyboard may result in injury.**


 **CAUTION: Viewing the monitor screen for extended periods of time may result in eye strain.**

For comfort and efficiency, observe the following guidelines when setting up and using your computer workstation:

- Position your computer so that the monitor and keyboard are directly in front of you as you work. Special shelves are commercially available to help you correctly position your keyboard.
- To reduce the risk of eye strain and neck, arm, back, or shoulder pain from using the monitor for long period, we recommend you to:
 1. Set the distance of the screen between 20 in. to 28 in. (50 cm - 70 cm) from your eyes.
 2. Blink frequently to moisten your eyes or wet your eyes with water after prolonged usage of the monitor.
 3. Take regular and frequent breaks for 20 minutes every two hours.
 4. Look away from your monitor and gaze at a distant object at 20 feet away for at least 20 seconds during the breaks.
 5. Perform stretches to relieve tension in the neck, arm, back, and shoulders during the breaks.
- Ensure that the monitor screen is at eye level or slightly lower when you are sitting in front of the monitor.
- Adjust the tilt of the monitor, its contrast, and brightness settings.
- Adjust the ambient lighting around you (such as overhead lights, desk lamps, and the curtains or blinds on nearby windows) to minimize reflections and glare on the monitor screen.
- Use a chair that provides good lower-back support.
- Keep your forearms horizontal with your wrists in a neutral, comfortable position while using the keyboard or mouse.
- Always leave space to rest your hands while using the keyboard or mouse.
- Let your upper arms rest naturally on both sides.
- Ensure that your feet are resting flat on the floor.



- When sitting, ensure that the weight of your legs is on your feet and not on the front portion of your seat. Adjust your chair's height or use a footrest if necessary to maintain a proper posture.
- Vary your work activities. Try to organize your work so that you do not have to sit and work for extended periods of time. Try to stand or get up and walk around at regular intervals.
- Keep the area under your desk clear of obstructions and cables or power cords that may interfere with comfortable seating or present a potential trip hazard.




Handling and moving your display


To ensure that the monitor is handled safely when lifting or moving it, observe the following guidelines:

- Before moving or lifting the monitor, turn off your computer and the monitor.
- Disconnect all cables from the monitor.
- Place the monitor in the original box with the original packing materials.
- Hold the bottom edge and the side of the monitor firmly without applying excessive pressure when lifting or moving the monitor.






- When lifting or moving the monitor, ensure that the screen is facing away from you. Do not press on the display area to avoid any scratches or damage.






- When transporting the monitor, avoid any sudden shock or vibration to it.
- When lifting or moving the monitor, do not turn the monitor upside down while holding the stand base or stand riser. It may result in accidental damage to the monitor or cause personal injury.







Maintenance guidelines

Cleaning your monitor

-  **WARNING:** Before cleaning the monitor, unplug the monitor power cable from the electrical outlet.
-  **CAUTION:** Read and follow the [Safety instructions](#) before cleaning the monitor.
-  **WARNING:** Before cleaning the monitor, unplug the monitor power cable from the electrical outlet.

For best practices, follow the instructions in the list below when unpacking, cleaning, or handling your monitor:

- Use a clean cloth that is slightly dampened with water to clean the stand assembly, the screen, and the chassis of your Dell monitor. If available, use a screen-cleaning tissue or solution suitable for cleaning Dell monitors.
- After cleaning the surface of the table, ensure that it is thoroughly dry and free from any moisture or cleaning agent before placing your Dell monitor on it.
-  **CAUTION:** Do not use detergents or other chemicals such as benzene, thinner, ammonia, abrasive cleaners, or compressed air.
-  **CAUTION:** Using chemicals for cleaning may cause changes in the appearance of the monitor, such as color fading, milky film on the monitor, deformation, uneven dark shade, and peeling of screen area.
-  **WARNING:** Do not spray the cleaning solution or even water directly on the surface of the monitor. Doing so will allow liquids to accumulate at the bottom of the display panel and corrode the electronics resulting in permanent damage. Instead, apply the cleaning solution or water to a soft cloth and then clean the monitor.
-  **NOTE:** Monitor damage due to improper cleaning methods and the use of benzene, thinner, ammonia, abrasive cleaners, alcohol, compressed air, detergent of any kind will lead to a Customer Induced Damage (CID). CID is not covered under the standard Dell warranty.
- If you notice white powder when you unpack your monitor, wipe it off with a cloth.
- Handle your monitor with care as a dark-colored monitor may get scratched and show white scuff marks more than a light-colored monitor.
- To help maintain the best image quality on your monitor, use a dynamically changing screen saver and turn off your monitor when not in use.



Setting up the monitor

Attaching the stand

- ✎ **NOTE:** The stand is not installed at the factory when shipped.
- ✎ **NOTE:** The following instructions are applicable only for the stand that was shipped with your monitor. If you are attaching a stand that you purchased from any other source, follow the setup instructions that were included with the stand.

To attach the monitor stand:

1. Follow the instructions on the flaps of carton to remove the stand from the top cushion that secures it.
2. Remove the stand base and stand riser from the packaging cushion.



- ✎ **NOTE:** The graphics are used for the purpose of illustration only. The appearance of the package cushion may vary.

3. Lower the side of the box with the handle.



 **NOTE:** Before attaching the stand assembly to the display, ensure that the front plate flap is opened to allow space for assembly.


4. Lift the cover, as shown, to access the VESA area for stand assembly.



5. Attach the stand riser to the display.
 - a. Insert the two tabs on the upper part of the stand to the groove on the back of the monitor.
 - b. Press the stand down till it snaps into its place.



6. Align the stand base protruded blocks to the matching slot on the stand.
7. Insert the stand base blocks fully into the stand slot.
8. Lift the screw handle and turn the screw clockwise.
9. After fully tightening the screw, fold the screw handle flat within the recess.



10. Hold the stand riser and lift the monitor carefully, then place it on a flat surface.



 **NOTE: Lift the monitor carefully to prevent it from slipping or falling.**



11. Remove the cover from the monitor.




 **NOTE:** Save the EPE foam cover as a protective blanket when placing the monitor facing downward when attaching the cables.



Routing the Cables






- △ **CAUTION:** Place monitor on a flat, clean, and soft surface to avoid scratching the display panel. You can use the EPE foam cover as a protective blanket.



- Spread the monitor protective cover on a flat surface.
- Place the monitor with its front facing downward on it.
- To routing the cables:
 1. Insert DP cable into DP connector (see Connecting Your Monitor), press the long side of cable hook and push cable to it from top to down.
 2. Repeat step 1 to insert HDMI/USB cables into corresponding connector and organize the cables.
 3. Insert and organize the power cable and tighten all the cables as shown above.



Setting up the monitor

| 1. Your PC connectivity supported by P2424HT | | 2. Cables required to connect P2424HT | | | | | 3. Enabled features on P2424HT | | | |
|--|---|---|---|---|---------------------|--------------------------------------|--------------------------------|---------------------------------------|-------------|--|
| Use case | Port logo (for reference) | USB-C to USB-C Connecting your monitor | USB-C to USB-A Connecting your monitor | DisplayPort or HDMI ⁽¹⁾ Connecting your monitor | RJ45 ⁽²⁾ | Power cords Operating the monitor | PC charging | DPBS Dell Power Button Sync (DPBS) | Touchscreen | Network ⁽²⁾ (WOL/PXE/MAPT ⁽³⁾) |
| Case1. Notebook has USB-C port(s) | USB-C  | Yes | | | Yes | Yes | Yes | Yes ⁽³⁾ | Yes | Yes |
| Case2. Notebook connected with USB-C docking, docking has USB-C port(s) | or  | Yes | | | Yes | Yes | ⁽⁴⁾ | Yes ⁽³⁾ | Yes | Yes |
| Case3. Notebook connected with USB-C docking, docking has USB-A and DisplayPort/HDMI ports | DisplayPort  HDMI  | | Yes | Yes | Yes | Yes | ⁽⁴⁾ | | Yes | Yes |
| Case4. Notebook/Desktop with USB-A and DisplayPort/HDMI ports | USB-A  | | Yes | Yes | Yes | Yes | | | Yes | Yes |

⁽¹⁾ Included for selected countries only.

⁽²⁾ If ethernet network available.

⁽³⁾ Dell selected platform only. Check in dell.com for DPBS compatibility models.

⁽⁴⁾ If USB-C docking supports PC charging as well.



Attaching the Cable Cover



To attach the cable cover:

- Place the cable cover on card slot.
- Follow the direction of arrow and push the cable cover till it snaps into place.




Using the Tilt, Swivel and Slant

 **NOTE:** The graphics are used for the purpose of illustration only. The appearance of the package cushion may vary.

Tilt

With the stand attached to the monitor, you can tilt the monitor for the most comfortable viewing angle and working angle for touch input.


Tilt angle between -5° ~ $+60^{\circ}$.



 **NOTE:** The fully extended 60° working angle is the recommended angle when making touch inputs.

Swivel

Swivel angle between $+30^{\circ}$ ~ -30° .



Slant adjust






Slant adjust angle between $+4^{\circ}$ ~ -4° .



NOTE: The stand is detached when the monitor is shipped from the factory.



Connecting your monitor


-  **WARNING:** Before you begin any of the procedures in this section, follow the [Safety instructions](#).
-  **NOTE:** Dell monitors are designed to work optimally with Dell supplied inbox cables. Dell does not guarantee the video quality and performance if non-Dell cables are used.
-  **NOTE:** Route the cables through the cable-management slot before connecting them.
-  **NOTE:** Do not connect all cables to the computer at the same time.
-  **NOTE:** The images are for the purpose of illustration only. The appearance of the computer may vary.

To connect your monitor to the computer:

1. Turn off your computer and disconnect the power cable.
2. Connect the USB-C (C-C), USB-C (C-A), DisplayPort, or HDMI cable from your monitor to the computer.

Connecting the USB-C (C-C) cable



-  **NOTE:** Use the USB-C (C-C) cable shipped with monitor only.
- This port supports DisplayPort Alternate Mode (DP1.2 standard only).
- The USB-C power delivery compliant port (PD Version 3.0) delivers up to 90 W of power.
- If your notebook requires more than 90 W to operate and the battery is drained, it may not be powered up or charged with the USB PD port of this monitor.
- If not using USB-C (C-C) connection, then need to connect a DisplayPort or an HDMI cable and a USB-C (C-A) data cable.




Connecting the USB-C (C-A) cable



NOTE: The touch input only works if a data cable is connected from the monitor's upstream USB-C port to the computer with the in-box USB C-C or USB C-A cable.

Connecting the DisplayPort (DisplayPort to DisplayPort) cable



Connecting the HDMI cable (optional)



HDMI* = Supports up to FHD 1920 x 1080 @ 60Hz as per specified in HDMI 1.4.




3. Connect the power cables from your computer and monitor into a wall outlet.




Use Quick Access Ports

1. Connect the USB-C (C-C) or USB-C (C-A) cable from your monitor to the computer.
2. Push down on quick access door center near inside opening till click sound. The door will be locked and keep open.
3. Connect USB cables or devices to the quick access ports.
4. After removing USB cables or devices from quick access ports. Push down on the door center near inside opening till click sound. The door will be released and back to original position.



or



Dell Power Button Sync (DPBS)

Your monitor is designed with Dell Power Button Sync (DPBS) feature to allow you to control PC system power state from the monitor power button. This feature is only supported with Dell platforms which has built-in DPBS function, and is only supported over USB-C interface.



To make sure the DPBS function works for the first time, perform the following steps on the DPBS supported platform in the **Control Panel** first.

 **NOTE: DPBS only supports the USB-C upstream port.**

1. Go to **Control Panel**.




4. In the drop-down menu of **When I press the power button**, there are a few options for selection, namely **Do nothing/Sleep/Hibernate/Shut down**. You can select **Sleep/Hibernate/Shut down**.



 **NOTE:** Do not select “Do nothing”, otherwise the monitor power button will not be able to sync with PC system power state.



Connecting the monitor for DPBS for the first time



For the first time setting up the DPBS function:

1. Make sure both the PC and the monitor are OFF.
2. Press the monitor power button to turn ON the monitor.
3. Connect the USB-C cable from the PC to the monitor.
4. Both the monitor and PC will turn ON normally except Dell Optiplex 7090/3090 Ultra platform.
5. When you connect the Dell Optiplex 7090/3090 Ultra platform, you may see both the monitor and PC will turn ON momentarily. Wait for a while (approximately 6 seconds) and both the PC and monitor will turn OFF. When you press either the monitor power button or PC power button, both the PC and monitor will turn ON. The PC system power state is in sync with the monitor power button.

NOTE: When the monitor and PC are both at power OFF state for the first time, it is recommended that you turn ON the monitor first, then connect the USB-C cable from the PC to the monitor.

NOTE: You can power the Dell PC* Ultra platform using its DC adaptor jack. Alternatively, you can power the Dell PC* Ultra platform using the monitor's USB-C cable via Power Delivery (PD); please set USB-C Charging ⚡ 90W to On in Off Mode.


*Ensure to check the Dell PC for DPBS supportability.



Using DPBS function

Waking on the USB-C cable

When you connect the USB-C cable, the Monitor/PC state is as follows:




***Not all Dell PC systems support to wake up the platform via the monitor.**

***After connect the USB-C cable, tap on Keyboard or moving the mouse for the system to continue its boot up process when necessary.**




When you press the monitor power button or PC power button, the Monitor/PC state is as follows:




- When the monitor and the PC power state are both ON, **press and hold the monitor power button for 4 seconds**, the screen prompt will ask if you would like to shut down the PC.





- When the monitor and the PC power state are both ON, **press and hold the monitor power button for 10 seconds**, the PC will shut down.



Connecting the monitor for USB-C


The Dell PC* Ultra platform has two USB-C ports, so both Monitor 1 and Monitor 2 power state can sync with the PC.

When the PC and two monitors are in an initial ON power state, pressing the power button on Monitor 1 or Monitor 2 will turn OFF the PC, Monitor 1, and Monitor 2.


*Ensure to check the Dell PC for DPBS supportability.



 **NOTE: DPBS only supports the USB-C upstream port.**




Ensure to set **USB-C Charging** to **On in Off Mode**. When the PC and two monitors are in an initial OFF power state, pressing the power button on Monitor 1 or Monitor 2 will turn ON the PC, Monitor 1, and Monitor 2.



Securing your monitor using Kensington lock (optional)

The security lock slot is located at the bottom of the monitor. (see [Security lock slot](#)). Secure your monitor to a table using the Kensington security lock.



For more information on using the Kensington lock (sold separately), see the documentation that is shipped with the lock.



 **NOTE:** The image is for the purpose of illustration only. The appearance of the lock may vary.




Removing the monitor stand


-  **NOTE:** To prevent scratches on the LCD screen when removing the stand, ensure that the monitor is placed on a soft surface and handle it carefully.
-  **NOTE:** The following steps are specifically for removing the stand that is shipped with your monitor. If you are removing a stand that you purchased from any other source, follow the setup instructions that are included with the stand.

To remove the stand:

1. Place the monitor on a soft cloth or cushion.
2. Press and hold the stand release button.
3. Lift the stand up and away from the monitor.



VESA wall mounting (optional)



(Screw dimension: M4 x 10 mm).

See the documentation that shipped with the VESA-compatible wall mounting kit.

1. Place the display on a soft cloth or cushion at the edge of the desk.
2. Remove the stand. See [Removing the monitor stand](#).
3. Remove the four screws that secure the display back cover.
4. Install the mounting bracket from the wall mounting kit to the display.
5. To mount the monitor on the wall, see the documentation that shipped with the wall mounting kit.




NOTE: For use only with UL or CSA or GS-listed wall mount bracket with minimum weight/load bearing capacity of 15.44 kg (34.04 lbs).




Operating the monitor

CAUTION: Before using the monitor, it is recommended to fasten the stand riser to a wall using cable tie or a cord that can support the weight of the monitor in order to prevent the monitor from falling.




Power on the monitor

Press the Power button to turn On the monitor.



Using the joystick control

Use the joystick control on the rear of the monitor to make On-Screen Display (OSD) adjustments.



1. Press the joystick to launch the Menu Launcher.
2. Move the joystick up/down/left/right to toggle between options.
3. Press the joystick again to confirm the selection.




Using the On-Screen Display (OSD) menu






Accessing the Menu Launcher

When you toggle or press the joystick, the Menu Launcher appears to let you access the OSD main menu and shortcut functions.

To select a function, move the joystick.




The following table describes the Menu Launcher functions:






| | Joystick | Description |
|---|--|---|
| 1 |  Shortcut key/ Input Source | To choose an input source from the list of video signals that may be connected to your monitor. |
| 2 |  Shortcut key/ Preset Modes | To choose a preferred color mode from the list of preset modes. |
| 3 |  Shortcut key/ Brightness/Contrast | To access the adjustment sliders of brightness and contrast. |
| 4 |  Menu | To launch the On-Screen Display (OSD) main menu. See Operating the monitor . |
| 5 |  Exit | To exit the Menu Launcher. |



Using the navigation keys


When the OSD main menu is active, move the joystick to configure the settings, following the navigation keys displayed below the OSD.





| | Joystick | Description |
|---|--|---|
| 1 |  Up | Use the Up direction to adjust (increase ranges) items in the OSD menu. |
| 2 |  Down | Use the Down direction to adjust (decrease ranges) items in the OSD menu. |
| 3 |  Left | For all first level in the Menu list, Left arrow will exit/close the OSD menu. |
| 4 |  Right | For all other levels except first level in the Menu list, Right arrow will go to the next level. |
| 5 |  OK | Press the joystick to confirm your selection. |








Accessing the menu system







 **NOTE:** If you change the settings and then either proceed to another menu or exit the OSD menu, the monitor automatically saves those changes. The changes are also saved if you change the settings and then wait for the OSD menu to disappear.

1. Select the  icon to launch the OSD and display the main menu.










2. Press the  and  directions to move between the setting options. As you move from one icon to another, the option is highlighted.
3. Press the  or  directions once to activate the highlighted option.

 **NOTE:** The directional buttons (and the OK button) displayed may differ according to the menu you've selected. Use available buttons to make your selection.

4. Press  and  directions to select the desired parameter.
5. Press  and then use the  and  directions, according to the indicators on the menu, to make your changes.
6. Select the  to return to the main menu.




| Icon | Menu and Submenus | Description |
|---|----------------------------|---|
|  | Brightness/Contrast | Use this menu to activate Brightness/Contrast adjustment. |
| | |   |
| | Brightness | <p>Brightness adjusts the luminance of the backlight.</p> <p>Press the  direction to increase the brightness and press the  direction to decrease the brightness (min. 0 / max. 100).</p> |
| | Contrast | <p>Adjust the Brightness first, and then adjust the Contrast only if further adjustment is necessary.</p> <p>Press the  direction to increase the contrast and press the  direction to decrease the contrast (min. 0 / max. 100).</p> <p>The Contrast function adjusts the degree of difference between darkness and lightness on the monitor screen.</p> |





Input Source

Selects between the different video signals that may be connected to your monitor.



USB-C 90W

Select the **USB-C 90W** input when you are using the USB-C connector. Press the joystick to confirm the selection.

DP

Select the **DP** input when you are using the DisplayPort (DP) connector. Press the joystick to confirm the selection.

HDMI

Select the **HDMI** input when you are using the HDMI connector. Press the joystick to confirm the selection.

Auto Select

Allows you to scan for available input sources. The default is **On**.

Auto Select for USB-C

Allows you to set Auto Select for USB-C to:

- **Prompt for Multiple Inputs:** Always displays the “Switch to USB-C Video Input” message for you to choose whether to switch or not.
- **Yes:** Always switches to USB-C video input (without asking) when the USB-C (C-C) cable is connected.
- **No:** Never automatically switches to USB-C video input when the USB-C (C-C) cable is connected.

Press the joystick to confirm the selection.

NOTE: The option is available only when Auto Select is on.



Rename Inputs Allows you to specify a preset input name for the selected input source. The preset options are **PC, PC 1, PC 2, Laptop, Laptop 1,** and **Laptop 2**. The default setting is **Off**.

NOTE: When you perform a rename for the USB-C input, the wattage value remains after the specified option, e.g., PC 1 ⚡ 90W.


NOTE: It is not applicable for the input names shown in the warning messages and Display Info.

Reset Input Source Resets your monitor input settings to the factory settings.




Color

Adjusts the color setting mode.



Preset Modes Allows you to choose from the list of preset color modes. Press the joystick to confirm the selection.




- **Standard:** Loads the monitor's default color settings. This is the default preset mode.
 - **Movie:** Loads color settings ideal for movies.
 - **Game:** Loads color settings ideal for most gaming applications.
 - **Warm:** Increases the color temperature. The screen appears warmer with a red/yellow tint.
 - **Cool:** Presents colors at higher color temperatures. The screen appears cooler with a blue tint.
 - **Custom Color:** Allows you to manually adjust the color settings. Move the joystick to adjust the R/G/B color values and create your own preset color mode.
-



Input Color Format

Allows you to set the video input mode to:

- **RGB:** Select this option if your monitor is connected to a computer or a media player that supports RGB output.
- **YCbCr:** Select this option if your media player supports only YCbCr output.



Hue

This feature can shift the color of the video image to green or purple. This is used to adjust the desired flesh tone color. Use ⤴ or ⤵ to adjust the hue from 0 to 100.

Press ⤴ to increase the green shade of the video image.

Press ⤵ to increase the purple shade of the video image.

NOTE: Hue adjustment is available only when you select Movie or Game preset mode.



Saturation This feature can adjust the color saturation of the video image. Use ⬆ or ⬇ to adjust the saturation from 0 to 100.

Press ⬆ to increase the monochrome appearance of the video image.


Press ⬇ to increase the colorful appearance of the video image.

NOTE: Saturation adjustment is available only when you select Movie or Game preset mode.

Reset Color Resets your monitor's color settings to the factory settings.



Display Use the **display** to adjust image.



Aspect Ratio Adjusts the image ratio to **16:9**, **4:3** or **5:4**.

Sharpness This feature can make the image look sharper or softer. Move the joystick to adjust the sharpness level from '0' to '100'.

Response Time Allows you to set the **Response Time** to **Normal** or **Fast**.

Dell Power Button Sync Allows you to control PC system power state from the monitor power button.


NOTE: This feature is only supported with Dell platform which has built-in DPBS function, and is only supported over USB-C interface.

Reset Display Resets all display settings to the factory preset values.







Audio



NOTE: The default status of the speaker is off and users will need to enable them manually via the OSD settings.

Volume

Volume adjusts the volume level of audio output.

Press the  direction to increase the volume and press the  direction to decrease the volume (min. 0% / max. 100%).

Speaker

Allows you to turn On or Off Speaker function.

Reset Audio


Resets all audio settings to the factory preset values.





Menu

Select this option to adjust the settings of the OSD, such as, the languages of the OSD, the amount of time the menu remains on screen and so on.



Language

Sets the OSD display to one of the eight languages (English, Spanish, French, German, Brazilian Portuguese, Russian, Simplified Chinese, or Japanese).

Transparency

Select this option to change the menu transparency by moving the joystick (min. 0 / max. 100).

Timer

Sets the length of time the OSD will remain active after the last time you pressed a button.

Move the joystick to adjust the slider in 1 second increments, from 5 to 60 seconds.

Lock

Controls user access to adjustments. User can select one of the following: Menu Buttons, Power Button, Menu + Power Buttons, Disable.


Reset Menu

Resets all OSD settings to the factory preset values.





Personalize




| | |
|------------------------------|--|
| Shortcut Key 1 | Allows you to choose a feature from Preset Modes , Brightness/Contrast , Input Source , Aspect Ratio , Volume , Speaker , or Display Info and set it as a shortcut key. |
| Shortcut Key 2 | |
| Shortcut Key 3 | |
| Power Button LED | Allows you to set the power LED indicator On or Off to save energy. |
| USB-C Charging 90W | The default setting is Off in Off Mode . Selecting On in Off Mode may automatically charge your notebook or mobile devices through the USB-C cable even when the monitor is in off mode. |
| Other USB Charging | Allows you to enable or disable USB Type-A (Downstream Ports) charging function during monitor standby mode. |
| Wake On Touch | The default setting is Off . Allows you to turn On or Off this feature in standby mode. |
| Reset Personalization | Resets all settings under the Personalize menu to the factory preset values. |





Others

Select this option to adjust the OSD settings, such as the DDC/CI, LCD conditioning, and so on.




Display Info

Displays the monitor's current settings.

DDC/CI


DDC/CI (Display Data Channel/Command Interface) allows you to adjust the monitor settings using software on your computer. You can disable this feature by selecting **Off**.

Enable this feature for best user experience and optimum performance of your monitor.



LCD Conditioning

Helps reduce minor cases of image retention. Depending on the degree of image retention, the program may take some time to run. You can enable this feature by selecting **On**.



Firmware Service Tag

Displays the firmware version of your monitor. Displays the service tag of your monitor. This string is required when you look for phone support, check your warranty status, update drivers on Dell's website, etc.

Self-Diagnostic


Allows you to check if your monitor is functioning properly.

Reset Others

Resets all settings under the **Others** menu to the factory preset values.

Factory Reset


Restore all preset values to the factory default settings. These are also the settings for ENERGY STAR® tests.



Menu and Power button lock


Prevents users to access or change OSD menu settings on the display.

By default, the Menu and Power button lock setting is disabled.



To access the lock menu, press and hold the Up or Down or Left or Right direction for four seconds. A lock menu appears at the bottom right corner of the display.


 **NOTE: The lock menu can be accessed using this method when the Menu and Power buttons are in unlocked state.**






To access the unlock menu, press and hold the Up or Down or Left or Right direction for four seconds. An unlock menu appears at the bottom right corner of the display.

 **NOTE: The unlock menu can be accessed when the Menu and Power buttons are in locked state.**





There are three lock options.


| | Menu | Description |
|---|---|--|
| 1 | Menu Buttons  | When Menu Buttons is selected, the OSD menu settings cannot be changed. All buttons are locked except Power button. |
| 2 | Power Button  | When Power Button is selected, the display cannot be turned off using the Power button. |
| 3 | Menu + Power Buttons  | When Menu + Power Buttons is selected, the OSD menu settings cannot be changed and the Power button is locked. |

NOTE: To access the Lock or Unlock menu – Press and hold the Up or Down or Left or Right direction for four seconds.

In the following scenarios, the  icon appears at the center of the display:

- When Up or Down or Left or Right direction are pressed. This indicates the OSD menu buttons are in lock state.
- When the Power button is pressed. This indicates the Power button is in lock state.
- When Up or Down or Left or Right direction or Power button are pressed. This indicates OSD menu buttons and the Power button is in lock state.


Unlocking the OSD menu and Power buttons:

1. Press and hold the Up or Down or Left or Right direction for four seconds. The unlock menu appears.
2. Select the unlock icon  to unlock the buttons on the display.




OSD warning messages

When the monitor does not support a particular resolution mode, you will see the following message:




This means that the monitor cannot synchronize with the signal that it is receiving from the computer. See monitor specifications for the Horizontal and Vertical frequency ranges addressable by this monitor. Recommended mode is **1920 x 1080**.

You will see the following message before the **DDC/CI** function is disabled:




When you adjust the **Brightness** level above the default level for the first time, the following message appears:



NOTE: If you select **Yes**, the message will not appear the next time you change the **Brightness** setting.


When you change the default setting of power saving features for the first time, such as **USB-C Charging** or **90W** or **Other USB Charging**, the following message appears:



NOTE: If you select **Yes** for either of the features mentioned above, the message will not appear the next time you change the settings of these features. When you perform a factory reset, the message will appear again.



When the monitor goes into Standby mode, the following message appears:




Activate the computer and wake up the monitor to gain access to the OSD. The OSD functions only in the normal operation mode. If you press the joystick during the Standby mode, the following message will appear depending on the selected input:



Activate the computer and the monitor to gain access to the OSD.


NOTE: The message may be slightly different according to the connected input signal.

If either USB-C, DisplayPort, or HDMI input is selected and the corresponding cable is not connected, the following message will appear:




or






or



NOTE: The message may be slightly different according to the connected input signal.

When the monitor is under DP/HDMI input and a USB-C (C-C) cable is connected to a notebook that supports DP Alternate Mode, if [Auto Select for USB-C](#) is enabled, the following message appears:




You will see the following message before the **Lock** function is activated:



NOTE: The message may be slightly different according to the selected settings.


When **Factory Reset** is selected, the following message appears:



When **Yes** is selected, the following message appears.



When **Yes** is selected, the following message appears.



See [Troubleshooting](#) for more information.



Setting the maximum resolution

NOTE: The steps may vary slightly depending on the version of Windows you have.

To set the maximum resolution for the monitor:

In Windows 8 and Windows 8.1:

1. Select the Desktop tile to switch to classic desktop.
2. Right-click on the desktop and click **Screen Resolution**.
3. If you have more than one monitor connected, ensure that you select **P2424HT**.
4. Click the **Screen Resolution** drop down list and select **1920 x 1080**.
5. Click **OK**.

In Windows 10 and Windows 11:

1. Right-click on the desktop and click **Display settings**.
2. If you have more than one monitor connected, ensure to select **P2424HT**.
3. Click the **Display Resolution** drop down list and select **1920 x 1080**.
4. Click **Keep changes**.

If you do not see **1920 x 1080** as an option, you must update your graphics driver to the latest version. Depending on your computer, complete one of the following procedures:

If you have a Dell desktop or laptop:

- Go to <https://www.dell.com/support>, enter your service tag, and download the latest driver for your graphics card.

If you are using a non-Dell computer (laptop or desktop):

- Go to the support site for your computer and download the latest graphic drivers.
- Go to your graphics card website and download the latest graphic drivers.



Troubleshooting


WARNING: Before you begin any of the procedures in this section, follow the [Safety instructions](#).

Self-Test


Your monitor provides a self-test feature that allows you to check if your monitor is functioning properly. If your monitor and computer are properly connected but the monitor screen remains dark, run the monitor self-test by performing the following steps:

1. Turn off both your computer and the monitor.
2. Disconnect all video cables from the monitor. This way, the computer doesn't have to be involved.
3. Turn on the monitor.

If the monitor cannot sense a video signal and is working correctly, the following message will appear:




or



or





NOTE: The message may be slightly different according to the connected input signal.

NOTE: While in self-test mode, the power LED remains white.

4. This box also appears during normal system operation, if the video cable becomes disconnected or damaged.
5. Turn Off your monitor and reconnect the video cable; then turn On both your computer and the monitor.

If your monitor screen remains blank after you use the previous procedure, check your video controller and computer, because your monitor is functioning properly.

Built-in diagnostics


Your monitor has a built-in diagnostic tool that helps you determine if any screen abnormality you experience is an inherent problem with your monitor, or with your computer and video card.

To run the built-in diagnostics:

1. Ensure that the screen is clean (no dust particles on the surface of the screen).
2. Press the Joystick button to launch the OSD Menu Launcher and move the Joystick up to select “ ” to open Main Menu.



3. Move the Joystick to select **Others > Self-Diagnostic** to initiate the self-diagnostic process.



4. When initiated, a gray screen appears. Inspect the screen for abnormalities.
5. Toggle the Joystick. The color of the screen changes to red. Inspect the screen for abnormalities.
6. Repeat step 5 to inspect the display in green, blue, black, white and text screens.
7. The test is complete when the text screen appears. To exit, toggle the Joystick again.

If you do not detect any screen abnormalities upon using the BID tool, the monitor is functioning properly. Please check the video card and computer.



Common problems

The following table contains general information about common monitor problems you might encounter and the possible solutions:

| Common Symptoms | What you experience | Possible Solutions |
|------------------------|---------------------------------------|---|
| No Video/Power LED off | No picture | <ul style="list-style-type: none">Ensure that the video cable connecting the monitor and the computer is properly connected and secure.• Verify that the power outlet is functioning properly using any other electrical equipment.• Ensure that the power button is pressed.• Ensure that the correct input source is selected via the Input Source menu. |
| No Video/Power LED on | No picture or no brightness | <ul style="list-style-type: none">• Increase brightness and contrast controls using the OSD.• Perform monitor self-test feature check.• Check for bent or broken pins in the video cable connector.• Run the built-in diagnostics.• Ensure that the correct input source is selected via the Input Source menu. |
| Poor Focus | Picture is fuzzy, blurry, or ghosting | <ul style="list-style-type: none">• Eliminate video extension cables.• Reset the monitor to Factory Settings (Factory Reset).• Change the video resolution to the correct aspect ratio. |
| Shaky/Jittery Video | Wavy picture or fine movement | <ul style="list-style-type: none">• Reset the monitor to Factory Settings (Factory Reset).• Check environmental factors.• Relocate the monitor and test in another room. |



| | | |
|---------------------------|-------------------------------|--|
| Missing Pixels | LCD screen has spots | <ul style="list-style-type: none"> • Cycle power On-Off. • Pixel that is permanently Off is a natural defect that can occur in LCD technology. • For more information on Dell Monitor Quality and Pixel Policy, see Dell Support site at: www.dell.com/pixelguidelines. |
| Stuck-on Pixels | LCD screen has bright spots | <ul style="list-style-type: none"> • Cycle power On-Off. • Pixel that is permanently off is a natural defect that can occur in LCD technology. • For more information on Dell Monitor Quality and Pixel Policy, see Dell Support site at: www.dell.com/pixelguidelines. |
| Brightness Problems | Picture too dim or too bright | <ul style="list-style-type: none"> • Reset the monitor to Factory Settings (Factory Reset). • Adjust brightness & contrast controls via OSD. |
| Geometric Distortion | Screen not centered correctly | <ul style="list-style-type: none"> • Reset the monitor to Factory Settings (Factory Reset). • Adjust horizontal & vertical controls via OSD. |
| Horizontal/Vertical Lines | Screen has one or more lines | <ul style="list-style-type: none"> • Reset the monitor to Factory Settings (Factory Reset). • Perform monitor self-test feature check and determine if these lines are also in self-test mode. • Check for bent or broken pins in the video cable connector. • Run the built-in diagnostics. |



| | | |
|--------------------------|-------------------------------------|---|
| Synchronization Problems | Screen is scrambled or appears torn | <ul style="list-style-type: none"> • Reset the monitor to Factory Settings (Factory Reset). • Perform monitor self-test feature check to determine if the scrambled screen appears in self-test mode. • Check for bent or broken pins in the video cable connector. • Restart the computer in the safe mode. |
| Safety Related Issues | Visible signs of smoke or sparks | <ul style="list-style-type: none"> • Do not perform any troubleshooting steps. • Contact Dell immediately. |
| Intermittent Problems | Monitor malfunctions on & off | <ul style="list-style-type: none"> • Ensure that the video cable connecting the monitor to the computer is connected properly and is secure. • Reset the monitor to Factory Settings (Factory Reset). • Perform monitor self-test feature check to determine if the intermittent problem occurs in self-test mode. |
| Missing Color | Picture missing color | <ul style="list-style-type: none"> • Perform monitor self-test feature check. • Ensure that the video cable connecting the monitor to the computer is connected properly and is secure. • Check for bent or broken pins in the video cable connector. |
| Wrong Color | Picture color not good | <ul style="list-style-type: none"> • Try different Preset Modes in Color settings OSD. Adjust R/G/B value in Custom Color in Color settings OSD. • Change the Input Color Format to RGB or YCbCr in the Color settings OSD. • Run the built-in diagnostics. |



| | | |
|---|--|---|
| Image retention from a static image left on the monitor for a long period of time | Faint shadow from the static image displayed appears on the screen | <ul style="list-style-type: none"> • Set the screen to turn off after a few minutes of screen idle time. These can be adjusted in Windows Power Options or Mac Energy Saver setting. • Alternatively, use a dynamically changing screensaver. |
|---|--|---|

Product specific problems

| Specific Symptoms | What you experience | Possible Solutions |
|--|--|---|
| Screen image is too small | Image is centered on screen, but does not fill entire viewing area | <ul style="list-style-type: none"> • Check the Aspect Ratio setting in the Display settings OSD. • Reset the monitor to Factory Settings (Factory Reset). |
| Cannot adjust the monitor with the joystick | OSD does not appear on the screen | <ul style="list-style-type: none"> • Turn Off the monitor, unplug the power cord, plug it back, and then turn On the monitor. • Check whether the OSD menu is locked. If yes, move and hold the joystick up/down/left/right for 4 seconds to unlock (for more information, see Menu and Power button lock). |
| No Input Signal when user controls are pressed | No picture, the LED light is white | <ul style="list-style-type: none"> • Check the signal source. Ensure the computer is not in Standby Mode by moving the mouse or pressing any key on the keyboard. • Check if the video cable is plugged in properly. Disconnect and reconnect the video cable if necessary. • Reset the computer or video player. |



| | | |
|---|---|--|
| The picture does not fill the entire screen | The picture cannot fill the height or width of the screen | <ul style="list-style-type: none"> • Due to different video formats (aspect ratio) of DVDs, the monitor may display in full screen. • Run the built-in diagnostics. |
| No video at HDMI/ DisplayPort/USB-C port | When connected to some dongle/ docking device at the port, there is no video when unplugging/plugging the cable from the notebook | <ul style="list-style-type: none"> • Unplug the HDMI/DisplayPort/ USB-C cable from dongle/ docking device, then plug the docking HDMI/DisplayPort/ USB-C cable to the notebook. |
| No network connection | Network dropped or intermittent | <ul style="list-style-type: none"> • Do not turn Off the monitor during network connection. |
| The LAN port is not functioning | OS setting or cable connection issue | <ul style="list-style-type: none"> • Ensure that the latest BIOS and drivers for your computer are installed on your computer. • Ensure that the RealTek Gigabit Ethernet Controller is installed in the Windows Device Manager. • If your BIOS Setup has a LAN/ GBE Enabled/Disabled option, make sure it is set to Enabled. • Ensure that the Ethernet cable is connected securely on the monitor and the hub/router/ firewall. • Check the status LED of the Ethernet cable to confirm connectivity. Re-connect both ends of the Ethernet cable if the LED is not lit. • First power off the computer and unplug the USB-C cable and the power cord from the monitor. Then, power on the computer and plug the power cord and the USB-C cable into the monitor. |



Touchscreen Problems

| Specific | What you experience | Possible Solutions |
|--|---|---|
| Touch report error | Touch function miss alignment or no touch function | <ul style="list-style-type: none"> • Use the Dell provided USB cable to connect your computer. • Make sure the power cable has a ground pin. • Unplug and replug the power cable from the power adapter to allow auto-recalibration of the touch module. • Make sure computer supports USB 2.0 or later. • If the display cannot be detected by the computer, power off/on the monitor or unplug and replug the USB cable. |
| Touchscreen non-responsive in standby mode | Touchscreen non-responsive in standby mode | <ol style="list-style-type: none"> 1. Access Device Manager, expand HID Interface Device under Human Device. 2. Right click HID- compliant device, click Properties and select the check-box to allow the device to wake the computer. |
| Windows 8, Windows 8.1 Windows 10 and Windows 11 Calibration | Cursor does not accurately follow your finger when you touch the screen | <ol style="list-style-type: none"> 1. Open Control Panel, open Hardware and Sound, and then open Tablet PC Settings. 2. Select Calibration. 3. Follow the instructions to recalibrate your screen |



Universal Serial Bus (USB) specific problems

| Common symptoms | What you experience | Possible Solutions |
|--|---|--|
| USB interface is not working | USB peripherals are not working | <ul style="list-style-type: none"> • Check that your monitor is turned On. • Reconnect the upstream cable to your computer. • Reconnect the USB peripherals (downstream connector). • Turn off the monitor and turn it on again. • Reboot the computer. • Certain USB devices such as portable hard drive require higher power source; connect the drive to the computer directly. |
| USB-C port does not supply power | USB peripherals can not be charged | <ul style="list-style-type: none"> • Check that the connected device is compliant with the USB-C specification. The USB-C port supports USB 3.2 Gen1 and an output of 90 W. • Check that you use the USB-C cable shipped with your monitor. |
| SuperSpeed USB 5 Gbps (USB 3.2 Gen1) interface is slow | SuperSpeed USB 5 Gbps (USB 3.2 Gen1) peripherals working slowly or not working at all | <ul style="list-style-type: none"> • Check that your computer is SuperSpeed USB 5 Gbps (USB 3.2 Gen1)-compatible. • Some computers have USB 3.2, USB 2.0, and USB 1.1 ports. Ensure that the correct USB port is used. • Reconnect the upstream cable to your computer. • Reconnect the USB peripherals (downstream connector). • Reboot the computer. |



Wireless USB peripherals stop working when a USB 3.2 device is plugged in

Wireless USB peripherals responding slowly or only working as the distance between itself and its receiver decreases

- Increase the distance between the USB 3.2 peripherals and the wireless USB receiver.
 - Position your wireless USB receiver as close as possible to the wireless USB peripherals.
 - Use a USB-extender cable to position the wireless USB receiver as far away as possible from the USB 3.2 port.
-



Regulatory information

FCC notices (U.S. Only) and other regulatory information

For FCC notices and other regulatory information, see the regulatory compliance website located at www.dell.com/regulatory_compliance.

EU product database for energy label and product information sheet

P2424HT: <https://eprel.ec.europa.eu/qr/1465328>

Contacting Dell

To contact Dell for sales, technical support, or customer service issues, see www.dell.com/contactdell.

NOTE: Availability varies by country and product, and some services may not be available in your country.

NOTE: If you do not have an active Internet connection, you can find contact information on your purchase invoice, packing slip, bill, or Dell product catalog.

