Dell USB-C Monitor P2423DE/P2723DE User's Guide



Monitor Model: P2423DE/P2723DE Regulatory Model: P2423DEc/P2723DEc

- NOTE: A NOTE indicates important information that helps you make better use of your computer.
- \bigtriangleup CAUTION: A CAUTION indicates potential damage to hardware or loss of data if instructions are not followed.
- MARNING: A WARNING indicates a potential for property damage, personal injury, or death.

Copyright © 2022 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. USB Type-C[®] and USB-C[®] are registered trademarks of USB Implementers Forum. Other trademarks may be trademarks of their respective owners.

2022 - 02

Rev. A00



Contents

Safety instructions
About your monitor7
Package contents
Product features
Identifying parts and controls
Front view
Back view
Bottom view
Monitor specifications
Resolution specifications
Supported video modes
Preset display modes
Physical characteristics
Environmental characteristics
Pin assignments
DisplayPort connector (in)
DisplayPort connector (out)
HDMI connector
Universal Serial Bus (USB) interface
RJ45 port (connector side)
Plug and play capability
LCD monitor quality and pixel policy
Ergonomics
Dell

Dell

Using the joystick control
Using the On-Screen Display (OSD) menu
Accessing the Menu Launcher
Using the navigation keys
Accessing the menu system
Menu and Power button lock
OSD warning messages
Setting the maximum resolution
Using the tilt, swivel, and vertical extension 80
Tilt, swivel
Vertical Extension
Rotating the monitor
Rotate clockwise
Rotate counterclockwise
Adjusting the rotation display settings of your system 83
Troubleshooting 84
Self-Test
Built-in diagnostics
Common problems
Universal Serial Bus (USB) specific problems 92
Regulatory information
FCC notices (U.S. Only) and other regulatory information94
EU product database for energy label and product information sheet
Contacting Dell

l

Dell

Safety instructions

Use the following safety guidelines to protect your monitor from potential damage and to ensure your personal safety. Unless otherwise noted, each procedure included in this document assumes that you have read the safety information that shipped with your monitor.

NOTE: Before using the monitor, read the safety information that is shipped with your monitor and printed on the product. Keep the documentation at a secure location for future reference.

MARNING: Use of controls, adjustments, or procedures other than those specified in this documentation may result in exposure to shock, electrical hazards, and/or mechanical hazards.

MARNING: The possible long-term effect of listening to audio at high volume through the headphones (on monitor that support it) may cause damage to your hearing ability.

- Place the monitor on a solid surface and handle it carefully. The screen is fragile and can be damaged if dropped or hit with a sharp object.
- Ensure that your monitor is electrically rated to operate with the AC power available in your location.
- Keep the monitor in room temperature. Excessive cold or hot conditions can have an adverse effect on the liquid crystal of the display.
- Connect the power cable from the monitor to a wall outlet that is near and accessible. See Connecting your monitor.
- $\cdot\,$ Do not place and use the monitor on a wet surface or near water.
- Do not subject the monitor to severe vibration or high impact conditions. For example, do not place the monitor inside a car trunk.
- $\cdot\,$ Unplug the monitor when it is going to be left unused for an extended period.
- $\cdot\,$ To avoid electric shock, do not attempt to remove any cover or touch the inside of the monitor.
- Read these instructions carefully. Keep this document for future reference. Follow all warnings and instructions marked on product.
- Certain monitors can be wall mounted using the VESA mount that is sold separately. Ensure to use the correct VESA specifications as mentioned in the wall mounting section of the *User's Guide*.

For information on safety instructions, see the *Safety*, *Environmental*, and *Regulatory Information* (*SERI*) document that is shipped with your monitor.



About your monitor

Package contents

The following table provides the list of components that are shipped with your monitor. If any component is missing, contact Dell. For more information, see Contacting Dell.



NOTE: Some items may be optional and may not ship with your monitor. Some features may not be available in certain countries.

Component image	Component description
	Display
	Stand riser
	Stand base
	Power cable (varies by country)



	DisplayPort to DisplayPort cable (1.8 meters)
0	Super speed USB 10 Gbps (USB 3.2 Gen2) Type-C to Type-C upstream cable (C-C cable) (1 meter)
0	Super speed USB 5 Gbps (USB 3.2 Gen1) Type-C to Type-A upstream cable (C-A cable) (1.8 meters)
/	Cable tie
	 Quick Setup Guide Safety, Environmental and Regulatory Information

(Dell

Product features

The Dell P2423DE/P2723DE monitor has an active matrix, Thin-Film Transistor (TFT), Liquid Crystal Display (LCD) and LED backlight. The monitor features include:

- P2423DE: 60.45 cm (23.8 in.) viewable area display (measured diagonally).
- P2723DE: 68.47 cm (27 in.) viewable area display (measured diagonally).
- $\cdot\,$ 2560 x 1440 resolution, with full-screen support for lower resolutions.
- · Color gamut of 99% sRGB (typical).
- · Digital connectivity with DisplayPort, USB-C and HDMI.
- Single USB-C to supply power (PD 90 W) to a compatible notebook while receiving video & data signal.
- Tilt, swivel, height, and rotate adjustment capabilities.
- Ultra-thin bezel minimizes the bezel gap in multi-monitor usage, enabling easier setup with an elegant viewing experience.
- Removable stand and Video Electronics Standards Association (VESA[™]) 100 mm mounting holes for flexible mounting solutions.
- Equipped with 1 USB-C upstream port and 4 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream ports.
- USB-C and RJ45 ports enable a single-cable, network-connected experience.
- Plug and play capability if supported by your system.
- On-Screen Display (OSD) adjustments for ease of set-up and screen optimization.
- · Power and joystick buttons lock.
- · Security lock slot.
- Stand lock.
- $\cdot\ \leq$ 0.3 W in Standby Mode.
- · Optimize eye comfort with a flicker-free screen and low blue light feature.
- The monitor use Low Blue Light panel and is in compliance with TUV Rheinland (Hardware Solution) at factory reset/default setting model (Preset mode: Standard).
- ▲ WARNING: The possible long-term effects of blue light emission from the monitor may cause damage to the eyes, which includes but is not limited to eye fatigue and digital eye strain. ComfortView Plus feature is designed to reduce the amount of blue light emitted from the monitor to optimize eye comfort.

Dell

Identifying parts and controls

Front view



Label	Description
1	Power LED indicator
	Solid white light indicates that the monitor is turned on and functioning normally. Blinking white light indicates that the monitor is in Standby Mode.



Back view



Back View with monitor stand

Label	Description	Use
1	VESA mounting holes (100 mm x 100 mm - behind attached VESA Cover)	Wall-mount the monitor using VESA- compatible wall mount kit (100 mm x 100 mm).
2	Regulatory label	Lists the regulatory approvals.
3	Stand release button	Releases the stand from the monitor.
4	Barcode, serial number, and Service Tag label	Contains monitor details and support information. Refer to this label if you need to contact Dell for technical support.
5	Power On/Off button	To turn the monitor on or off.
6	Joystick	Use to control the OSD menu. (For more Information, see Operating the monitor)
7	Cable-management slot	Use to organize cables by inserting them through the slot.



Bottom view



Bottom view without monitor stand

Label	Description	Use
1	Security lock slot (based on Kensington Security Slot)	Secure your monitor using a security lock (purchased separately) to prevent unauthorized movement of your monitor.
2	Power connector	Connect the power cable (shipped with your monitor).
3	HDMI port	Connect to your computer using a HDMI cable (purchased separately).
4	Stand lock	To lock the stand to the monitor using a M3 x 6 mm screw (screw not included).
5	DisplayPort (in)	Connect your computer with the DisplayPort cable (shipped with your monitor).
6	DisplayPort (out)	DisplayPort output for MST (multi-stream transport) capable monitor. To enable MST, see Connecting the monitor for DP Multi-Stream Transport (MST) function.
		NOTE: Remove the rubber plug when using DisplayPort out connector.



(dæli

7	USB-C upstream port	Connect the USB-C (C-C) or (C-A) cable that came with your monitor to the computer. This port supports USB Power Delivery, Data, and DisplayPort video signal. The SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-C port supports Alternate Mode DP1.4 with a maximum resolution of 2560 x 1440 at 60 Hz, PD 20 V/4.5 A, 15 V/3 A, 9 V/3 A, 5 V/3 A.
		NOTE: USB-C is not supported on versions of Windows prior to Windows 10.
8	SuperSpeed USB 5	Connect your USB device.*
	Gbps (USB 3.2 Gen1) Type-A downstream port (4)	NOTE: To use these ports, you must connect the USB-C (C-C) or (C-A) cable (shipped with your monitor) to the USB-C upstream port on the monitor and to your computer.
9	RJ45 port	Connect the Internet. You can surf Internet via RJ45 only after you have connected the USB-C (C-C) or (C-A) cable (shipped with your monitor) from the computer to the monitor.

*To avoid signal interference, when a wireless USB device has been connected to a USB downstream port, it is NOT recommended to connect any other USB devices to the adjacent port(s).

DELL

Monitor specifications

Model	P2423DE	P2723DE
Screen type	Active matrix - TFT LCD	
Panel type	In-Plane Switching Technology	
Aspect ratio	16:9	
Viewable image		
Diagonal	604.50 mm (23.80 in.)	684.70 mm (26.96 in.)
Horizontal, Active Area	526.85 mm (20.74 in.)	596.74 mm (23.49 in.)
Vertical, Active Area	296.35 mm (11.67 in.)	335.66 mm (13.21 in.)
Area	156132.00 mm ² (242.01 in. ²)	200301.75 mm ² (310.47 in. ²)
Native resolution and	2560 x 1440 at 60 Hz	
refresh rate		
Pixel pitch	0.2058 mm x 0.2058 mm	0.2331 mm x 0.2331 mm
Pixel per inch (PPI)	123	109
Viewing angle		
Horizontal	178° (typical)	
Vertical	178° (typical)	
Luminance output	300 cd/m² (typical)	350 cd/m² (typical)
Contrast ratio	1000 to 1 (typical)	
Display screen coating	Anti-glare treatment of the f coating	ront polarizer (3H) hard
Backlight	LED edgelight system	
Response time	5 ms (Fast mode) 8 ms (Normal mode)	
Color depth	16.7 million colors (8 bit)	
Color gamut	sRGB 99% (typical)	



Connectivity	\cdot 1 x HDMI port version 1.4 (HDCP 1.4)
	• 1 x DisplayPort version 1.4 (HDCP 1.4)	
	• 1 x DisplayPort (Out) with MST (HDCP 1.4)	
	 1 x USB-C upstream port (Alternate mode with DisplayPort 1.4, Power Delivery PD up to 90 W)* 	
	 4 x SuperSpeed USB 5 Gb downstream port 	ps (USB 3.2 Gen1)
	• 1 x RJ45 port	
Bezel width (edge of m	onitor to active area)	
Тор	5.42 mm	7.37 mm
Left/Right	5.48 mm	7.43 mm
Bottom	16.72 mm	17.77 mm
Adjustability	·	
Height adjustable stand	150 mm	
Tilt	-5° to 21°	
Swivel	-45° to 45°	
Pivot	-90° to 90°	
Cable management	Yes	
Dell Display Manager compatibility	Easy Arrange and other key	features
Security	Security lock slot (cable lock optional purchase)	

*DisplayPort and USB-C (Alternate mode with DisplayPort 1.4): HBR3 is supported.

DELL

Resolution specifications

Model	P2423DE/P2723DE
Horizontal scan range	29 kHz to 113 kHz
Vertical scan range	49 Hz to 75 Hz (automatic)
Maximum preset resolution	2560 x 1440 @ 60 Hz

Supported video modes

Model	P2423DE/P2723DE
Video display capabilities (HDMI & DisplayPort & USB-C DP alternate mode)	480p, 576p, 720p, 1080i(HDMI), 1080p, 1440p



Preset display modes

Display Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Pixel Clock (MHz)	Sync Polarity (Horizontal / Vertical)
IBM, 720 x 400	31.50	70.10	28.30	-/+
VESA, 640 x 480	31.50	59.90	25.20	-/-
VESA, 640 x 480	37.50	75.00	31.50	-/-
VESA, 800 x 600	37.90	60.30	40.00	+/+
VESA, 800 x 600	46.90	75.00	49.50	+/+
VESA, 1024 x 768	48.40	60.00	65.00	-/-
VESA, 1024 x 768	60.00	75.00	78.80	+/+
VESA, 1152 x 864	67.50	75.00	108.00	+/+
VESA, 1280 x 768	47.80	59.90	79.50	-/+
VESA, 1280 x 1024	64.00	60.00	108.00	+/+
VESA, 1280 x 1024	79.90	75.00	135.00	+/+
VESA, 1600 x 1200	75.00	60.00	162.00	+/+
VESA, 1680 x 1050	65.30	60.00	146.30	-/+
CTA, 1920 x 1080	67.50	60.00	148.50	+/+
VESA, 1920 x 1200	74.60	59.90	193.30	-/+
VESA, 2048 x 1080	66.60	60.00	147.20	+/-
VESA, 2560 x 1440	88.80	60.00	241.50	+/-

DP Multi-Stream Transport (MST) modes

MST Source Monitor	Maximum number of external monitor that can be supported
	2560 x 1440 @ 60 Hz
2560 x 1440 @ 60 Hz	• 1 (via USB-C input)
	・ 3 (via DisplayPort input)



NOTE: Maximum external monitor resolution supported is 2560 x 1440 60Hz only (HBR3).

DELL

Electrical specifications

Model	P2423DE	P2723DE	
Video input signals	 HDMI 1.4/DisplayPort 1.4*, 600 mV for each differential line, 100 ohm input impedance per differential pair 		
	 USB-C (with DP alternate mode) signal input support 		
AC input voltage/ frequency/current	100 VAC to 240 VAC / 50 Hz or 60 Hz ± 3 Hz / 2 A (typical)	100 VAC to 240 VAC / 50 Hz or 60 Hz ± 3 Hz / 2 A (typical)	
Inrush current	 120 V: 30 A (Max.) at 0°C (cold start) 240 V: 60 A (Max.) at 0°C (cold start) 		
Power consumption	 0.3 W (Off mode)¹ 0.3 W (Standby Mode)¹ 20 W (On mode)¹ 170 W (Max.)² 17.5 W (Pon)³ 56.5 kWh (TEC) 	 0.3 W (Off mode)¹ 0.3 W (Standby Mode)¹ 26 W (On mode)¹ 175 W (Max.)² 19.94 W (Pon)³ 63.98 kWh (TEC) 	

*HBR3/DisplayPort 1.4 is supported.

¹ As defined in EU 2019/2021 and EU 2019/2013.

 $^{\rm 2}$ Max brightness and contrast setting with maximum power loading on all USB ports.

³ Pon: Power consumption of On Mode as defined in Energy Star 8.0 version. TEC: Total energy consumption in kWh as defined in Energy Star 8.0 version.

This document is informational only and reflects laboratory performance. Your product may perform differently, depending on the software, components and peripherals you ordered and shall have no obligation to update such information.

Accordingly, the customer should not rely upon this information in making decisions about electrical tolerances or otherwise. No warranty as to accuracy or completeness is expressed or implied.





This product qualifies for ENERGY STAR in the factory default settings which can be restored by "Factory Reset" function in the OSD menu. Changing the factory default settings or enabling other features may increase power consumption that could exceed the ENERGY STAR specified limit.



Physical characteristics

Model	P2423DE	P2723DE	
Signal cable type	• Digital: DisplayPort, 20 pins		
	• Digital: HDMI, 19 pins (cable not included)		
	 Universal Series Bus: T 	ype-C, 24 pins	
NOTE: Dell monitors are designed to work optimally with the video cables that are shipped with your monitor. As Dell does not have control over the different cable suppliers in the market, the type of material, connector and process used to manufacture these cables, Dell does not guarantee video performance on cables that are not shipped with your Dell monitor.			
Dimensions (with stand)	1		
Height (extended)	496.11 mm (19.53 in.)	535.20 mm (21.07 in.)	
Height (compressed)	364.00 mm (14.33 in.)	385.20 mm (15.17 in.)	
Width	537.80 mm (21.17 in.)	611.60 mm (24.08 in.)	
Depth	179.57 mm (7.07 in.)	190.10 mm (7.48 in.)	
Dimensions (without stand))		
Height	318.50 mm (12.54 in.)	360.80 mm (14.20 in.)	
Width	537.80 mm (21.17 in.)	611.60 mm (24.08 in.)	
Depth	52.15 mm (2.05 in.)	52.18 mm (2.05 in.)	
Stand dimensions	`		
Height (extended)	410.80 mm (16.17 in.)	428.30 mm (16.86 in.)	
Height (compressed)	364.00 mm (14.33 in.)	381.50 mm (15.02 in.)	
Width	245.00 mm (9.65 in.)	268.00 mm (10.55 in.)	
Depth	179.57 mm (7.07 in.)	190.10 mm (7.48 in.)	
Base	245.00 x 173.00 mm (9.65 in. x 6.81 in.)	268.00 x 185.00 mm (10.55 in. x 7.28 in.)	
Weight			
Weight with packaging	7.97 kg (17.57 lb)	9.78 kg (21.56 lb)	
Weight with stand assembly and cables	5.98 kg (13.18 lb)	7.34 kg (16.18 lb)	



Weight without stand assembly (For wall mount or VESA mount considerations - no cables)	3.92 kg (8.64 lb)	5.07 kg (11.18 lb)
Weight of stand assembly	1.63 kg (3.59 lb)	1.84 kg (4.06 lb)
Front-frame gloss	Black frame 2-4 gloss units	

(DELL)

Environmental characteristics

Model	P2423DE	P2723DE	
Compliant Standards			
• ENERGY STAF	ENERGY STAR certified monitor.		
・ EPEAT registe	red where applicable. EPEAT regi	stration varies by country. See	
www.epeat.r	net for registration status by cour	ntry.	
 RoHS-complia 	ant.		
 TCO Certified 	& TCO Certified Edge.		
・BFR/PVC free	e monitor (excluding external cabl	es).	
• Meets NFPA S	99 leakage current requirements.		
 Arsenic-free g 	lass and Mercury-free for the par	nel only.	
Temperature			
Operating	0°C to 40°C (32°F to 104°F)		
Non-operating	• Storage: -20°C to 60°C (-4°F to 140°F)		
	 Shipping: -20°C to 60°C (-4°F to 140°F) 		
Humidity			
Operating	10% to 80% (non-condensing)		
Non-operating	 Storage 5% to 90% (non-condensing) 		
	Shipping 5% to 90% (non-condensing)		
Altitude			
Operating	5,000 m (16,400 ft)		
(maximum)			
Non-operating	ting 12,192 m (40,000 ft)		
(maximum)			
Thermal	• 581.40 BTU/hour (Maximum)	· 598.50 BTU∕hour (Maximum)	
dissipation	· 68.40 BTU∕hour (On Mode)	· 88.92 BTU∕hour (On Mode)	



Pin assignments

DisplayPort connector (in)



Pin number	20-pin side of the connected signal cable
1	ML3 (n)
2	GND
3	ML3 (p)
4	ML2 (n)
5	GND
6	ML2 (p)
7	ML1 (n)
8	GND
9	ML1 (p)
10	ML0 (n)
11	GND
12	ML0 (p)
13	GND
14	GND
15	AUX (p)
16	GND
17	AUX (n)
18	Hot Plug Detect
19	Re-PWR
20	+3.3 V DP_PWR

DisplayPort connector (out)



Pin number	20-pin side of the connected signal cable
1	ML0 (p)
2	GND
3	ML0 (n)
4	ML1 (p)
5	GND
6	ML1 (n)
7	ML2 (p)
8	GND
9	ML2 (n)
10	ML3 (p)
11	GND
12	ML3 (n)
13	CONFIG1
14	CONFIG2
15	AUX CH (p)
16	GND
17	AUX CH (n)
18	Hot Plug Detect
19	Return
20	DP_PWR

HDMI connector



Pin number	19-pin side of the connected signal cable	
1	TMDS DATA 2+	
2	TMDS DATA 2 SHIELD	
3	TMDS DATA 2-	
4	TMDS DATA 1+	
5	TMDS DATA 1 SHIELD	
6	TMDS DATA 1-	
7	TMDS DATA 0+	
8	TMDS DATA 0 SHIELD	
9	TMDS DATA 0-	
10	TMDS CLOCK+	
11	TMDS CLOCK SHIELD	
12	TMDS CLOCK-	
13	CEC	
14	Reserved (N.C. on device)	
15	DDC CLOCK (SCL)	
16	DDC DATA (SDA)	
17	DDC/CEC Ground	
18	+5 V POWER	
19	HOT PLUG DETECT	

Universal Serial Bus (USB) interface

This section gives you information about the USB ports that are available on the monitor.

SuperSpeed USB 5 Gbps (USB 3.2 Gen1)

Transfer speed	Data rate	Maximum power supported (each port)
SuperSpeed	5 Gbps	4.5 W
High speed	480 Mbps	4.5 W
Full speed	12 Mbps	4.5 W

USB-C

USB-C	Description
Video	DisplayPort 1.4*
Data	SuperSpeed USB 5 Gbps (USB 3.2 Gen1)
Power Delivery (PD)	Up to 90 W

*HBR3 is supported.



USB downstream connector



Pin number	9-pin side of the connector
1	VCC
2	D-
3	D+
4	GND
5	SSRX-
6	SSRX+
7	GND
8	SSTX-
9	SSTX+

DELL

USB-C connector



Pin number	er Signal name Pin number		Signal name
A1	A1 GND		GND
A2	A2 TX1+ B2		TX2+
A3	TX1-	B3	TX2-
A4	VBUS	B4	VBUS
A5	CC1	B5	CC2
A6	D+	B6	D+
A7	D-	B7	D-
A8	SBU1	B8	SBU1
A9	VBUS B9		VBUS
A10	RX2-	B10	RX1-
A11	RX2+	B11	RX1+
A12	GND	B12	GND

USB ports

- · 1 USB-C upstream bottom
- 4 SuperSpeed USB 5 Gbps (USB 3.2 Gen1) Type-A downstream bottom



NOTE: The USB ports on the monitor work only when the monitor is turned On or in power save mode. If you turn Off the monitor and then turn it On, the attached peripherals may take a few seconds to resume normal functionality.

RJ45 port (connector side)



8 D. 75 <u>Di Corre</u> Ci Corre 0.0521000Т

Pin number	Signal		
1	СТ		
2	TD1+		
3	TD1-		
4	TD2+		
5	TD2-		
6	TD3+		
7	TD3-		
8	TD4+		
9	TD4-		
10	GND		
11	GREEN		
12	GREEN		
13	GREEN_AMBER		
14	GREEN_AMBER		

DELL

Driver installation

Install the Realtek USB GBE Ethernet Controller Driver available for your system. This is available for download at **www.dell.com/support** under the "Driver and download" section.

Network (RJ45) data rate via USB-C max speed is 1000 Mbps.



NOTE: This LAN port is 1000Base-T IEEE 802.3az compliant. supporting Mac Address (Printed on model label) Pass-thru (MAPT), Wake-on-LAN (WOL) from standby mode (S3 only) and UEFI* PXE Boot function [UEFI PXE Boot is not supported on Dell Desktop PC's (except for OptiPlex 7090/3090 Ultra Desktop)], these 3 features depend on BIOS settings and version of the OS. Functionality may vary with Non Dell PC's.

*UEEL stands for Unified Extensible Firmware Interface

RJ45 connector LED status





Label	LED	Color	Description
1	Left LED	Green	Link/Activity indicator:
			• Blinking - Activity on the port.
			 Green On - Link is being established.
			• Off - Link is not established.
2	Right LED	Amber or Green	Speed indicator:
			• Amber On - 1000 Mbps
			• Green On - 100 Mbps
			• Off - 10 Mbps



NOTE: The RJ45 cable is non in-box standard accessory.

Plug and play capability

You can install the monitor in any Plug and Play-compatible system. The monitor automatically provides the computer system with its Extended Display Identification Data (EDID) using Display Data Channel (DDC) protocols so that the system can configure itself and optimize the monitor settings. Most monitor installations are automatic; you can select different settings if desired. For more information about changing the monitor settings, see Operating the monitor.

LCD monitor quality and pixel policy

During the LCD Monitor manufacturing process, it is not uncommon for one or more pixels to become fixed in an unchanging state which are hard to see and do not affect the display quality or usability. For more information on Dell Monitor Quality and Pixel Policy, see Dell Support site at www.dell.com/pixelguidelines.

Ergonomics



\wedge CAUTION: Improper or prolonged usage of keyboard may result in injury.

\wedge CAUTION: Viewing the monitor screen for extended periods of time may result in eye strain.

For comfort and efficiency, observe the following guidelines when setting up and using your computer workstation:

- Position your computer so that the monitor and keyboard are directly in front of you as you work. Special shelves are commercially available to help you correctly position your keyboard.
- To reduce the risk of eye strain and neck, arm, back, or shoulder pain from using the monitor for long period, we recommend you to:
 - 1. Set the distance of the screen between 20 in. to 28 in. (50 cm 70 cm) from your eyes.
 - 2. Blink frequently to moisten your eyes or wet your eyes with water after prolonged usage of the monitor.
 - **3.** Take regular and frequent breaks for 20 minutes every two hours.
 - 4. Look away from your monitor and gaze at a distant object at 20 feet away for at least 20 seconds during the breaks.
 - 5. Perform stretches to relieve tension in the neck, arm, back, and shoulders during the breaks.



- Ensure that the monitor screen is at eye level or slightly lower when you are sitting in front of the monitor.
- · Adjust the tilt of the monitor, its contrast, and brightness settings.
- Adjust the ambient lighting around you (such as overhead lights, desk lamps, and the curtains or blinds on nearby windows) to minimize reflections and glare on the monitor screen.
- Use a chair that provides good lower-back support.
- Keep your forearms horizontal with your wrists in a neutral, comfortable position while using the keyboard or mouse.
- · Always leave space to rest your hands while using the keyboard or mouse.
- · Let your upper arms rest naturally on both sides.
- Ensure that your feet are resting flat on the floor.
- When sitting, ensure that the weight of your legs is on your feet and not on the front portion of your seat. Adjust your chair's height or use a footrest if necessary to maintain a proper posture.
- Vary your work activities. Try to organize your work so that you do not have to sit and work for extended periods of time. Try to stand or get up and walk around at regular intervals.
- Keep the area under your desk clear of obstructions and cables or power cords that may interfere with comfortable seating or present a potential trip hazard.



DELL

Handling and moving your display

To ensure that the monitor is handled safely when lifting or moving it, observe the following guidelines:

- Before moving or lifting the monitor, turn off your computer and the monitor.
- · Disconnect all cables from the monitor.
- Place the monitor in the original box with the original packing materials.
- Hold the bottom edge and the side of the monitor firmly without applying excessive pressure when lifting or moving the monitor.



• When lifting or moving the monitor, ensure that the screen is facing away from you. Do not press on the display area to avoid any scratches or damage.



- $\cdot\,$ When transporting the monitor, avoid any sudden shock or vibration to it.
- When lifting or moving the monitor, do not turn the monitor upside down while holding the stand base or stand riser. It may result in accidental damage to the monitor or cause personal injury.





Maintenance guidelines

Cleaning your monitor

- A WARNING: Before cleaning the monitor, unplug the monitor power cable from the electrical outlet.
- CAUTION: Read and follow the Safety instructions before cleaning the monitor.

A WARNING: Before cleaning the monitor, unplug the monitor power cable from the electrical outlet.

For best practices, follow the instructions in the list below when unpacking, cleaning, or handling your monitor:

- To clean the Dell monitor screen, lightly dampen a soft, clean cloth with water. If possible, use a special screen-cleaning tissue or solution suitable for the Dell monitor screen.
- CAUTION: Do not use detergents or other chemicals such as benzene, thinner, ammonia, abrasive cleaners, or compressed air.
- △ CAUTION: Using chemicals for cleaning may cause changes in the appearance of the monitor, such as color fading, milky film on the monitor, deformation, uneven dark shade, and peeling of screen area.
- WARNING: Do not spray the cleaning solution or even water directly on the surface of the monitor. Doing so will allow liquids to accumulate at the bottom of the display panel and corrode the electronics resulting in permanent damage. Instead, apply the cleaning solution or water to a soft cloth and then clean the monitor.



NOTE: Monitor damage due to improper cleaning methods and the use of benzene, thinner, ammonia, abrasive cleaners, alcohol, compressed air, detergent of any kind will lead to a Customer Induced Damage (CID). CID is not covered under the standard Dell warranty.

- If you notice white powder when you unpack your monitor, wipe it off with a cloth.
- Handle your monitor with care as a dark-colored monitor may get scratched and show white scuff marks more than a light-colored monitor.
- To help maintain the best image quality on your monitor, use a dynamically changing screen saver and turn off your monitor when not in use.


Setting up the monitor

Attaching the stand



NOTE: The stand is not installed at the factory when shipped.

NOTE: The following instructions are applicable only for the stand that was shipped with your monitor. If you are attaching a stand that you purchased from any other source, follow the setup instructions that were included with the stand.

To attach the monitor stand:

- **1.** Follow the instructions on the flaps of carton to remove the stand from the top cushion that secures it.
- 2. Remove the stand base and stand riser from the packaging cushion.



NOTE: The graphics are used for the purpose of illustration only. The appearance of the package cushion may vary.

- **3.** Insert the stand base blocks fully into the stand slot.
- 4. Lift the screw handle and turn the screw clockwise.
- 5. After fully tightening the screw, fold the screw handle flat within the recess.



6. Lift the cover, as shown, to access the VESA area for stand assembly.



NOTE: Before attaching the stand assembly to the display, ensure that the front plate flap is opened to allow space for assembly.

7. Attach the stand assembly to the display.

a. Fit the two tabs on the upper part of the stand to the groove on the back of the display.

b. Press the stand down till it snaps into place.





8. Hold the stand riser and lift the monitor carefully, then place it on a flat surface.





9. Remove the cover from the monitor.



Connecting your monitor

- MARNING: Before you begin any of the procedures in this section. follow the Safety instructions.
- NOTE: Dell monitors are designed to work optimally with Dell supplied inbox cables. Dell does not guarantee the video guality and performance if non-Dell cables are used.

NOTE: Route the cables through the cable-management slot before connecting them.

- NOTE: Do not connect all cables to the computer at the same time.
- NOTE: The images are for the purpose of illustration only. The appearance of the computer may vary.

To connect your monitor to the computer:

- **1.** Turn off your computer and disconnect the power cable.
- 2. Route the power cable through the cable-management slot on the stand and then connect it to the monitor.



3. Connect the DisplayPort, HDMI, USB-C (C-C), or USB-C (C-A) cable from your monitor to the computer.

DEL

Connecting the DisplayPort (DisplayPort to DisplayPort) cable



Connecting the USB-C (C-A) cable



Connecting the USB-C (C-C) cable





NOTE: Use the USB-C (C-C) cable shipped with monitor only.

- This port supports DisplayPort Alternate Mode (DP1.4 standard only).
- The USB-C power delivery compliant port (PD Version 3.0) delivers up to 90 W of power.
- If your notebook requires more than 90 W to operate and the battery is drained, it may not be powered up or charged with the USB PD port of this monitor.



Connecting the HDMI cable (optional)



Connecting the monitor for DP Multi-Stream Transport (MST) function



- NOTE: This monitor supports the DP MST feature. To make use of this feature, your PC Graphics Card must be certified to DP1.4 with MST option.
- NOTE: Remove the rubber plug when using DP out connector.

Connecting the monitor for USB-C Multi-Stream Transport (MST) function



DELL

NOTE: The maximum number of supported monitors via MST is subjected to the bandwidth of the USB-C source.

NOTE: Remove the rubber plug when using the DP out connector.

Connecting the RJ45 cable (optional)







Dell Power Button Sync (DPBS)

Your monitor is designed with Dell Power Button Sync (DPBS) feature to allow you to control PC system power state from the monitor power button. This feature is only supported with Dell platform which has built-in DPBS function, and is only supported over USB-C interface.



To make sure the DPBS function works for the first time, perform the following steps on the DPBS supported platform in the **Control Panel** first.

- NOTE: DPBS only supports the USB-C upstream port.
 - 1. Go to Control Panel.





2. Select Hardware and Sound, followed by Power Options.



3. Go to System Settings.

 - States can be accessed as a set of the s	- 1 - 1 1711 (11)70
Anne alternation	
G	
G	
Freezen	
 Construction Statement Construction Construction	
	_



4. In the drop-down menu of When I press the power button, there are a few options for selection, namely Do nothing/Sleep/Hibernate/Shut down. You can select Sleep/Hibernate/Shut down.



NOTE: Do not select "Do nothing", otherwise the monitor power button will not be able to sync with PC system power state.

Connecting the monitor for DPBS for the first time



For the first time setting up the DPBS function:

- 1. Make sure both the PC and the monitor are OFF.
- 2. Press the monitor power button to turn ON the monitor.
- 3. Connect the USB-C cable from the PC to the monitor.
- **4.** Both the monitor and PC will turn ON normally except Dell Optiplex 7090/3090 Ultra platform.
- 5. When you connect the Dell Optiplex 7090/3090 Ultra platform, you may see both the monitor and PC will turn ON momentarily. Wait for a while (approximately 6 seconds) and both the PC and monitor will turn OFF. When you press either the monitor power button or PC power button, both the PC and monitor will turn ON. The PC system power state is in sync with the monitor power button.
- NOTE: When the monitor and PC are both at power OFF state for the first time, it is recommended that you turn ON the monitor first, then connect the USB-C cable from the PC to the monitor.
- ▶ NOTE: You can power the Dell PC* Ultra platform using its DC adaptor jack. Alternatively, you can power the Dell PC* Ultra platform using the monitor's USB-C cable via Power Delivery (PD); please set USB-C Charging ♦ 90W to On in Off Mode.

*Ensure to check the Dell PC for DPBS supportability.

Using DPBS function Waking on the USB-C cable

When you connect the USB-C cable, the Monitor/PC state is as follows:



*Not all Dell PC systems support to wake up the platform via the monitor.

*After connect the USB-C cable, tap on Keyboard or moving the mouse for the system to continue its boot up process when necessary.

When you press the monitor power button or PC power button, the Monitor/PC state is as follows:



DELI

 When the monitor and the PC power state are both ON, press and hold the monitor power button for 4 seconds, the screen prompt will ask if you would like to shut down the PC.





• When the monitor and the PC power state are both ON, **press and hold the monitor power button for 10 seconds**, the PC will shut down.





DEL

Connecting the monitor for USB-C Multi-Stream Transport (MST) function

A PC is connected to two monitors in an initial OFF power state, and the PC system power state is in sync with Monitor 1 power button. When you press Monitor 1 or PC power button, both Monitor 1 and PC turns ON. Meanwhile, Monitor 2 will remain OFF. You need to manually press the power button on Monitor 2 to turn it ON.



Similarly, a PC is connected to two monitors in an initial ON power state, and the PC system power state is in sync with Monitor 1 power button. When you press Monitor 1 or PC power button, both Monitor 1 and PC turns OFF. Meanwhile, Monitor 2 will be in Standby mode. You need to manually press the power button on Monitor 2 to turn it OFF.





DEL

Connecting the monitor for USB-C

The Dell PC* Ultra platform has two USB-C ports, so both Monitor 1 and Monitor 2 power state can sync with the PC.

When the PC and two monitors are in an initial ON power state, pressing the power button on Monitor 1 or Monitor 2 will turn OFF the PC, Monitor 1, and Monitor 2.

*Ensure to check the Dell PC for DPBS supportability.

NOTE: DPBS only supports the USB-C upstream port.



DELL

Ensure to set **USB-C Charging** rightarrow **90W** to **On in Off Mode**. When the PC and two monitors are in an initial OFF power state, pressing the power button on Monitor 1 or Monitor 2 will turn ON the PC, Monitor 1, and Monitor 2.



DEL

Organizing cables



After attaching all necessary cables to your monitor and computer, (See Connecting your monitor for cable attachment,) organize all cables as shown above.

Securing your monitor using Kensington lock (optional)

The security lock slot is located at the bottom of the monitor. (see Security lock slot). Secure your monitor to a table using the Kensington security lock.

For more information on using the Kensington lock (sold separately), see the documentation that is shipped with the lock.



NOTE: The image is for the purpose of illustration only. The appearance of the lock may vary.

Removing the monitor stand

- NOTE: To prevent scratches on the LCD screen when removing the stand, ensure that the monitor is placed on a soft surface and handle it carefully.
- NOTE: The following steps are specifically for removing the stand that is shipped with your monitor. If you are removing a stand that you purchased from any other source, follow the setup instructions that are included with the stand.

To remove the stand:

- **1.** Place the monitor on a soft cloth or cushion.
- **2.** Press and hold the stand release button.
- **3.** Lift the stand up and away from the monitor.



VESA wall mounting (optional)



(Screw dimension: M4 x 10 mm).

See the documentation that shipped with the VESA-compatible wall mounting kit.

- 1. Place the display on a soft cloth or cushion at the edge of the desk.
- 2. Remove the stand. See Removing the monitor stand.
- **3.** Remove the four screws that secure the display back cover.
- 4. Install the mounting bracket from the wall mounting kit to the display.
- **5.** To mount the monitor on the wall, see the documentation that shipped with the wall mounting kit.
- NOTE: For use only with UL or CSA or GS-listed wall mount bracket with minimum weight/load bearing capacity of 15.68 kg (P2423DE) / 20.28 kg (P2723DE).

DEL

Operating the monitor

Power on the monitor

Press the Power button to turn On the monitor.



Using the joystick control

Use the joystick control on the rear of the monitor to make On-Screen Display (OSD) adjustments.



- **1.** Press the joystick to launch the Menu Launcher.
- 2. Move the joystick up/down/left/right to toggle between options.
- 3. Press the joystick again to confirm the selection.



Using the On-Screen Display (OSD) menu

Accessing the Menu Launcher

When you toggle or press the joystick, the Menu Launcher appears to let you access the OSD main menu and shortcut functions.

To select a function, move the joystick.



The following table describes the Menu Launcher functions:

	Joystick	Description
1	⊛ Shortcut key∕ Input Source	To choose an input source from the list of video signals that may be connected to your monitor.
2	⊛ Shortcut key∕ Preset Modes	To choose a preferred color mode from the list of preset modes.
3	Shortcut key/ Brightness/Contrast	To access the adjustment sliders of brightness and contrast.
4	li) Menu	To launch the On-Screen Display (OSD) main menu. See Operating the monitor.
5	⊗ OK	To exit the Menu Launcher.

 \bigcirc

DEL

Using the navigation keys

When the OSD main menu is active, move the joystick to configure the settings, following the navigation keys displayed below the OSD.



	Joystick	Description
1	Op Up	Use the Up direction to adjust (increase ranges) items in the OSD menu.
2	Down	Use the Down direction to adjust (decrease ranges) items in the OSD menu.
3	() Left	For all first level in the Menu list, Left arrow will exit/ close the OSD menu.
4) Right	For all other levels except first level in the Menu list, Right arrow will go to the next level.
5	<mark>О</mark> к	Press the joystick to confirm your selection.

Accessing the menu system

NOTE: If you change the settings and then either proceed to another menu or exit the OSD menu, the monitor automatically saves those changes. The changes are also saved if you change the settings and then wait for the OSD menu to disappear.

1. Select the (\square) icon to launch the OSD and display the main menu.



- 2. Press the O and O directions to move between the setting options. As you move from one icon to another, the option is highlighted.
- **3.** Press the \bigcirc or \oslash directions once to activate the highlighted option.
- NOTE: NOTE: The directional buttons (and the OK button) displayed may differ according to the menu you've selected. Use available buttons to make your selection.
 - **4.** Press O and O directions to select the desired parameter.
 - **5.** Press $^{\textcircled{O}}$ and then use the $^{\textcircled{O}}$ and $^{\textcircled{O}}$ directions, coording to the indicators on the menu, to make your changes.
 - **6.** Select the \bigcirc to return to the main menu.

Del

lcon	Menu and Submenus		Descripti	on
	Brightness/ Contrast	Use this menu to adjustment.	o activate Brigh	tness/Contrast
		(Nell) 2X Monitor		
		Imput Source Imput Source Color Daplay Menu Cr Personalize Others		•
				75%
				< Exit

Brightness	Brightness adjusts the luminance of the backlight.
	Press the igodoldoldoldoldoldoldoldoldoldoldoldoldol
	press the $^{\bigodot}$ direction to decrease the brightness (min. 0 / max. 100).
Contrast	Adjust the Brightness first, and then adjust the Contrast only if further adjustment is necessary.
	Press the \bigcirc direction to increase the contrast and press the \bigcirc direction to decrease the contrast (min. 0 / max. 100).
	The Contrast function adjusts the degree of difference between darkness and lightness on the monitor screen.



Input Source Selects between the different video signals that may be connected to your monitor.



USB-C ^快 90W	Select the USB-C ^낮 90W input when you are using the USB-C connector. Press the joystick to confirm the selection.
DP	Select the DP input when you are using the DisplayPort (DP) connector. Press the joystick to confirm the selection.
HDMI	Select the HDMI input when you are using the HDMI connector. Press the joystick to confirm the selection.
Auto Select	Allows you to scan for available input sources. The default is On .
Auto Select for	Allows you to set Auto Select for USB-C to:
USB-C	• Prompt for Multiple Inputs : Always displays the "Switch to USB-C Video Input" message for you to choose whether to switch or not.
	• Yes : Always switches to USB-C video input (without asking) when the USB-C (C-C) cable is connected.
	 No: Never automatically switches to USB-C video input when the USB-C (C-C) cable is connected.
	Press the joystick to confirm the selection. NOTE: The option is available only when Auto Select is on.

DELL

	Rename Inputs	Allows you to sp selected input s 1, PC 2, Laptop setting is Off. NOTE: Wh USB-C input the specifi	becify a preset in ource. The prese p, Laptop 1, and hen you perforr but, the wattag ied option, e.g.	put name for et options are d Laptop 2 . T n a rename f e value rema ., PC 1 ᅷ 90\	the PC, PC he default or the ains after W.
		NOTE: It i shown in t Info.	s not applicable the warning me	e for the inpessages and l	ut names Display
	Reset Input Source	Resets your mo settings.	nitor input settin	gs to the fact	.ory
¢	Color	Adjusts the cold	or setting mode.		
		Brightness/Contrast			
		- Input Source			
		Color			
		Display			
		E Menu			
		☆ Personalize			
		II Others			
					$\bigotimes_{\bigcirc}^{\bigcirc}$

(Dell

Preset Modes Allows you to choose from the list of preset color modes. Press the joystick to confirm the selection.

0001	2X Monitor			
ø	Brightness/Contrast	~		
Ð	Input Source		Movie	
			Game	
Ð	Display		Warm	
	Menu		Cool	
습	Personalize		Custom Cool	
Ш	Others			
				< Exit



- **Standard**: Loads the monitor's default color settings. This is the default preset mode.
- Movie: Loads color settings ideal for movies.
- Game: Loads color settings ideal for most gaming applications.
- Warm: Increases the color temperature. The screen appears warmer with a red/yellow tint.
- **Cool:** Presents colors at higher color temperatures. The screen appears cooler with a blue tint.
- Custom Color: Allows you to manually adjust the color settings. Move the joystick to adjust the R/G/B color values and create your own preset color mode.

DEL

 Allows you to set the video input mode to: RGB: Select this option if your monitor is connected to a computer or a media player that supports RGB output. YCbCr: Select this option if your media player supports only YCbCr output. 					
Imput Source ⊕ Input Source ⊕ Color ● Deplay ⊡ Menu ☆ Personalize [1] Others	Preset Modes Input Color Format Hue Saturation Reset Color	< Ros Vobor < Evit			

Hue This feature can shift the color of the video image to green or purple. This is used to adjust the desired flesh tone color. Use or or to adjust the hue from 0 to 100.
 Press to increase the green shade of the video image.
 Press to increase the purple shade of the video image.





Saturation	This feature can adjust the color saturation of the video image. Use \bigcirc or \bigcirc to adjust the saturation from 0 to 100.
	Press igodoldoldoldoldoldoldoldoldoldoldoldoldol
	Press $^{\bigodot}$ to increase the colorful appearance of the video image.
	NOTE: Saturation adjustment is available only when you select Movie or Game preset mode.
Reset Color	Resets your monitor's color settings to the factory settings.

(Dell





Aspect Ratio	Adjusts the image ratio to 16:9, 4:3 or 5:4.
Sharpness	This feature can make the image look sharper or softer.
	Move the joystick to adjust the sharpness level from 'O' to '100'.
Response Time	Allows you to set the Response Time to Normal or Fast .
MST	DisplayPort Multi Stream Transport. The default setting is Off. To enable MST (DP out), select On. NOTE: When the DisplayPort/USB-C cable and the DP downstream cable are connected, the OSD will set MST to On automatically. This action will only be done once after Fac- tory Reset or Reset Display is selected.
USB-C Prioritization	Allows you to specify the priority to transfer the data with high resolution (High Resolution) or high speed (High Data Speed) when using the USB-C port/ DisplayPort.
Reset Display	Resets all display settings to the factory preset values.



Menu

Select this option to adjust the settings of the OSD, such as, the languages of the OSD, the amount of time the menu remains on screen and so on.

	2X Monitor		
Ó	Brightness/Contrast		
Ð	Input Source		
٢	Color		
Ţ	Display		
☆	Personalize		
II	Others		
			< Exit



Language	Sets the OSD display to one of the eight languages (English, Spanish, French, German, Brazilian Portuguese, Russian, Simplified Chinese, or Japanese).
Rotation	Press the joystick to rotate the OSD and the screen by 0/90/180/270 degrees.
	You can adjust the menu according to your display rotation.
Transparency	Select this option to change the menu transparency by moving the joystick (min. 0 / max. 100).
Timer	Sets the length of time the OSD will remain active after the last time you pressed a button.
	Move the joystick to adjust the slider in 1 second increments, from 5 to 60 seconds.
Lock	Controls user access to adjustments. User can select one of the following: Menu Buttons, Power Button, Menu + Power Buttons, Disable.
Reset Menu	Resets all OSD settings to the factory preset values.



Personalize

0	Brightness/Contrast		
Ð	Input Source		
\$	Color		
₽	Display		
	Menu	USB-C Charging 분+ 90W	
Ш	Others		
			<

Shortcut Key 1	Allows you to choose a feature from Preset Modes,			
Shortcut Key 2	Brightness/Contrast, Input Source, Aspect Ratio,			
Shortcut Key 3	Totation, or Display into and set it as a shortcut key.			
Power Button LED	Allows you to set the power LED indicator On or Off to save energy.			
USB-C Charging ^使 90W	The default setting is Off in Off Mode . Selecting On in Off Mode may automatically charge your notebook or mobile devices through the USB-C cable even when the monitor is in off mode.			
Other USB Charging	Allows you to enable or disable USB Type-A (Downstream Ports) charging function during monitor standby mode.			
Fast Wakeup	The default setting is Off . Selecting On may prevent the monitor from going into Standby mode.			
	Pressing or move the joystick (except the power button) on the rear panel of the monitor may also wake up the monitor after it goes into Standby mode.			
Reset Personalization	Resets all settings under the Personalize menu to the factory preset values.			



Others

Select this option to adjust the OSD settings, such as the DDC/CI, LCD conditioning, and so on.

()	2X Monitor		
÷.	Brightness/Contrast		
Ð	Input Source		
હ	Color		
Ţ	Display		
	Menu		
습	Personalize		
			< Exit



Display Info	Displays the mor	nitor's current sett	ings.
DDC/CI	DDC/CI (Display allows you to adj on your compute selecting Off .	y Data Channel/Co ust the monitor se er. You can disable	ommand Interface) ettings using software this feature by
	Enable this featu optimum perform	re for best user ex nance of your mor	xperience and hitor.
	2X Monitor		
	(); Brightness/Contrast		
	- Input Source		
	🔂 Color		Off
	🖵 Display		
	E Menu		
	☆ Personalize	Self-Disgnostic	
	If Others		
		Factory Reset	



LCD Conditioning

Helps reduce minor cases of image retention. Depending on the degree of image retention, the program may take some time to run. You can enable this feature by selecting **On**.





Firmware	Displays the firmware version of your monitor.
Service Tag	Displays the service tag of your monitor. This string is required when you look for phone support, check your warranty status, update drivers on Dell's website, etc.
Self-Diagnostic	Allows you to check if your monitor is functioning properly.
Reset Others	Resets all settings under the Others menu to the factory preset values.
Factory Reset	Restore all preset values to the factory default settings. These are also the settings for ENERGY STAR® tests.

0 844	2X Monitor			
Ó.	Brightness/Contrast			
Ð	Input Source			
╚	Color			
Ç	Display			
	Menu			
슙	Personalize			



Menu and Power button lock

Prevents users to access or change OSD menu settings on the display.

By default, the Menu and Power button lock setting is disabled.



To access the lock menu, press and hold the Up or Down or Left or Right direction for four seconds. A lock menu appears at the bottom right corner of the display.

NOTE: The lock menu can be accessed using this method when the Menu and Power buttons are in unlocked state.



To access the unlock menu, press and hold the Up or Down or Left or Right direction for four seconds. An unlock menu appears at the bottom right corner of the display.



NOTE: The unlock menu can be accessed when the Menu and Power buttons are in locked state.





There are three lock options.

	Menu	Description
1	Menu Buttons	When Menu Buttons is selected, the OSD menu settings cannot be changed. All buttons are locked except Power button.
2	Power Button	When Power Button is selected, the display cannot be turned off using the Power button.
3	Menu + Power Buttons – ID	When Menu + Power Buttons is selected, the OSD menu settings cannot be changed and the Power button is locked.

NOTE: To access the Lock or Unlock menu – Press and hold the Up or Down or Left or Right direction for four seconds.

In the following scenarios, the 📋 icon appears at the center of the display:

- When Up or Down or Left or Right direction are pressed. This indicates the OSD menu buttons are in lock state.
- When the Power button is pressed. This indicates the Power button is in lock state.
- When Up or Down or Left or Right direction or Power button are pressed. This indicates OSD menu buttons and the Power button is in lock state.

Unlocking the OSD menu and Power buttons:

- 1. Press and hold the Up or Down or Left or Right direction for four seconds. The unlock menu appears.
- 2. Select the unlock icon 🔁 to unlock the buttons on the display.


OSD warning messages

When the monitor does not support a particular resolution mode, you will see the following message:



This means that the monitor cannot synchronize with the signal that it is receiving from the computer. See monitor specifications for the Horizontal and Vertical frequency ranges addressable by this monitor. Recommended mode is **2560** \times **1440**.

You will see the following message before the **DDC/CI** function is disabled:





D&L

When you adjust the **Brightness** level above the default level for the first time, the following message appears:



NOTE: If you select Yes, the message will not appear the next time you change the Brightness setting.

When you change the default setting of power saving features for the first time, such as **USB-C Charging** ^낮 **90W**, **Other USB Charging**, or **Fast Wakeup**, the following message appears:



NOTE: If you select Yes for either of the features mentioned above, the message will not appear the next time you change the settings of these features. When you perform a factory reset, the message will appear again.



When the monitor goes into Standby mode, the following message appears:



Activate the computer and wake up the monitor to gain access to the OSD. The OSD functions only in the normal operation mode. If you press the joystick during the Standby mode, the following message will appear depending on the selected input:



Activate the computer and the monitor to gain access to the OSD.

NOTE: The message may be slightly different according to the connected input signal.

If either USB-C, DisplayPort, or HDMI input is selected and the corresponding cable is not connected, the following message will appear:



or

Del

No DP Cable
The display will go into Standby mode in 4 minutes.
www.dell.com/P2X23DE
or
No HDMI Cable
The display will go into Standby mode in 4 minutes.
www.dell.com/P2X23DE

NOTE: The message may be slightly different according to the connected input signal.

When the monitor is under DP/HDMI input and a USB-C (C-C) cable is connected to a notebook that supports DP Alternate Mode, if Auto Select for USB-C is enabled, the following message appears:



DEL

You will see the following message before the **Lock** function is activated:



NOTE: The message may be slightly different according to the selected settings.

When **Factory Reset** is selected, the following message appears:



When **Yes** is selected, the following message appears.

🛞 22 Montes
Select "We love de plue following fandt enýs".
-SUM ALL NORS C Charping
- File a USX "The give,
Yes
Ha



When **Yes** is selected, the following message appears.



See Troubleshooting for more information.

DEL

Setting the maximum resolution



NOTE: The steps may vary slightly depending on the version of Windows you have.

To set the maximum resolution for the monitor:

In Windows 8.1:

- 1. For Windows 8.1, select the Desktop tile to switch toclassic desktop.
- 2. Right-click on the desktop and click Screen Resolution.
- 3. If you have more than one monitor connected, ensure that you select P2423DE/ P2723DE.
- 4. Click the Screen Resolution dropdown list and select 2560 x 1440.

5. Click OK.

In Windows 10 and Windows 11:

- 1. Right-click on the desktop and click **Display settings**.
- 2. If you have more than one monitor connected, ensure to select P2423DE/ P2723DE.
- 3. Click the **Display Resolution** dropdown list and select 2560 x 1440.

4. Click Keep changes.

If you do not see **2560 × 1440** as an option, you must update your graphics driver to the latest version. Depending on your computer, complete one of the following procedures:

If you have a Dell desktop or laptop:

• Go to **https://www.dell.com/support**, enter your service tag, and download the latest driver for your graphics card.

If you are using a non-Dell computer (laptop or desktop):

- Go to the support site for your computer and download the latest graphic drivers.
- \cdot Go to your graphics card website and download the latest graphic drivers.

D&L

Using the tilt, swivel, and vertical extension

NOTE: The following instructions are applicable only for attaching the stand that was shipped with your monitor. If you are attaching a stand that you purchased from any other source, follow the set up instructions that were included with the stand.

Tilt, swivel

With the stand attached to the monitor, you can tilt and swivel the monitor for the most comfortable viewing angle.



NOTE: The stand is not installed at the factory when shipped.

Vertical Extension

NOTE: The stand extends vertically up to 150 mm. The figure below illustrates how to extend the stand vertically.





Rotating the monitor

Before you rotate the monitor, your monitor should be fully vertically extended (Vertical Extension) and fully tilted up to avoid hitting the bottom edge of the monitor.



Rotate clockwise





Rotate counterclockwise



- NOTE: To use the Display Rotation function (Landscape versus Portrait view) with your Dell computer, you require an updated graphics driver that is not included with this monitor. To download the graphics driver, go to www.dell.com/support and see the Download section for Video Drivers for latest driver updates.
- NOTE: When in the Portrait View Mode, you may experience performance degradation in graphic-intensive applications (3D Gaming and etc.).



Adjusting the rotation display settings of your system

After you have rotated your monitor, you need to complete the procedure below to adjust the Rotation Display Settings of your system.

NOTE: If you are using the monitor with a non-Dell computer, you need to go to the graphics driver website or your computer manufacturer website for information on rotating the 'contents' on your display.

To adjust the Rotation Display Settings:

- 1. Right-click on the desktop and click **Properties**.
- 2. Select the Settings tab and click Advanced.
- **3.** If you have an ATI graphics card, select the **Rotation** tab and set the preferred rotation.
- **4.** If you have an NVIDIA graphics card, click the **NVIDIA** tab, in the left-hand column select **NVRotate**, and then select the preferred rotation.
- If you have an Intel[®] graphics card, select the Intel graphics tab, click Graphic Properties, select the Rotation tab, and then set the preferred rotation.
- NOTE: If you do not see the rotation option or it is not working correctly, go to www.dell.com/support and download the latest driver for your graphics card.

DEL

Troubleshooting

WARNING: Before you begin any of the procedures in this section, follow the Safety instructions.

Self-Test

Your monitor provides a self-test feature that allows you to check if your monitor is functioning properly. If your monitor and computer are properly connected but the monitor screen remains dark, run the monitor self-test by performing the following steps:

- **1.** Turn off both your computer and the monitor.
- 2. Disconnect all video cables from the monitor. This way, the computer doesn't have to be involved.
- 3. Turn on the monitor.

If the monitor cannot sense a video signal and is working correctly, the following message will appear:





or



DEL





NOTE: The message may be slightly different according to the connected input signal.



NOTE: While in self-test mode, the power LED remains white.

- **4.** This box also appears during normal system operation, if the video cable becomes disconnected or damaged.
- 5. Turn Off your monitor and reconnect the video cable; then turn On both your computer and the monitor.

If your monitor screen remains blank after you use the previous procedure, check your video controller and computer, because your monitor is functioning properly.

Built-in diagnostics

Your monitor has a built-in diagnostic tool that helps you determine if any screen abnormality you experience is an inherent problem with your monitor, or with your computer and video card.

To run the built-in diagnostics:

- 1. Ensure that the screen is clean (no dust particles on the surface of the screen).
- 2. Press the Joystick button to launch the OSD Menu Launcher and move the

Joystick up to select " () " to open Main Menu.





3. Move the Joystick to select **Others > Self-Diagnostic** to initiate the self-diagnostic process.

(Detu	2X Monitor		
֯:	Brightness/Contrast		
Ð	Input Source		
6	Color		
Q	Display		
	Menu		
☆	Personalize		
III			
			< Exit

- **4.** When initiated, a gray screen apppears. Inspect the screen for abnormalities.
- **5.** Toggle the Joystick. The color of the screen changes to red. Inspect the screen for abnormalities.
- 6. Repeat step 5 to inspect the display in green, blue, black, white and text screens.
- **7.** The test is complete when the text screen appears. To exit, toggle the Joystick again.

If you do not detect any screen abnormalities upon using the BID tool, the monitor is functioning properly. Please check the video card and computer.

Common problems

The following table contains general information about common monitor problems you might encounter and the possible solutions:

Common Symptoms	What you experience	Possible Solutions
No Video/Power LED off	No picture	Ensure that the video cable connecting the monitor and the computer is properly connected and secure.
		 Verify that the power outlet is functioning properly using any other electrical equipment.
		\cdot Ensure that the power button is pressed.
		Ensure that the correct input source is selected via the Input Source menu.
No Video/Power LED on	No picture or no brightness	 Increase brightness and contrast controls using the OSD.
		• Perform monitor self-test feature check.
		 Check for bent or broken pins in the video cable connector.
		 Run the built-in diagnostics.
		Ensure that the correct input source is selected via the Input Source menu.
Poor Focus	Picture is fuzzy,	 Eliminate video extension cables.
	blurry, or ghosting	 Reset the monitor to Factory Settings (Factory Reset).
		Change the video resolution to the correct aspect ratio.
Shaky/Jittery Video	Wavy picture or fine movement	 Reset the monitor to Factory Settings (Factory Reset).
		 Check environmental factors.
		Relocate the monitor and test in another room.

Missing Pixels	LCD screen has	 Cycle power On-Off.
	spots	 Pixel that is permanently Off is a natural defect that can occur in LCD technology.
		For more information on Dell Monitor Quality and Pixel Policy, see Dell Support site at:
Stuck on Divola		Quelo power On Off
SLUCK-UIT FIXEIS	hright spots	Cycle power OT-OT.
	bight spots	 Pixel that is permanently off is a natural defect that can occur in LCD technology.
		 For more information on Dell Monitor Quality and Pixel Policy, see Dell Support site at:
D. I.		www.dell.com/pixeiguidelines.
Brightness Problems	Picture too dim or too bright	• Reset the monitor to Factory Settings (Factory Reset).
		 Adjust brightness & contrast controls via OSD.
Geometric Distortion	Screen not centered correctly	Reset the monitor to Factory Settings (Factory Reset).
		 Adjust horizontal & vertical controls via OSD.
Horizontal/ Vertical Lines	Screen has one or more lines	 Reset the monitor to Factory Settings (Factory Reset).
		• Perform monitor self-test feature check and determine if these lines are also in self-test mode.
		Check for bent or broken pins in the video cable connector.
		 Run the built-in diagnostics.

88 | Troubleshooting

(Dell

Synchronization Problems	Screen is scrambled or appears torn	 Reset the monitor to Factory Settings (Factory Reset). Perform monitor self-test feature check to determine if the scrambled screen appears in self-test mode. Check for bent or broken pins in the video cable connector. Restart the computer in the safe mode.
Safety Related Issues	Visible signs of smoke or sparks	 Do not perform any troubleshooting steps. Contact Dell immediately.
Intermittent Problems	Monitor malfunctions on & off	 Ensure that the video cable connecting the monitor to the computer is connected properly and is secure. Reset the monitor to Factory Settings (Factory Reset).
		• Perform monitor self-test feature check to determine if the intermittent problem occurs in self-test mode.
Missing Color	Picture missing color	 Perform monitor self-test feature check. Ensure that the video cable connecting the monitor to the computer is connected properly and is secure. Check for bent or broken pins in the video cable connector.
Wrong Color	Picture color not good	 Try different Preset Modes in Color settings OSD. Adjust R/G/B value in Custom Color in Color settings OSD. Change the Input Color Format to RGB or YCbCr in the Color settings OSD. Run the built-in diagnostics.

Image retention	Faint shadow from	•	Set the screen to turn off after a few
from a static	the static image		minutes of screen idle time. These can
image left on	displayed appears		be adjusted in Windows Power Options
the monitor for	on the screen		or Mac Energy Saver setting
a long period of time		•	Alternatively, use a dynamically changing screensaver.

Specific Symptoms	What you experience	Possible Solutions
Screen image is too small	Image is centered on screen, but does not fill entire viewing area	• Check the Aspect Ratio setting in the Display settings OSD.
		 Reset the monitor to Factory Settings (Factory Reset).
Cannot adjust the monitor with the joystick	OSD does not appear on the screen	• Turn Off the monitor, unplug the power cord, plug it back, and then turn On the monitor.
		 Check whether the OSD menu is locked. If yes, move and hold the joystick up/down/left/right for 4 seconds to unlock (for more information, see Menu and Power button lock).
No Input Signal when user controls are pressed	No picture, the LED light is white	 Check the signal source. Ensure the computer is not in Standby Mode by moving the mouse or pressing any key on the keyboard.
		 Check if the video cable is plugged in properly. Disconnect and reconnect the video cable if necessary.
		 Reset the computer or video player.

Product specific problems

Deell

The picture does not fill the entire screen	The picture cannot fill the height or width of the screen	 Due (as mo screte 	e to different video formats pect ratio) of DVDs, the nitor may display in full een.
No video at HDMI/ DisplayPort/USB-C port	When connected to some dongle/ docking device at the port, there is no video when unplugging/plugging the cable from the notebook	Kur Unj US doc doc US	Pure built-in diagnostics. plug the HDMI/DisplayPort/ B-C cable from dongle/ cking device, then plug the cking HDMI/DisplayPort/ B-C cable to the notebook.
No network connection	Network dropped or intermittent	• Do dur	not turn Off the monitor ing network connection.
The LAN port is not functioning	OS setting or cable connection issue	 Ensidrivity Ensidrivity Ethenside If y GB Maine Ensidrivity GB Change Change	sure that the latest BIOS and vers for your computer are talled on your computer. sure that the RealTek Gigabit hernet Controller is installed in Windows Device Manager. our BIOS Setup has a LAN/ E Enabled/Disabled option, ke sure it is set to Enabled. sure that the Ethernet cable nonnected securely on the nitor and the hub/router/ wall. eck the status LED of the hernet cable to confirm nectivity. Re-connect both ds of the Ethernet cable if the D is not lit.
		 First and the The and US 	at power off the computer d unplug the USB-C cable and power cord from the monitor. en, power on the computer d plug the power cord and the B-C cable into the monitor.
			(D&LL)

Common symptoms	What you experience	Possible Solutions
USB interface is not working	USB peripherals are not working	Check that your monitor is turned On.
		Reconnect the upstream cable to your computer.
		 Reconnect the USB peripherals (downstream connector).
		 Turn off the monitor and turn it on again.
		 Reboot the computer.
		 Certain USB devices such as portable hard drive require higher power source; connect the drive to the computer directly.
USB-C port does not supply power	USB peripherals can not be charged	 Check that the connected device is compliant with the USB-C specification. The USB-C port supports USB 3.2 Gen1 and an output of 90 W.
		 Check that you use the USB-C cable shipped with your monitor.
SuperSpeed USB 5 Gbps (USB 3.2 Gen1) interface is	SuperSpeed USB 5 Gbps (USB 3.2 Gen1) peripherals working	 Check that your computer is SuperSpeed USB 5 Gbps (USB 3.2 Gen1)-compatible.
slow	slowly or not working at all	 Some computers have USB 3.2, USB 2.0, and USB 1.1 ports. Ensure that the correct USB port is used.
		 Reconnect the upstream cable to your computer.
		 Reconnect the USB peripherals (downstream connector).
		 Reboot the computer.

Universal Serial Bus (USB) specific problems

Dell

peripherals stop working when a USB 3.2 device is plugged in distance between itself and its receiver decreases	 Wireless USB receiver. Position your wireless USB receiver as close as possible to the wireless USB peripherals. Use a USB-extender cable to position the wireless USB receiver as far away as possible from the USB 3.2 port.
---	--

Regulatory information

FCC notices (U.S. Only) and other regulatory information

For FCC notices and other regulatory information, see the regulatory compliance website located at **www.dell.com/regulatory_compliance**.

EU product database for energy label and product information sheet

P2423DE: https://eprel.ec.europa.eu/qr/1057583 P2723DE: https://eprel.ec.europa.eu/qr/1057602

Contacting Dell

To contact Dell for sales, technical support, or customer service issues, see **www.** dell.com/contactdell.

- NOTE: Availability varies by country and product, and some services may not be available in your country.
- NOTE: If you do not have an active Internet connection, you can find contact information on your purchase invoice, packing slip, bill, or Dell product catalog.