LCD Monitor User Manual

The color and the appearance may differ depending on the product, and the specifications are subject to change without prior notice to improve the performance.



MAJOR SAFETY PRECAUTIONS

Before You Start	1-1
Custody and Maintenance	1-2
Safety Precautions	1-3

INSTALLING THE PRODUCT

Package Contents 2-	1
Installing the Stand 2-2	2
Removing the Stand 2-	3
Connecting with a PC 2-	4
Connecting an HDMI cable 2-	5
Connecting to an Amplifier 2-	6
Kensington Lock 2-	7

USING THE PRODUCT

Setting the Optimal Resolution 3-	-1
Standard Signal Mode Table 3-	·2
Installing the Device Driver 3-	.3
Product Operating Buttons 3-	-4
Using the Screen Adjustment Menu (OSD: On Screen Display) 3-	·5

INSTALLING THE SOFTWARE

Natural Color	4-1
MagicTune	4-2
MultiScreen	4-3

TROUBLESHOOTING

Monitor Self-Diagnosis	5-1
Before Requesting Service	5-2
FAQ	5-3

MORE INFORMATION

Specifications	6-1
Power Saving Function	6-2
Contact SAMSUNG WORLDWIDE	6-3
Correct Disposal of This Product	
(Waste Electrical & Electronic Equipment) - Europe only	6-4

1-1 Before You Start

Icons used in this manual

ICON	NAME	MEANING
	Caution	Indicates cases where the function may not work or the setting may be canceled.
	Note	Indicates a hint or tip to operate a function.

Using this Manual

- The contents of this manual are subject to change without prior notice for performance improvement.
- Make yourself fully aware of the safety precautions before using this product.
- If a problem occurs, refer to the 'Troblemshooting' section.

Copyright Notice

Copyright © 2010 Samsung Electronics Co., Ltd. All Rights Reserved.

The copyright of this manual is reserved by Samsung Electronics, Co., Ltd.

The contents of this manual may not be partially or in whole reproduced, distributed or used in any form without the written permission of Samsung Electronics, Co., Ltd.

The SAMSUNG logo and SyncMaster are the registered trademarks of Samsung Electronics, Co., Ltd.

Microsoft, Windows and Windows NT are the registered trademarks of Microsoft Corporation.

VESA, DPM and DDC are the registered trademarks of the Video Electronics Standard Association.

All other trademarks mentioned herein belong to their respective companies.

1-2 Custody and Maintenance

External Surface and Screen Maintenance

Clean the product with a soft dry cloth.

- Do not clean the product with an inflammable substance such as benzene or thinner or with a wet cloth. This may result in a problem with the product.
- Do not scratch the screen with your fingernails or a sharp object.
 - This may result in scratches or damage to the product.
- Do not clean the product directly by spraying water onto the product.

If water enters the product, it may result in fire, electric shock or a problem with the product.

- A white stain may be generated on the surface of the highglossy model due to the inherent characteristics of the material, if a supersonic humidifier is used.
- The appearance and the color may differ depending on the model.



About persistent images

- Displaying a still image for a long time may create a persistent image or stain on the screen. If you do not use the product for a long time, set the power-saving mode or screen saver.
- Due to technological constraints of the LCD Panel manufacturer, the images generated by this product may appear either brighter or darker than normal by appr. 1ppm (parts per million) pixel.
 The number of sub-pixels of an LCD panel by size: The number of Sub-Pixels = Max. Horizontal Resolution x Max. Vertical Resolution x 3


Example) If the maximum resolution is 1680 x 1050, the number of sub-pixels is 1680 x 1050 x 3 = 5,292,000.

1-3 Safety Precautions

Icons used for safety precautions

ICON	NAME	MEANING
Δ	Warning	Failing to follow the precautions marked with this sign, may result in a serious injury or even a fatality.
Δ	Caution	Failing to follow the precautions marked with this sign, may result in a personal injury or property damage.

Meaning of Signs



Power Related

The product image used in the following pictures for your reference may look different from the actual product.




Avoid using a damaged power cord or plug or a loose power outlet.

 Otherwise, it may result in electric shock or fire.







Otherwise, it may result in electric shock.

Make sure to connect the power cord to a grounded wall outlet (for insulation class 1 equipment only).

• Otherwise, it may result in electric shock or injury.

Keep the power cord and the product away from a heater.

Otherwise, it may result in electric shock or fire.












Avoid connecting multiple electric appliances to a single wall outlet.

• Otherwise, it may result in fire due to overheating of the wall outlet.

Plug the power plug in firmly.

• Otherwise, it may result in fire.



• Otherwise, it may result in electric shock or fire due to a damaged power cord.

If the pins of the power plug or the wall outlet are covered in dust, clean it using a dry cloth.

• Otherwise, it may result in fire.





Avoid unplugging the power plug while the product is operating.

• Otherwise, it may damage the product due to electric shock.



- When unplugging the power plug from the wall outlet, make sure to hold it by the plug and not by the cord.
 - Otherwise, it may result in electric shock or fire.

Make sure to use only the power cord supplied by our company. In addition, do not use the power cord of another electric appliance.

Otherwise, it may result in electric shock or fire.

Connect the power plug to a wall outlet that can be easily reached.

• When a problem occurs with the product, you must unplug the power plug to cut the power off completely. You cannot cut the power off completely using only the power button on the product.

Installation Related



Avoid placing burning candles, mosquitorepellent or cigarettes on the product and installing the product near a heater.

Otherwise, it may result in fire.



Avoid installing the product in a badly-ventilated location such as inside a bookshelf or closet.

• Otherwise, it may result in fire due to internal over-heating.

Keep the plastic bags used to pack the product away from children.

 If children place the plastic bags over their heads, they may suffocate.







Ask an installation engineer or relevant company to install the product onto the wall.

- Otherwise, it may result in injury.
- Make sure to use the specified wall mount.

Keep a distance of at least 10 cm from the wall when installing the product for ventilation.

• Otherwise, it may result in fire due to internal over-heating.

Avoid installing the product in a location that is unstable or exposed to excessive vibrations such as on an unstable or slanted shelf.

- The product may fall and this may result in damage to the product or injury.
- If you use the product in a location exposed to excessive vibrations, it may result in a problem with the product or fire.

Avoid installing the product in a location exposed to direct sunlight and installing the product near a heat source such as a fire or heater.

 This may shorten the product life cycle or cause fire.



exposed to dust, moisture (sauna), oil, smoke or water (rain drops) and installing it within a vehicle.

Avoid installing the product in a location

• This may result in electric shock or fire.

Avoid installing the product at an easily reachable height where children may reach it.


- If a child touches the product, the product may fall and this may result in injury.
- Since the front part is heavier, install the product on a flat and stable surface.





Do not let the product drop while moving it.

 This may result in a problem with the product or injury.



 Otherwise, this may cause the product to fall off and result in a malfunction or injury.

does not protrude out of the console or shelf.

 Make sure to use a cabinet or shelf suitable to the size of the product.



If the product is installed in a location where the operating conditions vary considerably, a serious quality problem may occur due to the surrounding environment. In this case, install the product only after consulting one of our service engineers about the matter.

 Places exposed to microscopic dust, chemicals, too high or low temperature, high humidity, such as airports or stations where the product is continuously used for a long time and so on.





Do not place the product face down on the floor.

This may damage the panel of the product.

When putting the product down, handle it gently.

Otherwise, it may result in a problem with the product or injury.

Cleaning Related



Since using a surfactant, which contains a large amount of alcohol, solvent or other strong chemicals, may result in the discoloration or cracking of the product exterior or the panel surface coming off, be sure to use the recommended cleansing agent only.

You can purchase the recommended cleansing agent from a service center.



Before cleaning the product, unplug the power cord.

• Otherwise, it may result in electric shock or fire.



When cleaning the product, do not spray water directly over the product parts.

- Make sure that water does not enter the product.
- Otherwise, it may result in fire, electric shock or a problem with the product.





Avoid spraying cleansing agent directly onto the product.

This may result in discoloration or cracking of the exterior of the product or the panel coming off.



When cleaning the product, disconnect the power cord and clean the product with a soft dry cloth.

Avoid using chemicals such as wax, benzene, alcohol, thinner, mosquitorepellent, fragrance, lubrication or cleansing agent when cleaning the product. This may result in the exterior being deformed or the print being removed.

Since the exterior of the product is easily scratched, be sure to use a proper cleansing cloth. Use the cleansing cloth with a small amount of water. However, if the cloth is contaminated by alien substances, it may result in scratches to the exterior; therefore shake off any alien substances from the cloth before using it.



Use a soft, damp cloth with a "monitorexclusive cleansing agent" and wipe the product with it.

If no monitor-exclusive cleansing agent is available, dilute a cleansing agent with water at a ratio of 1:10 before cleaning the product.

Usage Related

Warning



Since a high voltage runs through the product, never disassemble, repair or modify the product vourself.

- Otherwise, it may result in fire or electric shock.
- If the product needs to be fixed, contact a service center.



If the product generates a strange noise, a burning smell, or smoke, unplug the power plug immediately and contact a service center.

Otherwise, it may result in electric shock or fire.





If you drop the product or the case is damaged, turn the power off and unplug the power cord. Contact a service center.

Otherwise, it may result in fire or electric shock.

When thunder or lighting occurs, unplug the power cord and under no circumstance touch the antenna cable as this is dangerous.

Otherwise, it may result in electric shock or fire.



When cleaning the product, do not spray water directly over the product parts.

- Make sure that water does not enter the product.
- Otherwise, it may result in fire, electric shock or a problem with the product.

Avoid letting children to hang or climb onto the product.

Otherwise, it may result in the product falling and this may result in injury or death.



Avoid placing objects such as toys and cookies on top of the product.

If a child hangs over the product to grab an object, the object or the product may fall and this may result in injury or even death.

Avoid dropping an object over the product or cause impact to the product.

Otherwise, it may result in electric shock or fire.



Avoid moving the product by pulling the power cord or antenna cable.

Otherwise, it may result in electric shock, fire or a problem with the product due to damage to the cable.



When a gas leak occurs, do not touch the product or the power plug and ventilate immediately.

- A spark may result in an explosion or fire.
- During a thunder or lighting storm, do not touch the power cord or antenna cable.

Avoid using or placing inflammable spray or

This may result in an explosion or fire.

objects near the product.

Avoid lifting up or move the product by holding only the power cord or signal cable.

Otherwise, it may result in electric shock, fire or a problem with the product due to damage to the cable.

Take care not to block the vent by a table cloth or curtain.

Otherwise, it may result in fire due to internal overheating.





Avoid inserting metal objects such as a chopsticks, coins or hairpins, or inflammable

objects into the product (the vents, ports, etc).

- If water or an alien substance enters the product, turn the power off, unplug the power cord and contact a service center.
- Otherwise, it may result in a problem with the product, electric shock or fire.



Avoid placing a liquid container such as a vase, flowerpot, beverage, cosmetics or drugs, or a metal object over the product.

- If water or an alien substance enters the product, turn the power off, unplug the power cord and contact a service center.
- Otherwise, it may result in a problem with the product, electric shock or fire.





Displaying a still image for a long time may create a persistent image or stain on the screen.

If you do not use the product for a long time, use the power-saving mode or set the screensaver to the moving picture mode.




Set the appropriate resolution and frequency for the product.

Otherwise, it may result in eye strain.

Do not place the adapter on top of another adapter.

Otherwise, it may result in fire.





Otherwise, it may result in fire.



When not using the product for a long time such as leaving your home, unplug the power cord from the wall outlet.

Otherwise, it may cause dust accumulation and result in fire caused by overheating or short circuit or result in an electric shock.

Avoid turning the product upside down or move the product holding only the stand.

This may cause the product to fall resulting in damage to the product or injury.

Keep power adaptor away from any other heat source.

Otherwise, it may result in fire.

Always keep power adaptor in well-ventilated area.



Be careful that adaptor should not be in contact with water and therefore not be wet.

This may cause a malfunction, electric shock or fire. Do not use adaptor by the waterside or outside particularly when it rains or snows. Be careful that adaptor should not be wet while cleaning floor with water.



Avoid using a humidifier or cooker near the product.

 Otherwise, it may result in electric shock or fire.



Since the display panel is hot after using it for a long time, do not touch the product.



- Take care when adjusting the angle of the product or the height of the stand.
 - If your hand or finger is caught, you may be injured.
- If the product is tilted excessively, the product may fall and this may result in injury.



Watching the product from too close a distance continuously may damage your eyesight.



It is important to give your eyes some rest (5 minutes every hour) when viewing the product screen for long periods of time.

This will alleviate any eye strain.

Keep small accessories away from the children.



Avoid placing a heavy object over the product.

• Otherwise, it may result in a problem with the product or injury.

Maintaining the Correct Posture when Using this Product



Maintain the correct posture when using this product.

- Straighten your back.
- Keep a distance of 45~50 cm from your eyes to the screen. Look down at the screen and face the screen forwards.
- Adjust the angle of the product so that light is not reflected onto the screen.
- Keep your elbow at a right angle and keep your arm level with the back of your hand.
- Keep your elbow at a right angle.
- Place your heels flat on the ground while keeping your knees at an angle of 90 degrees or higher and maintain the position of your arm so that your arm is below your heart.

2 Installing the Product

2-1 Package Contents

- Unpack the product and check if all of the following contents have been included.
 - Store the packaging box in case you need to move the Product at a later stage.
 - If any items are missing, contact your dealer.
 - Contact a local dealer to purchase optional items.



Monitor

	CONTENTS				
E	\Box				
Quick Setup Guide	Warranty Card (Not available in all locations)	User Manual	'DVI-A to D-Sub' Cable		
Power Cord	DC-Adapter	Cleaning Cloth	Stand Connector		
Stand					
	OPTIONA	L PARTS			
3					
HDMI Cable	DVI Cable				

- The color and the appearance may differ depending on the product, and the specifications are subject to change without prior notice to improve the performance.
 - The cleaning cloth is supplied with black high-glossy models only.

Before assembling the product, place the product down on a flat and stable surface so that the screen is facing downwards.



Insert the Stand Connector into the Stand in the direction shown by the figure.



Check if the Stand Connector is firmly connected.



Turn the connecting screw at the bottom of the stand fully so that it is completely fixed.



Place a soft cloth over the table to protect the product and place the product onto the cloth so that the front of the product is facing downwards.

Hold the main body of the product with your hand as shown by the figure.



Push the assembled stand into the main body in the direction of the arrow as shown in the figure.

- Caution

Avoid lifting the product holding only the stand.



Before removing the stand, place the product down on a flat and stable surface so that the screen faces downwards.



Place a soft cloth over the table to protect the product and place the product onto the cloth so that the front of the product faces downwards.



Hold the main body of the product with your hand as shown by the figure. Pull the stand in the direction of the arrow as shown in the figure to separate it.




Turn the connecting screw at the bottom of the stand to separate it.




Take the Stand Connector out of the Stand by pulling it in the direction of the arrow as shown in the figure.

2-4 Connecting with a PC

- The connecting part may differ depending on the product model.
- 1. Connect the product to a PC depending on the video output supported by the PC.
 - When the graphics card provides D-Sub (Analog) output
 - Connect the [DVI IN] port of the product to the [D-Sub] port on your PC using the DVI-A to D-Sub cable.



- When the graphics card provides DVI (Digital) output
 - Connect the [DVI IN] port of the product to the [DVI] port of the PC with the DVI cable.




2. Connect one end of the power cord to the DC-Adapter and plug the other end into a dedicated 220V or 110V wall outlet. (The input voltage is switched automatically.)



When the product is connected to a PC, you can turn the product on and use it.
 When both the DVI (<Digital>) and D-Sub (<Analog>) cables are connected, you can select the input signal <Analog/
 Digital> by pressing the use button.

2-5 Connecting an HDMI cable

1. Connect the HDMI output port of your digital output device to the [HDMI IN] port of the product using the HDMI cable.



2. Connect a speaker to the [AUDIO OUT] port of the product.



This product won't make any sound when only the HDMI cable is connected without a speaker connected.
 When all the connections are complete, you can turn on and use the product and your DVD player (or digital output device).
 Press the L= button and select <HDMI> as an input signal.

2-6 Connecting to an Amplifier

1. Connect the [DIGITAL AUDIO OUT] terminal of your monitor to the optical input of your amplifier using an optical cable.



- If no sound is emitted from the monitor, you need to use an amplifier.
 - For information on how to connect a speaker and amplifier, refer to the respective user manuals provided by their manufacturers.

2-7 Kensington Lock

A Kensington Lock is an anti-theft device that enables users to lock the product so that they can safely use it in public locations. Since the shape and usage of the locking device may differ depending on the model and the manufacturer, refer to the User Manual supplied with the locking device for more information.

You must purchase the Kensington Lock separately.



To lock the product, follow these steps:

- 1. Wrap the Kensington lock cable around a large, stationary object such as a desk or chair.
- 2. Slide the end of the cable with the lock attached through the looped end of the Kensington lock cable.
- 3. Insert the locking device into the Kensington slot on the Monitor (B).
- 4. Lock the lock (A).
- These are general instructions. For exact instructions, see the User Manual supplied with the locking device.
 - · You can purchase the locking device from an electronics store, an online shop, or our service center.

3-1 Setting the Optimal Resolution

If you turn the power on after purchasing the product, a message regarding the optimal resolution setting appears on the screen. Select a language and the optimal resolution.



▲/▼ : You can select a language with these buttons. MENU : If you press this button, the message disappears.

- The message appears up to 3 times if the resolution has not been set to the optimal resolution.
 - To set the resolution to the optimal resolution
 - When the PC is turned off, connect the product and the PC and turn the power on.
 - Right-click over the Desktop and select 'Properties' from the pop-up menu.
 - In the 'Settings' tab, set the resolution to the optimal resolution.

The LCD monitor has one optimal resolution for the best visual quality depending on the screen size due to the inherent characteristics of the panel, unlike for a CDT monitor.

Therefore, the visual quality will be degraded if the optimal resolution is not set for the panel size. It is recommended setting the resolution to the optimal resolution of the product.

If the signal from the PC is one of the following standard signal modes, the screen is set automatically. However, if the signal from the PC is not one of the following signal modes, a blank screen may be displayed or only the Power LED may be turned on. Therefore, configure it as follows referring to the User Manual of the graphics card.

DISPLAY MODE	HORIZONTAL FREQUENCY (KHZ)	VERTICAL FREQUENCY (HZ)	PIXEL CLOCK (MHZ)	SYNC POLARITY (H/ V)
IBM, 640 x 480	31.469	59.940	25.175	-/-
VESA, 800 x 600	35.156	56.250	36.000	+/+
VESA, 800 x 600	37.879	60.317	40.000	+/+
VESA, 1024 x 768	48.363	60.004	65.000	-/-
VESA, 1280 x 800	49.702	59.810	83.500	-/+
VESA, 1280 x 960	60.000	60.000	108.000	+/+
VESA, 1280 x 1024	63.981	60.020	108.000	+/+
VESA, 1440 x 900	55.935	59.887	106.500	-/+
VESA, 1600 x 1200	75.000	60.000	162.000	+/+
VESA, 1680 x 1050	65.290	59.954	146.250	-/+
VESA, 1920 x 1080	67.500	60.000	148.500	+/+

Horizontal Frequency

The time taken to scan one line from the left-most position to the right-most position on the screen is called the horizontal cycle and the reciprocal of the horizontal cycle is called the horizontal frequency. The horizontal frequency is represented in kHz.

Vertical Frequency

A panel must display the same picture on the screen tens of times every second so that humans can see the picture. This frequency is called the vertical frequency. The vertical frequency is represented in Hz.

3-3 Installing the Device Driver

- If you install the device driver, you can set up the appropriate resolution and frequency for the product. The device driver is included on the CD-ROM supplied with the product. If the supplied drive file is corrupted, please visit a service center or Samsung Electronics website(http://www.samsung.com/), and download the driver.
- 1. Insert the driver installation CD into the CD-ROM drive.
- 2. Click on Windows Driver.
- 3. Complete the remaining installation steps according to the instructions displayed on the screen.
- 4. Select the model of your product from the model list.



5. Check if the appropriate resolution and screen refresh rate are displayed in the Control Panel settings. For more information, refer to the document about the Windows operating system.

Product Operating Buttons



ICON	DESCRIPTION
MENU	Press this button to view the On Screen Display (OSD).
	This button is also used to exit the OSD or to return to a higher-level OSD menu
	* OSD Adjustment Lock
	This function locks the OSD in order to maintain the current settings or to prevent the settings from being changed by another person
	On: If you press and hold the MENU button down for 5 seconds, the OSD Adjustment Lock function is activated.
	Off: If you press and hold the MENU button down for 5 seconds again, the OSD Adjustment Lock function is disabled.
	Even if the OSD Adjustment Lock function is activated, users can adjust the brightness and contrast and can set up the adjustment function assigned to the [FF].
▲/▼	Use these buttons to navigate the menu or to adjust a value in the OSD.
÷٦	Users can set the Customized Key to one of the following functions. If the user presses the Customized Key [$r_{\rm T}$] after setting it, the configured function will be performed
	 PC signals : <magicbright> - <magiccolor> - <color effect=""> - <image size=""/></color></magiccolor></magicbright>
	AV signals : <picture mode=""> - <magiccolor> - <color effect=""> - <image size=""/></color></magiccolor></picture>
	You can set the function of the Customized Key by selecting "SETUP&RESET -> Customized Key" in the OSD.
¢	Use this button to control the brightness of the screen.
	The sound can be adjusted only if the <pc av="" mode=""> is under <av> and the external input is connected with the HDMI or DVI.</av></pc>
Ú15	Use this button to select a function
	If you press the [III] button when there is no OSD, the input signal (Analog/Digital/HDMI)
	is switched. When the input signal is switched by pressing [[]]] button or the product is turned on, a message displaying the selected input signal appears at the top left of the screen.)
	To select Digital mode, you have to connect the product and the PC with the DVI cable.

ICON	DESCRIPTION	
AUTO	Press [AUTO] button to adjust the screen settings automatically	
	This function is only available in Analog mode.	
	If the resolution settings are changed in the Display Properties, the AUTO adjustment func- tion is performed.	
Ö	Press this button to turn the product on or off	
	 The buttons on the right of the product are touch-type buttons. 	
	Touch the buttons lightly with your finger.	
	Power LED	
	This LED is turned on when the product works normally.	
	For more information on the power-saving function, refer to the power saving function in More Information. When not using the product for a long time, unplugging the power cord is recommended to minimize power consumption.	

3-5 Using the Screen Adjustment Menu (OSD: On Screen Display)

TOP MENUS	SUB MENUS				
PICTURE	Brightness	Contrast	Sharpness	MagicBright	Picture Mode
	Coarse	Fine	Response Time	HDMI Black Level	
COLOR	MagicColor	Red	Green	Blue	Color Tone
	Color Effect	Gamma			
SIZE & POSI- TION	H-Position	V-Position	Image Size	Menu H-Position	Menu V-Position
SETUP&RESET	Reset	Menu Transpar- ency	Language	LED On/Off	LED Brightness
	Off Timer On/Off	Off Timer Setting	Auto Source	PC/AV Mode	Display Time
	Customized Key				
INFORMA- TION					

The Screen Adjustment Menu (OSD: On Screen Display) Structure

PICTURE



<PC signals>



<AV signals>

MENU	DESCRIPTION		
Brightness	Controls the screen brightness. This menu is unavailable when <magicbright> is set to <dynamic contrast=""> mode.</dynamic></magicbright>		
Contrast	 Controls the contrast of the pictures displayed on the screen This menu is unavailable when <magicbright> is set to <dynamic contrast=""> mode.</dynamic></magicbright> This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor> 		
Sharpness	 Controls the clarity of details of pictures displayed on the screen This menu is unavailable when <magicbright> is set to <dynamic contrast=""> mode.</dynamic></magicbright> This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor> 		

MENU	DESCRIPTION
MagicBright	Provides preset picture settings optimized for various user environments such as editing a document, surfing the Internet, playing games, watching sports or movies and so on.
	 <custom> If the preset picture modes are not sufficient, users can configure the <brightness> and <contrast> directly using this mode. </contrast></brightness></custom>
	 <text> This mode provides the picture setting appropriate for editing a document.</text> <internet></internet>
	This mode provides the picture setting appropriate for surfing the Internet (text + picture). • <game></game>
	This mode provides the picture setting appropriate for playing games that include lots of graphics and that require a fast screen refresh rate.
	 <sport> This mode provides the picture setting appropriate for watching sports games that include lots of movement.</sport>
	 <movie> This mode provides brightness and sharpness settings similar to those of a TV for the best entertainment environment (movie, DVD, etc.).</movie>
	 <dynamic contrast=""> Controls the picture contrast automatically so that bright and dark pictures are balanced overall.</dynamic>
Picture Mode	The Monitor has four automatic picture settings <custom>, <dynamic>, <standard> and <movie> that are preset at the factory. You can activate either <custom>, <dynamic>, <standard> or <movie>. You can select "Custom" which automatically recalls your personalized picture settings.</movie></standard></dynamic></custom></movie></standard></dynamic></custom>
	 <custom> Select this mode when you want to adjust the image according to your preferences.</custom>
	 <dynamic> Select this mode to view a sharper image than in Standard mode.</dynamic> <standard></standard>
	 Select this mode when the surroundings are bright. This also provides a sharp image. <movie></movie>
	Select this mode when the surroundings are dark. This will save power and reduce eye fatigue.
	This can only be set when the external input is connected through HDMI/DVI and <pc av="" mode=""> is set to <av>.</av></pc>
Coarse	Removes vertical noise lines (line pattern) from the screen.
	The location of the screen may be changed after the adjustment. In this case, move the screen so that the screen is displayed at the center of the display panel using the <h-position> menu.</h-position>
	This function is only available in <analog> mode.</analog>
Fine	Removes horizontal noise lines (line pattern) from the screen.
	If you cannot remove the noise completely with the <fine> function, adjust the <coarse> and then use the <fine> function again.</fine></coarse></fine>
	This function is only available in <analog> mode.</analog>

MENU	DESCRIPTION		
Response Time	Accelerates the response time of the LCD panel faster than the original response time so that movin pictures appear sharper and more natural.		
	• <normal></normal>		
	 <faster></faster> 		
	Fastest>		
	It is recommended setting the Normal or Faster when not viewing a movie.		
HDMI Black Level	When a DVD or set-top box is connected to your TV via <hdmi>, it may cause a degradation in the</hdmi>		
	screen quality, such as an increase in the black level, a low contrast, or discoloration, etc.,		
	depending on the external device connected. In this case, adjust the screen quality of your TV by		
	configuring the <hdmi black="" level="">.</hdmi>		
	• <normal></normal>		
	• <low></low>		
	This function is active only when the external device is connected via <hdmi>. The <hdmi black="" level=""> function may not be compatible with all external devices.</hdmi></hdmi>		

😭 COLOR



MENU	DESCRIPTION
MagicColor	Expresses natural colors more clearly without changing the picture quality using proprietary digital picture quality improvement technology developed by Samsung Electronics.
	• <off> - Turns the MagicColor function off.</off>
	• <demo> - You can compare the pictures processed by MagicColor with the original pictures.</demo>
	- Full> - Provides a clearer picture including areas corresponding to skin color.
	Intelligent> - Improves the chroma of pictures except for areas corresponding to skin color.
Red	You can adjust the red color value of pictures according to your preference.
	This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor>
Green	You can adjust the green color value of pictures according to your preference.
	This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor>
Blue	You can adjust the blue color value of pictures according to your preference.
	This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor>
Color Tone	You can set the color temperature according to your preference.
	Cool> - Sets the color temperature of the screen to a cooler color.
	• <normal> - Sets the color temperature of the screen to the standard color temperature.</normal>
	• <warm> - Sets the color temperature of the screen to a warmer color.</warm>
	 <custom> - Select this menu to set the color temperature manually.</custom>
	If you do not like the preset color temperatures, you can manually adjust the colors of <color effect="">.</color>
	This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor>
Color Effect	You can change the overall atmosphere by changing the color of pictures.
	• <off> - Turns the color effect function off.</off>
	• <grayscale> -Displays pictures in black and white.</grayscale>
	• <green> - Displays pictures in green mono color.</green>
	 <aqua> - Displays pictures in aqua mono color.</aqua>
	Sepia> - Displays pictures in sepia mono color.
	This menu is unavailable when <magiccolor> is set to <full> mode or <intelligent> mode.</intelligent></full></magiccolor>
Gamma	Using this menu, you can change the intensity of the colors of medium brightness.
	• <mode1> - <mode2> - <mode3></mode3></mode2></mode1>

Color> feature is not available when <MagicBright> is set to <Dynamic Contrast> mode.

SIZE & POSITION



MENU	DESCRIPTION
H-Position	Moves the position of the display area on the screen horizontally.
	This function is only available in <analog> mode.</analog>
V-Position	Moves the position of the display area on the screen vertically.
	This function is only available in <analog> mode.</analog>
Image Size	PC signals
	 <auto> - The picture is displayed at the aspect ratio of the input signal.</auto>
	• <wide> - The picture is displayed in full screen regardless of the aspect ratio of the input signal.</wide>
	 A signal not in the standard mode table is not supported.
	 If the resolution is set to the optimal resolution, the aspect ratio does not change whether the <image size=""/> is set to <auto> or <wide>.</wide></auto>
	AV signals
	• <4 : 3> - Displays pictures at the 4 : 3 aspect ratio.
	• <16 : 9> - Displays pictures at the 16 : 9 aspect ratio.
	 <screen fit=""> - If a 720P, 1080i or 1080P signal is input in HDMI/DVI input mode, the picture is displayed as is without truncation.</screen>
	This can only be set when the external input is connected through HDMI/DVI and <pc av="" mode=""> is set to <av>.</av></pc>
Menu H-Position	You can adjust the horizontal position of the OSD.
Menu V-Position	You can adjust the vertical position of the OSD.

SETUP&RESET



MENU	DESCRIPTION	
Reset	Use this function to restore the visual quality and color settings to the factory defaults.	
	• <no> - <yes></yes></no>	
Menu Transparency	You can select the transparency of the OSD.	
	• <off> - <on></on></off>	
Language	Select a language for the OSD.	
	 English, Deutsch, Español, Français, Italiano, Svenska, Русский, Português, Türkçe 	
	The selected language is only applied to the product OSD. This setting does not affect the other functions of the PC.	
LED On/Off	Turns the Menu button LED on or off.	
	• <off> - Turns the Power button LED lamp off.</off>	
	• <on> - Turns the Power button LED lamp on.</on>	
LED Brightness	Adjusts the brightness of the Menu button LED in levels.	
Off Timer On/Off	You can turn the Off Timer on or off.	
	• <off> - <on></on></off>	
Off Timer Setting	Turns the power off automatically when the configured time is reached.	
Auto Source	 <auto> - The monitor automatically selects an input signal.</auto> 	
	 <manual> - Users have to manually select an input signal.</manual> 	
PC/AV Mode	Set to PC when connected to a PC.	
	Set to AV when connected to an AV device.	
	This function does not support <analog> mode.</analog>	
Display Time	The OSD automatically disappears if no action is taken by the user.	
	You can determine the time to wait before the OSD is hidden.	
	• <5 sec> - <10 sec> - <20 sec> - <200 sec>	
Customized Key	You can set the function of the Customized Key to one of the following.	
	PC signals : <magicbright> - <magiccolor> - <color effect=""> - <image size=""/></color></magiccolor></magicbright>	
	AV signals : <picture mode=""> - <magiccolor> - <color effect=""> - <image size=""/></color></magiccolor></picture>	

INFORMATION



MENU	DESCRIPTION	
INFORMATION	Shows the frequency and resolution set on the PC.	

4-1 Natural Color

What is Natural Color ?

This software works only for Samsung products and enables adjusting the displayed colors on the product and matches the colors on the product with the colors of the printed pictures. For more information, refer to the online help of the software (F1).

The Natural Color is provided online. You can download it from the website below and install;

http://www.samsung.com/us/consumer/learningresources/monitor/naturalcolorexpert/pop_download.html

What is MagicTune?



MagicTune is a software program that helps with monitor adjustments by providing comprehensive descriptions of monitor functions and easy-to-understand guidelines.

Users can adjust the product with the mouse and the keyboard without using the operating buttons of the product.

Installing the Software

- 1. Insert the installation CD into the CD-ROM drive.
- 2. Select the MagicTune setup program.
 - If the pop-up screen for the software installation does not appear on the main screen, find and double-click the MagicTune setup file on the CD-ROM.
- 3. Select the installation language and click [Next].
- 4. Complete the remaining software installation steps according to the instructions displayed on the screen.
 - The software may not work properly if you do not restart the computer after the installation.
 - The MagicTune icon may not appear depending on the computer system and the product specifications.
 - If the shortcut icon does not appear, press the F5 key.

Restrictions and Problems with the Installation (MagicTune™)

The installation of MagicTune™may be affected by the graphics card, motherboard and the networking environment.

System Requirements

- OS
- Windows 2000
- Windows XP Home Edition
- Windows XP Professional
- Windows Vista
- · Windows 7 32Bit

For MagicTune™, Windows 2000 or later is recommended.

Hardware

- At least 32MB of memory
- At least 60MB of free space on the hard disk drive

For more information, refer to the website.

Removing the Software

You can only remove MagicTune™through [Add or Remove Programs] in Windows.

To remove MagicTune[™], complete the following steps.

1. Click [Start] select [Settings], and select [Control Panel] from the menu. For Windows XP, click [Start], and select [Control Panel] from the menu.

- 2. Double-click the [Add or Remove Programs] icon in the Control Panel.
- 3. In the [Add/Remove] window, find and select MagicTune™so that it is highlighted.
- 4. Click [Change or Remove Programs] to remove the software.
- 5. Select [Yes] to start removing MagicTune™.
- 6. Wait until a message box appears informing you that the software has been removed completely.
- For technical support, the FAQ (frequently asked questions) or information about the software upgrade for MagicTune™, please visit our website.

What is MultiScreen ?



MultiScreen enables users to use the monitor by partitioning multiple sections.

Installing the Software

- 1. Insert the installation CD into the CD-ROM drive.
- 2. Select the MultiScreen setup program.
 - If the pop-up screen for the software installation does not appear on the main screen, find and double-click the MultiScreen setup file on the CD-ROM.
- 3. When the Installation Wizard appears, click [Next].
- 4. Complete the remaining software installation steps according to the instructions displayed on the screen.
 - The software may not work properly if you do not restart the computer after the installation.
 - · The MultiScreen icon may not appear depending on the computer system and the product specifications.
 - If the shortcut icon does not appear, press the F5 key.

Restrictions and Problems with the Installation (MultiScreen)

The MultiScreen installation may be affected by the graphics card, motherboard and the networking environment.

Operating System

OS

- Windows 2000
- Windows XP Home Edition
- Windows XP Professional
- Windows Vista
- Windows 7 32Bit

For MultiScreen, the operating systems Windows 2000 or later is recommended.

Hardware

- At least 32MB of memory
- · At least 60MB of free space on the hard disk drive

Removing the Software

Click [Start], select [Settings]/[Control Panel], and then double-click [Add or Remove Programs].

Select MultiScreen from the program list and click the [Add/Delete] button.

5-1 Monitor Self-Diagnosis

- You can check if the product is working properly using the Self-Diagnosis function.
 - If a blank screen is displayed and the Power LED blinks even if the product and the PC are properly connected, perform the self-diagnosis function according to the procedures below.
- 1. Turn the product and the PC off.
- 2. Separate the D-Sub cable from the product .
- 3. Turn the product on.
- 4. If the product is working properly, the 'Check Signal Cable' message appears. In this case, if a blank screen is displayed again, make sure that there is no problem with the PC and the connection. The product is working properly.

5-2 Before Requesting Service

Please check the following before requesting After-Sales service. If the problem continues, please contact your nearest Samsung Electronics Service Center.

A BLANK SCREEN APPEARS / I C	ANNOT TURN THE PRODUCT ON
Is the power cord connected properly?	Check the connection status of the power cord.
Is the "Check Signal Cable" message displayed on the	Check the cable connecting the PC and the product.
screen?	If the message appears on the screen even if the cable is properly connected, recheck the input signal by pressing the the button of the product.
Is the "Not Optimum Mode" message displayed on the screen?	This occurs when the signal from the graphics card exceeds the maximum resolution or the maximum frequency of the product.
	In this case, set up the appropriate resolution and the fre- quency for the product.
Is a blank screen displayed and does the power LED blink at	This occurs when the power saving function is running.
a 1 second interval?	If you click the mouse or press any key, the screen will be turned on.
Did you connect with a DVI cable?	If you connect the DVI cable when the PC has booted up or if you reconnect the DVI cable after disconnecting the cable while using a PC, the screen may not be displayed because some graphics cards do not output the video signal.
	In this case, reboot the PC while the DVI cable is connected.
Blank spaces are found at the top and bottom of the screen	Blank spaces on the screen are not caused by the monitor.
when an HDMI or HDMI-DVI cable is connected to the moni- tor and PC.	The cause of the problem is the PC or graphics card, and can be fixed by adjusting the screen size in the HDMI or DVI option of the graphics card settings menu.
	If the graphics card settings menu has no option to adjust the screen size, update the graphics card driver to the latest version. (Please contact the graphics card or computer manufacturer
	for details on how to adjust the screen settings.)
	MENU (OSD) DOES NOT APPEAR.
Did you cancel the screen adjustment?	Check if the <osd adjustment="" lock=""> function is set to Off.</osd>
THE COLOR IS WEIRD / THE PICTURE	IS DISPLAYED IN BLACK AND WHITE
Is the entire screen displayed in the same color as if viewing	Check the cable connection to the computer.
the screen through a cellophane paper?	Reinsert the graphics card into the computer completely.
	Check if the <color effect=""> is set to <off>.</off></color>
Is the graphics card configured correctly?	Set up the graphics card referring to the user manual.
THE DISPLAY AREA SUDDENLY MOV	ES TO AN EDGE OR TO THE CENTER.
Did you change the graphics card or the driver?	Please press the [AUTO] button to run the auto adjustment function.
Did you change the resolution and frequency appropriate to the product?	Set the resolution and the frequency to the appropriate values in the graphics card
	refer to the (Standard Signal Mode Table)
Is the graphics card configured correctly?	Set up the graphics card referring to the user manual.

THE PICTURES ARE OUT-OF-FOCUS.		
Did you change the resolution and the frequency appropriate to the product?	Set the resolution and the frequency to the appropriate values in the graphics card	
	refer to the (Standard Signal Mode Table)	
THE COLOR IS DISPLAYED IN 16 BIT (16 COLORS). THE COLOR HAS BEEN CHANGED AFTER CHANGING THE GRAPHICS CARD.		
Did you install the device driver for the product?	Windows XP : Set the color again by selecting Control Panel \rightarrow Appearance and Themes \rightarrow Display \rightarrow Settings.	
	Windows ME/2000 : Set the color again by selecting Control Panel \rightarrow Display \rightarrow Settings.	
	Windows Vista : Change the color settings by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Personalization \rightarrow Display settings.	
	Windows 7 : Change the color settings by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Display \rightarrow Adjust resolution \rightarrow Advanced settings \rightarrow Monitor.	
	(For more information, refer to the Windows user manual for the computer.)	
Is the graphics card configured correctly?	Configure the color again in accordance with the new graph- ics card driver.	
WHEN I CONNECT THE MONITOR, THE 'UNKNOWN MONITOR, PLUG&PLAY (VESA DDC) MONITOR FOUND' MESSAGE IS DISPLAYED.		
Did you install the device driver for the product?	Install the device driver referring to the descriptions about the driver installation.	
Check if all the Plug&Play (VESA DDC) functions are supported referring to the User Manual of the graphics card.	Install the device driver referring to the descriptions about the driver installation.	
WHEN I LOOK AT THE EXTERIOR EDGES OF THE PRODUCT, SMALL ALIEN SUBSTANCES APPEAR ON IT.		

Since this product is designed so that the color has a soft appearance by coating it with a transparent material over the black edges, such things may be seen. This is not a defect of the product.

A "BEEP, BEEP" SOUND IS HEARD WHEN BOOTING THE COMPUTER.

If the beep sound is generated 3 or more times when booting up the computer, please request service for the computer.

5-3 FAQ

FAQ!	PLEASE TRY THE FOLLOWING!
How can I change the frequency of the video signal?	You have to change the frequency of the graphics card. Windows XP : Change the frequency by selecting Control Panel \rightarrow Appearance and Themes \rightarrow Display \rightarrow Settings \rightarrow Advanced \rightarrow Monitor, and then change the refresh rate under Monitor Settings.
	Windows ME/2000 : Change the frequency by selecting Con- trol Panel \rightarrow Display \rightarrow Settings \rightarrow Advanced \rightarrow Monitor, and then change the refresh rate under Monitor Settings.
	Windows Vista : Change the frequency by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Personalization
	\rightarrow Display settings \rightarrow Advanced settings \rightarrow Monitor, and then change the refresh rate under Monitor Settings.
	Windows 7 : Change the frequency by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Display \rightarrow Adjust resolution \rightarrow Advanced settings \rightarrow Monitor, and then change the refresh rate under Monitor Settings.
	(For more information, refer to the User Manual of the com- puter or the graphics card.)
How can I change the resolution?	Windows XP : Change the resolution by selecting Control Panel \rightarrow Appearance and Themes \rightarrow Display \rightarrow Settings.
	Windows ME/2000 : Change the resolution by selecting Control Panel \rightarrow Display \rightarrow Settings.
	Windows Vista : Change the resolution by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Personalization \rightarrow Display settings.
	Windows 7 : Change the resolution by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Display \rightarrow Adjust resolution.
	(For more information, refer to the User Manual of the com- puter or the graphics card.)
How can I use the power saving function?	Windows XP : Configure it by selecting Control Panel \rightarrow Appearance and Themes \rightarrow Display \rightarrow Screen Saver Setting or configure it in the BIOS Setup of the computer.
	Windows ME/2000 : Configure it by selecting Control Panel \rightarrow Display \rightarrow Screen Saver Setting or Configure it in the BIOS Setup of the computer.
	Windows Vista : Change settings by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Personalization \rightarrow Screen Saver. You can also use the BIOS SETUP menu on the PC.
	Windows 7 : Change settings by selecting Control Panel \rightarrow Appearance and Personalization \rightarrow Personalization \rightarrow Screen Saver. You can also use the BIOS SETUP menu on the PC.
	(For more information, refer to the Windows user manual for the computer.)

6-1 Specifications

MODEL NAME		P2770FH
LCD Panel Size		27 inches (68 cm)
	Display area	597.89 mm (H) x 336.31 mm (V)
	Pixel Pitch	0.3114 mm (H) x 0.3114 mm (V)
Synchroniza-	Horizontal	30 ~ 81 kHz
tion	Vertical	56 ~ 60 Hz
Display Color	·	16.7 M
Resolution	Optimum resolution	1920 x 1080 @ 60 Hz
	Maximum resolution	1920 x 1080 @ 60 Hz
		DVI-I(Analog/Digital), HDMI, Audio Out, Optical Out
Input Signal, T	erminated	0.7 Vp-p ± 5 %
input olgnai, T	erminated	Separate Type H/V Sync, Composite
		TTL Level (V high ≥ 2.0 V, V low ≤ 0.8 V)
Maximum Pixe	I Clock	164 MHz (Analog, Digital)
Power Supply		This product supports 100 - 240 V. Since the standard voltage may differ from country to country, please check the label on the back of the product.
		(Less than 30Ap-p at AC 120V or 50Ap-p at AC 220V)
Signal connect	ors	29Pin 3-row DVI-I Connector, HDMI connector, Audio Out, Optical Out
Dimensions (W	/xHxD) / Weight (Simple	667.0 × 422.0 × 63.0 mm / 26.3 × 16.6 × 2.5 inch (Without Stand)
stand)		667.0 × 484.0 × 244.0 mm / 26.3 × 19.1 × 9.6 inch / 6.7 kg / 14.8 lbs (With Stand)
Environmen- tal consider- ations	Operating	Temperature : 32°F ~ 104°F (0°C ~ 40°C)
		Humidity :20 % ~ 80 %, non-condensing
	Storage	Temperature : -4°F ~ 113°F (-20°C ~ 45°C)
		Humidity : 5 % ~ 95 %, non-condensing
Tilt		-2° ~ 21°

Class B (Information Communication equipment for residential use)

This device is registered for EMC requirements for home use (Class B). It can be used in all areas. (Class B equipment emits less electromagnetic waves than Class A equipment.)

Design and specifications are subject to change without prior notice.

6-2 Power Saving Function

This product provides a power saving function that automatically turns the screen off when the product is not used for a predetermined period of time to reduce power consumption. If the product enters power saving mode, the power LED turns to a different color to indicate that the product is in power saving mode.

When the product is in power saving mode, the power is not turned off and you can turn the screen on again by pressing any key or clicking the mouse. However, the power saving function only works when the product is connected to a computer that provides the power saving function.

STATE	NORMAL OPERATION	POWER SAVING MODE	POWER OFF
Power Indicator	On	Blinking	Off
Power Consumption	50 watts	1 watts	0.7 watts

 The actual power consumption may be different from the indicated power consumption above if the system conditions or settings are changed.

• If there is no power cut-off switch, the power consumption is "0" only when the power cord is disconnected.

6-3 Contact SAMSUNG WORLDWIDE

If you have any questions or comments relating to Samsung products, please contact the SAMSUNG customer care center.

NORTH AMERICA				
U.S.A	1-800-SAMSUNG(726-7864)	http://www.samsung.com		
CANADA	1-800-SAMSUNG(726-7864)	http://www.samsung.com		
MEXICO	01-800-SAMSUNG(726-7864)	http://www.samsung.com		
	LATIN AMERICA	-		
ARGENTINA	0800-333-3733	http://www.samsung.com		
BRAZIL	0800-124-421	http://www.samsung.com		
	4004-0000			
CHILE	800-SAMSUNG(726-7864)	http://www.samsung.com		
COLOMBIA	01-8000112112	http://www.samsung.com		
COSTA RICA	0-800-507-7267	http://www.samsung.com		
ECUADOR	1-800-10-7267	http://www.samsung.com		
EL SALVADOR	800-6225	http://www.samsung.com		
GUATEMALA	1-800-299-0013	http://www.samsung.com		
HONDURAS	800-7919267	http://www.samsung.com		
JAMAICA	1-800-234-7267	http://www.samsung.com		
NICARAGUA	00-1800-5077267	http://www.samsung.com		
PANAMA	800-7267	http://www.samsung.com		
PUERTO RICO	1-800-682-3180	http://www.samsung.com		
REP. DOMINICA	1-800-751-2676	http://www.samsung.com		
TRINIDAD & TOBAGO	1-800-SAMSUNG(726-7864)	http://www.samsung.com		
VENEZUELA	0-800-100-5303	http://www.samsung.com		
	EUROPE	1		
AUSTRIA	0810 - SAMSUNG(7267864,€ 0.07/min)	http://www.samsung.com		
BELGIUM	02-201-24-18	http://www.samsung.com/be (Dutch)		
		http://www.samsung.com/be_fr (French)		
CZECH	800 - SAMSUNG (800-726786)	http://www.samsung.com		
	Distributor pro Českou republiku: Samsung Zrt., česká organizační složka, Oasis	Distributor pro Českou republiku: Samsung Zrt., česká organizační složka, Oasis Florenc, Sokolovská394/17, 180 00, Praha 8		
DENMARK	70 70 19 70	http://www.samsung.com		
EIRE	0818 717100	http://www.samsung.com		
ESTONIA	800-7267	http://www.samsung.com		
FINLAND	030 - 6227 515	http://www.samsung.com		
FRANCE	01 48 63 00 00	http://www.samsung.com		

	EUROPE		
GERMANY	01805 - SAMSUNG (726-7864,€ 0,14/ Min)	http://www.samsung.com	
HUNGARY	06-80-SAMSUNG(726-7864)	http://www.samsung.com	
ITALIA	800-SAMSUNG(726-7864)	http://www.samsung.com	
LATVIA	8000-7267	http://www.samsung.com	
LITHUANIA	8-800-77777	http://www.samsung.com	
LUXEMBURG	261 03 710	http://www.samsung.com	
NETHERLANDS	0900 - SAMSUNG (0900-7267864) (€ 0,10/Min)	http://www.samsung.com	
NORWAY	815-56 480	http://www.samsung.com	
POLAND	0 801 1SAMSUNG (172678) 022 - 607 - 93 - 33	http://www.samsung.com	
PORTUGAL	80820 - SAMSUNG (726-7864)	http://www.samsung.com	
SLOVAKIA	0800-SAMSUNG(726-7864)	http://www.samsung.com	
SPAIN	902 - 1 - SAMSUNG (902 172 678)	http://www.samsung.com	
SWEDEN	0771 726 7864 (SAMSUNG)	http://www.samsung.com	
SWITZERLAND	0848-SAMSUNG(7267864, CHF 0.08/	http://www.samsung.com/ch	
	min)	http://www.samsung.com/be_fr (French)	
U.K	0845 SAMSUNG (7267864)	http://www.samsung.com	
	CIS		
ARMENIA	0-800-05-555		
AZERBAIJAN	088-55-55-555		
BELARUS	810-800-500-55-500		
GEORGIA	8-800-555-555		
KAZAKHSTAN	8-10-800-500-55-500		
KYRGYZSTAN	00-800-500-55-500	http://www.samsung.com	
MOLDOVA	00-800-500-55-500		
RUSSIA	8-800-555-55-55	http://www.samsung.com	
TADJIKISTAN	8-10-800-500-55-500	http://www.samsung.com	
UKRAINE	0-800-502-000	http://www.samsung.com/ua	
		http://www.samsung.com/ua_ru	
UZBEKISTAN	8-10-800-500-55-500	http://www.samsung.com	
	ASIA PACIFIC		
AUSTRALIA	1300 362 603	http://www.samsung.com	
AUSTRALIA			
	400-810-5858	http://www.samsung.com	
CHINA	400-810-5858 010-6475 1880	http://www.samsung.com	
		http://www.samsung.com http://www.samsung.com/hk	

ASIA PACIFIC				
INDIA	3030 8282 1800 110011 1800 3000 8282 1800 266 8282	http://www.samsung.com		
INDONESIA	0800-112-8888 021-5699-7777	http://www.samsung.com		
JAPAN	0120-327-527	http://www.samsung.com		
MALAYSIA	1800-88-9999	http://www.samsung.com		
NEW ZEALAND	0800 SAMSUNG (0800 726 786)	http://www.samsung.com		
PHILIPPINES	1-800-10-SAMSUNG(726-7864) 1-800-3-SAMSUNG(726-7864) 1-800-8-SAMSUNG(726-7864) 02-5805777	http://www.samsung.com		
SINGAPORE	1800-SAMSUNG(726-7864)	http://www.samsung.com		
TAIWAN	0800-329-999	http://www.samsung.com		
THAILAND	1800-29-3232 02-689-3232	http://www.samsung.com		
VIETNAM	1 800 588 889	http://www.samsung.com		
MIDDLE EAST & AFRICA				
BAHRAIN	8000-4726			
JORDAN	800-22273			
SOUTH AFRICA	0860-SAMSUNG(726-7864)	http://www.samsung.com		
TURKEY	444 77 11	http://www.samsung.com		
U.A.E	800-SAMSUNG(726-7864)	http://www.samsung.com		

6-4 Correct Disposal of This Product (Waste Electrical & Electronic Equipment) - Europe only



(Applicable in the European Union and other European countries with separate collection systems)

This marking on the product, accessories or literature indicates that the product and its electronic accessories (e.g. charger, headset, USB cable) should not be disposed of with other household waste at the end of their working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate these items from other types of waste and recycle them responsibly to promote the sustainable reuse of material resources.

Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take these items for environmentally safe recycling.

Business users should contact their supplier and check the terms and conditions of the purchase contract. This product and its electronic accessories should not be mixed with other commercial wastes for disposal.