

www.philips.com/welcome

EN User manual 1
Customer care and warranty 20
Troubleshooting & FAQs 24



Table of Contents

1.	Important
2.	Setting up the monitor
3.	Image Optimization123.1 SmartImage123.2 SmartContrast13
4.	Technical Specifications
5.	Power Management19
6.	Customer care and warranty20 6.1 Philips' Flat Panel Monitors Pixel Defect Policy20 6.2 Customer Care & Warranty23
7.	Troubleshooting & FAQs24 7.1 Troubleshooting24 7.2 General FAOs25



1. Important

This electronic user's guide is intended for anyone who uses the Philips monitor. Take time to read this user's manual before you use your monitor. It contains important information and notes regarding the operation of your monitor.

The Philips guarantee applies provided the product is handled properly for its intended use, in accordance with its operating instructions and upon presentation of the original invoice or cash receipt, indicating the date of purchase, dealer's name and model and production number of the product.

1.1 Safety precautions and maintenance

Warnings

Use of controls, adjustments or procedures other than those specified in this documentation may result in exposure to shock, electrical hazards and/or mechanical hazards.

Read and follow these instructions when connecting and using your computer monitor.

Operation

- Please Keep the monitor out of direct sunlight, very strong bright lights and away from any other heat source. Lengthy exposure to this type of environment may result in discoloration and damage to the monitor.
- Remove any object that could fall into ventilation holes or prevent proper cooling of the monitor's electronics.
- Do not block the ventilation holes on the cabinet.

- When positioning the monitor, make sure the power plug and outlet are easily accessible.
- If turning off the monitor by detaching the power cable or DC power cord, wait for 6 seconds before attaching the power cable or DC power cord for normal operation.
- Please use approved power cord provided by Philips at all times. If your power cord is missing, please contact your local service center. (Please refer to Customer Care Consumer Information Center)
- Do not subject the monitor to severe vibration or high impact conditions during operation.
- Do not knock or drop the monitor during operation or transportation.

Maintenance

- To protect your monitor from possible damage, do not put excessive pressure on the LCD panel. When moving your monitor, grasp the frame to lift; do not lift the monitor by placing your hand or fingers on the LCD panel.
- Unplug the monitor if you are not going to use it for an extensive period of time.
- Unplug the monitor if you need to clean it with a slightly damp cloth.
 The screen may be wiped with a dry cloth when the power is off.
 However, never use organic solvent, such as, alcohol, or ammonia-based liquids to clean your monitor.
- To avoid the risk of shock or permanent damage to the set, do not expose the monitor to dust, rain, water, or excessive moisture environment.
- If your monitor gets wet, wipe it with dry cloth as soon as possible.
- If foreign substance or water gets in your monitor, please turn the power

. Important

- off immediately and disconnect the power cord. Then, remove the foreign substance or water, and send it to the maintenance center.
- Do not store or use the monitor in locations exposed to heat, direct sunlight or extreme cold.
- In order to maintain the best performance of your monitor and use
 it for a longer lifetime, please use
 the monitor in a location that falls
 within the following temperature
 and humidity ranges.
 - Temperature: 0-40°C 32-104°F
 - Humidity: 20-80% RH
- IMPORTANT: Always activate a moving screen saver program when you leave your monitor unattended.
 Always activate a periodic screen refresh application if your monitor will display unchanging static content. Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or "ghost imaging", on your screen.
- "Burn-in", "after-imaging", or "ghost imaging" is a well-known phenomenon in LCD panel technology.
 In most cases, the "burned in" or "after-imaging" or "ghost imaging" will disappear gradually over a period of time after the power has been switched off

Warning

Failure to activate a screen saver, or a periodic screen refresh application may result in severe "burn-in" or "afterimage" or "ghost image" symptoms that will not disappear and cannot be repaired. The damage mentioned above is not covered under your warranty.

Service

- The casing cover should be opened only by qualified service personnel.
- If there is any need for any document for repair or integration,
 please contact with your local
 service center. (please refer to the
 chapter of "Consumer Information
 Center")
- For transportation information, please refer to "Technical Specifications".
- Do not leave your monitor in a car/ trunk under direct sun light.



Consult a service technician if the monitor does not operate normally, or you are not sure what procedure to take when the operating instructions given in this manual have been followed.

1.2 Notational Descriptions

The following subsections describe notational conventions used in this document.

Notes, Cautions and Warnings

Throughout this guide, blocks of text may be accompanied by an icon and printed in bold or italic type. These blocks contain notes, cautions or warnings. They are used as follows:

■ Note

This icon indicates important information and tips that help you make better use of your computer system.

Caution

This icon indicates information that tells you how to avoid either potential damage to hardware or loss of data.

Warning

This icon indicates the potential for bodily harm and tells you how to avoid the problem.

Some warnings may appear in alternate formats and may not be accompanied by an icon. In such cases, the specific presentation of the warning is mandated by the relevant regulatory authority.

1.3 Disposal of product and packing material

Waste Electrical and Electronic Equipment-WEEE



This marking on the product or on its packaging illustrates that, under European Directive 2012/19/EU governing used electrical and electronic appliances, this product may not be disposed of with normal household waste. You are responsible for disposal of this equipment through a designated waste electrical and electronic equipment collection. To determine the locations for dropping off such waste electrical and electronic, contact your local government office, the waste disposal organization that serves your household or the store at which you purchased the product.

Your new monitor contains materials that can be recycled and reused. Specialized companies can recycle your product to increase the amount of reusable materials and to minimize the amount to be disposed of.

All redundant packing material has been omitted. We have done our utmost to make the packaging easily separable into mono materials.

Please find out about the local regulations on how to dispose of your old monitor and packing from your sales representative.

Taking back/Recycling Information for Customers

Setting up the monitor

Philips establishes technically and economically viable objectives to optimize the environmental performance of the organization's product, service and activities.

From the planning, design and production stages, Philips emphasizes the important of making products that can easily be recycled. At Philips, end-of-life management primarily entails participation in national takeback initiatives and recycling programs whenever possible, preferably in cooperation with competitors, which recycle all materials (products and related packaging material) in accordance with all Environmental Laws and taking back program with the contractor company.

Your display is manufactured with high quality materials and components which can be recycled and reused.


To learn more about our recycling program please visit

http://www.philips.com/a-w/about/sustainability.html

2. Setting up the monitor


2.1 Installation

Package contents




* Different according to region.

- Install base stand
- Place the monitor face down on soft and smooth surface taking care to avoid scratching or damaging the screen.
- 2. Attach/Slide the base column with the monitor until it clicks into position.




3. Hold the monitor base stand with both hands and firmly insert the base stand into the base column.



2. Setting up the monito


Connecting to your PC

2X3V7QS




- 1 AC power input
- 2 VGA input
- 3 DVI-D input
- 4 Kensington anti-theft lock

2X3V7QHA




- 1 AC power input
- **2** VGA input
- 3 HDMI input
- 4 Earphone output
- 5 Audio input
- 6 Kensington anti-theft lock

2X3V7QHS



- 1 AC power input
- 2 VGA input
- 3 HDMI input
- 4 HDMI audio out
- **5** Kensington anti-theft lock


2X3V7QDA



- AC power input
- **2** VGA input
- 3 DVI-D input
- 4 HDMI input
- **5** Earphone output
- 6 Audio input
- **7** Kensington anti-theft lock


Setting up the monito

2X3V7QDS



- 1 AC power input
- 2 VGA input
- 3 DVI-D input
- 4 HDMI input
- **5** HDMI audio out
- 6 Kensington anti-theft lock

2X3V7QJA




- 1 AC power input
- 2 VGA input
- 3 HDMI input
- 4 DisplayPort input
- **5** Earphone output
- 6 Audio input
- **7** Kensington anti-theft lock


Connect to PC

- 1. Connect the power cord to the back of the monitor firmly.
- 2. Turn off your computer and unplug its power cable.
- 3. Connect the monitor signal cable to the video connector on the back of your computer.
- Plug the power cord of your computer and your monitor into a nearby outlet.
- 5. Turn on your computer and monitor. If the monitor displays an image, installation is complete.

2.2 Operating the monitor


1 Front view product description 2X3V7QS, 2X3V7QHS, 2X3V7QDS






0	Ф	Switch monitor's power ON and OFF.
2	■/OK	Access the OSD menu. Confirm the OSD adjustment.
3	\blacksquare	Adjust the OSD menu.
4	Ö	Adjust the brightness level.
6	•	Change the signal input source.
6	4	Return to previous OSD level.
0	回	SmartImage. There are multiple selections: EasyRead, Office, Photo, Movie, Game, Economy, LowBlue Mode and Off.

2X3V7QHA, 2X3V7QDA, 2X3V7QJA






0	Ф	Switch monitor's power ON and OFF.
2	■/OK	Access the OSD menu. Confirm the OSD adjustment.
3		Adjust the OSD menu.
4	I	Adjust the speaker volume.
6	•	Change the signal input source.
6	4	Return to previous OSD level.
7	町	SmartImage. There are multiple selections: EasyRead, Office, Photo, Movie, Game, Economy, LowBlue Mode and Off.

Description of the On Screen Display


What is On-Screen Display (OSD)?

On-Screen Display (OSD) is a feature in all Philips LCD monitors. It allows an end user to adjust screen performance or select functions of the monitors directly through an on-screen instruction window. A user friendly on screen display interface is shown as below:

2X3V7OS



2X3V7QH, 2X3V7QD, 2X3V7QJ




Basic and simple instruction on the control keys

In the OSD shown above, you can press ▼ ▲ buttons at the front bezel of the monitor to move the cursor, and press OK button to confirm the choice or change.

The OSD Menu

Below is an overall view of the structure of the On-Screen Display. You can use this as a reference when you want to work your way around the different adjustments later on.



2. Setting up the monito


Resolution notification

This monitor is designed for optimal performance at its native resolution, 1920×1080 @ 60 Hz. When the monitor is powered on at a different resolution, an alert is displayed on screen: Use 1920 \times 1080 @ 60 Hz for best results.

Display of the native resolution alert can be switched off from Setup in the OSD (On Screen Display) menu.

4 Physical Function

Tilt




2.3 Remove the Base Assembly for VESA Mounting


Remove the Base Stand

Before you start disassembling the monitor base, please follow the instructions below to avoid any possible damage or injury.


 Place the monitor face down on a smooth surface, taking care to avoid scratching or damaging the screen.



2. Press the locking clips to detach the base stand away from the base column.




3. Press the release button to detach the base column.



Note

This monitor accepts a 100mm x 100mm VESA-Compliant mounting interface. VESA Mounting Screw M4. Always contact manufacturer for wall-mount installation.



3. Image Optimization

3.1 SmartImage

What is it?

SmartImage provides presets that optimize display for different types of content, dynamically adjusting brightness, contrast, color and sharpness in real time. Whether you're working with text applications, displaying images or watching a video, Philips SmartImage delivers great optimized monitor performance.


2 Why do I need it?

You want a monitor that delivers optimized display all your favorite types of content, SmartImage software dynamically adjust brightness, contrast, color and sharpness in real time to enhance your monitor viewing experience.

3 How does it work?

SmartImage is an exclusive, leading edge Philips technology that analyzes the content displayed on your screen. Based on a scenario you select, SmartImage dynamically enhances the contrast, color saturation and sharpness of images to enhance the contents being displayed – all in real time with the press of a single button.

4 How to enable SmartImage?



- 1. Press to launch the SmartImage on screen display.
- Keep pressing ▼ ▲ to toggle among EasyRead, Office, Photo, Movie, Game, Economy, LowBlue Mode and Off
- 3. The SmartImage on screen display will remain on screen for 5 seconds, or you can also press "OK" to make confirmation

There are multiple selections: EasyRead, Office, Photo, Movie, Game, Economy, LowBlue Mode and Off.



- EasyRead: Helps improve reading of text based application like PDF ebooks. By using a special algorithm which increases the contrast and boundary sharpness of text content, the display is optimized for a stress-free reading by adjusting the brightness, contrast and color temperature of the monitor.
- Office: Enhances text and dampens brightness to increase readability and reduce eye strain. This mode significantly enhances readability and productivity when you're working with spreadsheets, PDF files, scanned articles or other general office applications.

3. Image Optimizatior

- Photo: This profile combines color saturation, dynamic contrast and sharpness enhancement to display photos and other images with outstanding clarity in vibrant colors

 all without artifacts and faded colors.
- Movie: Ramped up luminance, deepened color saturation, dynamic contrast and razor sharpness displays every details in darker areas of your videos without color washout in brighter areas maintaining a dynamic natural values for the ultimate video display.
- Game: Turn on over drive circuit for best response time, reduce jaggy edges for fast moving objects on screen, enhance contrast ratio for bright and dark scheme, this profile delivers the best gaming experience for gamers.
- Economy: Under this profile, brightness, contrast are adjusted and backlighting finetuned for just right display of everyday office applications and lower power consumption.
- LowBlue Mode: LowBlue Mode
 for easy on-the-eyes productivity
 Studies have shown that just as
 ultra-violet rays can cause eye
 damage, shortwave length blue light
 rays from LED displays can cause
 eye damage and affect vision over
 time. Developed for wellbeing,
 Philips LowBlue Mode setting uses a
 smart software technology to reduce
 harmful shortwave blue light.
- Off: No optimization by SmartImage.

3.2 SmartContrast

1 What is it?

Unique technology that dynamically analyzes displayed content and automatically optimizes a Monitor's contrast ratio for maximum visual clarity and viewing enjoyment, stepping up backlighting for clearer, crisper and brighter images or dimming backlighting for clear display of images on dark backgrounds.

2 Why do I need it?

You want the very best visual clarity and viewing comfort for every type of content. SmartContrast dynamically controls contrast and adjusts backlighting for clear, crisp, bright gaming and video images or displays clear, readable text for office work. By reducing your monitor's power consumption, you save on energy costs and extend the lifetime of your monitor.

3 How does it work?

When you activate SmartContrast, it will analyse the content you are displaying in real time to adjust colors and control backlight intensity. This function will dynamically enhance contrast for a great entertainment experience when viewing videos or playing games.

4. Technical Specifications

Monitor Panel Type	Picture/Display		
Backlight W-LED system 223V7: 21.5" W (54.6 cm) 243V7: 23.8" W (60.5 cm) 273V7: 27" W (68.6 cm) 273V7: 27" W (68.6 cm) 273V7: 27" W (68.6 cm) 223V7: 0.248 x 0.248 mm 243V7: 0.275 x 0.275 mm 273V7: 0.311 x 0.311 x 0.311 mm 273V7: 0.31 x 0.311 x 0.311 mm 273V7: 0.31 x 0.311 x 0.311 mm 273V7: 0.31 x 0.311	Monitor Panel Type	IPS Technology	
Panel Size	Backlight	W-LED system	
Aspect Ratio 16:9 223V7: 0.248 x 0.248 mm 223V7: 0.275 x 0.275 mm 223V7: 0.311 x 0.311 mm 273V7: 0.311 x 0.311 mm 273V7QI.		223V7: 21.5" W (54.6 cm)	
Aspect Ratio 16:9 223V7: 0.248 x 0.248 mm 243V7: 0.275 x 0.275 mm 243V7: 0.311 x 0.311 mm 243V7: 0.311 mm 243V7QH; 233V7QH; 233V7QH; 233V7QH; 233V7QH; 233V7QH; 243V7QH;	Panel Size	243V7: 23.8" W (60.5 cm)	
Pixel Pitch		273V7: 27" W (68.6 cm)	
Pixel Pitch	Aspect Ratio	16:9	
273V7: 0.311 x 0.311 mm SmartContrast 10,000,000:1 Response Time (typ.) Smart Response (typ.) (2X3V7QH, 2X3V7QD, 2X3V7QD, 2X3V7QJ) Optimum Resolution Viewing Angle (typ.) Picture Enhancement Display Colors Vertical Refresh Rate Display Colors Vertical Refresh Rate Horizontal Frequency SRGB YES Flicker Free LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QD: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), HDMI(Digital), DisplayPort(Digital) 2X3V7QD: VGA(Analog), HDMI(Digital), DisplayPort(Digital) 2X3V7QD: VGA(Analog), HDMI(Digital) 2X3V7Q		223V7: 0.248 x 0.248 mm	
SmartContrast Response Time (typ.) Smart Response (typ.) (2X3V7QH, 2X3V7QD, 2X3V7QD, 2X3V7QJ) Optimum Resolution Viewing Angle (typ.) Picture Enhancement Display Colors Vertical Refresh Rate Horizontal Frequency SRGB Flicker Free LowBlue Mode YES Connectivity 2X3V7QJ: VGA(Analog), DVI(Digital) 2X3V7QJ: VGA(Analog), DVI(Digital), DisplayPort(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Input Signal Separate Sync, Sync on Green 2X3V7QH, 2X3V7QDA, 2X3V7QJA: PC audio—in,headphone out 2X3V7QHS, 2X3V7QDA, 2X3V7QDA, 2X3V7QJA) Convenience Built—in speakers(typ.) User Convenience User Convenience 10,000,0000: Sms (GtG) Sms (Gt) Sms (GtG) Sms (Gt) Sms (GtG) Sms (Gt) Sms (Gt) Spms	Pixel Pitch	243V7: 0.275 x 0.275 mm	
Response Time (typ.) Smart Response (typ.) (2X3V7QH, 2X3V7QD, 2X3V7QJ) Optimum Resolution Viewing Angle (typ.) Picture Enhancement Display Colors Vertical Refresh Rate Horizontal Frequency SRGB Flicker Free LowBlue Mode YES Connectivity 2X3V7QD: VGA(Analog), DVI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), DisplayPort(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), DisplayPort(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), DisplayPort(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio—in,headphone out 2X3V7QHA, 2X3V7QDS: HDMI audio out Convenience Built—in speakers(typ.) User Convenience User Convenience 8 W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QDA) 2X3V7QHA, 2X3V7QDA, 2X3V7QDA; ©P/		273V7: 0.311 x 0.311 mm	
Smart Response (typ.) (2X3V7QH, 2X3V7QD, 2X3V7QJ) Optimum Resolution Viewing Angle (typ.) Picture Enhancement Display Colors Vertical Refresh Rate Horizontal Frequency SRGB Flicker Free LowBlue Mode Connectivity 2X3V7QE: VGA(Analog), DVI(Digital) 2X3V7QB: VGA(Analog), DVI(Digital) 2	SmartContrast	10,000,000:1	
Canalogy	Response Time (typ.)	8ms (GtG_BW)	
Optimum Resolution Viewing Angle (typ.) Picture Enhancement Display Colors 16.7M Vertical Refresh Rate Horizontal Frequency SRGB Flicker Free LowBlue Mode Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital) 2X3V7QJA: PC audio- in,headphone out 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QDA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □ / ● / ▼ ※ / ▲ □ / OK		5ms (GtG)	
Viewing Angle (typ.) 178° (H) / 178° (V) @ C/R > 10 Picture Enhancement SmartImage Display Colors 16.7M Vertical Refresh Rate 56Hz - 76Hz Horizontal Frequency 30kHz - 83kHz \$RGB YES Flicker Free YES LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) Signal Input 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audionin,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QDA, 2X3V7QJA) User Convenience ©/ ©/ User Convenience 2X3V7QHA, 2X3V7QDA, 2X3V7QDA:	2X3V7QJ)		
Picture Enhancement Display Colors 16.7M Vertical Refresh Rate Horizontal Frequency \$RGB Flicker Free LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), DVI(Digital) 2X3V7QJ: VGA(Analog), DVI(Digital) 2X3V7QJ: VGA(Analog), DVI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) User Convenience Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QDA, 2X3V7QJA) 2X3V7QHS, 2X3V7QDB, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/◀ ⊕/▼ □/♥ □/♥ □/♥ □/♥ □/♥ □/♥ □/♥ □/♥ □/♥ □/♥	Optimum Resolution	1920 x 1080 @ 60Hz	
Display Colors Vertical Refresh Rate Horizontal Frequency \$RGB YES Flicker Free LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QJ: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) User Convenience 16.7M 208HZ - 76HZ 30kHz - 76HZ 404(Analog) 405(Digital) 405(Digital) 406(Digital)	Viewing Angle (typ.)	178° (H) / 178° (V) @ C/R > 10	
Vertical Refresh Rate Horizontal Frequency 30kHz - 83kHz \$RGB Flicker Free YES LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio—in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/◀ ⊕/▼ ☆/▲ □/OK ⊕ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Picture Enhancement	SmartImage	
SRGB YES	Display Colors	16.7M	
Flicker Free LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/ ◆ /▼ ☆/ ▲ □/OK ◆ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Vertical Refresh Rate	56Hz - 76Hz	
Flicker Free LowBlue Mode YES Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/ ◆ /▼ ☆/ ▲ □/OK ◆ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Horizontal Frequency	30kHz - 83kHz	
LowBlue Mode Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/ ◆ /▼ ☆/ ▲ □/OK ◆ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	sRGB	YES	
Connectivity 2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □ ✓ ◆ ✓ ☆ ▲ □ / OK ◆ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Flicker Free	YES	
2X3V7QS: VGA(Analog), DVI(Digital) 2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □ ✓ ◆ /▼ ☆ / ▲ □ / OK	LowBlue Mode	YES	
2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital) Input Signal Separate Sync, Sync on Green 2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio- in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/ ◆ ◆/ ▼ ☆/ ▲ □/OK ⊕ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Connectivity		
2X3V7QHA, 2X3V7QDA, 2X3V7QJA: PC audio-in,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: ☑/◀ ④/▼ ☆/▲ 圖/OK ① 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	· ·	2X3V7QH: VGA(Analog), HDMI(Digital) 2X3V7QD: VGA(Analog), DVI(Digital), HDMI(Digital) 2X3V7QJ: VGA(Analog), HDMI(Digital), DisplayPort(Digital)	
In,headphone out 2X3V7QHS, 2X3V7QDS: HDMI audio out Convenience Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: □/ ◆ ◆/ ▼ ☆/ ▲ □/OK ◆ 2X3V7QHA, 2X3V7QDA, 2X3V7QJA:	Input Signal	Separate Sync, Sync on Green	
Built-in speakers(typ.) 2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA) 2X3V7QS, 2X3V7QHS, 2X3V7QDS: ② / ▼	Audio in/out	in,headphone out	
2X3V7QS, 2X3V7QHS, 2X3V7QDS: ⑤ (□) (■	Convenience		
User Convenience	Built-in speakers(typ.)	2W x 2 (2X3V7QHA, 2X3V7QDA, 2X3V7QJA)	
	User Convenience		

4. Technical Specificatio	4. Technical Specifications					
Picture/Display Picture						
OSD Languages		English, French, German, Spanish, Italian, Russian, Simplified Chinese, Portuguese, Turkish, Dutch, Swedish, Finnish, Polish, Czech, Korean, Japanese, Hungarian, Ukraine, Brazil Portuguese, Greek, Traditional Chinese				
Other Convenience		Kensington L	_ock			
Plug & Play Compati	ibility	DDC/CI, sRGB, Windows 7/Windows 8/Windows 8.1/ Windows 10, Mac OSX				
VESA mount		100x100 mm	1			
Stand						
Tilt		-5 / +20				
Power (223V7)						
Consumption	at 100	out Voltage OVAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz		
Normal Operation		V (typ.)	20.01 W (typ.)	20.63 W (typ.)		
Sleep(Standby)	<0.5 W		<0.5 W	<0.5 W		
Off	<0.5 W	/	<0.5 W	<0.5 W		
Heat Dissipation*		out Voltage OVAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz		
Normal Operation	77.52 E	BTU/hr(typ.)	78.50 BTU/hr(typ.)	80.97 BTU/hr(typ.)		
Sleep(Standby)	<1.71 B	TU/hr	<1.71 BTU/hr	<1.71 BTU/hr_		
Off	<1.71 BTU/hr		<1.71 BTU/hr	<1.71 BTU/hr_		
Power LED indicator	On mo	ode: White, Sta	andby/Sleep mode: W	hite (blinking)		
Power Supply	Built-i	n,100-240V A	C, 50-60Hz			
Power (243V7)						
Consumption		out Voltage OVAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz		
Normal Operation	20.52	W (typ.)	20.89 W (typ.)	21.25 W (typ.)		
Sleep(Standby)	<0.5 W	<u> </u>	<0.5 W	<0.5 W		
Off	<0.5 W	/	<0.5 W	<0.5 W		
Heat Dissipation*		out Voltage OVAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz		
Normal Operation	67.58 I	BTU/hr(typ.)	70.10 BTU/hr(typ.)	71.67 BTU/hr(typ.)		
Sleep(Standby)	<1.71 B		<1.71 BTU/hr	<1.71 BTU/hr_		
Off	<1.71 B	TU/hr	<1.71 BTU/hr	<1.71 BTU/hr_		
Power LED indicator			andby/Sleep mode: W	hite (blinking)		
Power Supply	Power Supply Built-in,100-240V AC, 50-60Hz					
Power (273V7QS, 27	3V7QD,	273V7QH)				
Consumption	AC Inp	out Voltage OVAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz		
Name of Organists	2007	\ \ / /± \	25 00 14/ (+)	25.70 \\/ (+ \		

25.99 W (typ.)

25.70 W (typ.)

26.07 W (typ.)

Normal Operation

4. Technical Specifications

Sleep(Standby)	<0.5 W	<0.5 W	<0.5 W	
Off	<0.5 W	<0.5 W	<0.5 W	
Heat Dissipation*	AC Input Voltage at 100VAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz	
Normal Operation	88.98 BTU/hr(typ.)	88.74 BTU/hr(typ.)	85.56 BTU/hr(typ.)	
Sleep(Standby)	<1.71 BTU/hr	<1.71 BTU/hr	<1.71 BTU/hr_	
Off	<1.71 BTU/hr <1.71 BTU/hr <1.71 BTU/hr_			
Power LED indicator	On mode: White, Standby/Sleep mode: White (blinking)			
Power Supply	Built-in,100-240V AC, 50-60Hz			

Power (273V7QJ)	Power (273V7QJ)					
Consumption	AC Input Voltage at 100VAC, 50Hz	AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz			
Normal Operation	25.17 W (typ.)	24.99 W (typ.)	25.19 W (typ.)			
Sleep(Standby)	<0.5 W	<0.5 W	<0.5 W			
Off	<0.3 W	<0.3 W	<0.3 W			
Heat Dissipation* AC Input Voltage at 100VAC, 50Hz		AC Input Voltage at 115VAC, 50Hz	AC Input Voltage at 230VAC, 50Hz			
Normal Operation	85.92 BTU/hr(typ.)	85.29 BTU/hr(typ.)	85.96 BTU/hr(typ.)			
Sleep(Standby)	<1.71 BTU/hr	<1.71 BTU/hr	<1.71 BTU/hr_			
Off	<1.02BTU/hr <1.02 BTU/hr <1.02BTU/hr_					
Power LED indicator	On mode: White, Standby/Sleep mode: White (blinking)					
Power Supply	Built-in,100-240V AC, 50-60Hz					

Dimension	
Product with stand (WxHxD)	490 x 368 x 195 mm(223V7) 540 x 415 x 209 mm(243V7) 612 x 453 x 227 mm(273V7)
Product without stand (WxHxD)	490 x 296 x 45 mm(223V7) 540 x 325 x 45 mm(243V7) 612 x 367 x 45 mm(273V7)
Product with packaging (WxHxD)	575 x 440 x 113 mm(223V7) 588 x 465 x 115 mm(243V7) 664 x 452 x 134 mm(273V7)
Weight	
Product with stand	2.92 kg(223V7) 3.50 kg(243V7) 4.50 kg(273V7)
Product without stand	2.56 kg(223V7) 3.10 kg(243V7QS, 243V7QD, 243V7QH) 3.08 kg(243V7QJ) 4.04 kg(273V7)

4. Technical Specifications

Product with packaging	4.23 kg(223V7) 4.82 kg(243V7) 6.07 kg(273V7QS, 273V7QD, 273V7QH) 6.09 kg(273V7QJ)				
Operating Condition					
Temperature range (operation)	0°C to 40 °C				
Relative humidity (operation)	20% to 80%				
Atmospheric pressure (operation)	700 to 1060hPa				
Temperature range (Non-operation)	-20°C to 60°C				
Relative humidity (Non-operation)	10% to 90%				
Atmospheric pressure (Non-operation)	500 to 1060hPa				
Environmental					
ROHS	YES				
EPEAT	YES (Refer to note1 for more details)				
Packaging	100% recyclable				
Specific Substances	100% PVC BFR free housing				
EnergyStar	YES				
Compliance and standards					
Regulatory Approvals	CU, Semko, ETL, ISO9241-307, WEEE, TCO Certified, CE Mark, FCC Class B, ICES-003, RCM, UKRAINIAN, VCCI CLASS B(2X3V7QHS, 2X3V7QDS), KCC(2X3V7QDA, 243V7QDS, 273V7QJA), CCC, CECP(2X3V7QS, 2X3V7QHS, 2X3V7QDS), BSMI(2X3V7QHA, 2X3V7QDA)				
Cabinet					
Color	Black				
Finish	Texture				



- 1. EPEAT Gold or Silver is valid only where Philips registers the product. Please visit www.epeat.net for registration status in your country.
- 2. This data is subject to change without notice. Go to www.philips.com/support to download the latest version of leaflet.
- 3. Smart response time is the optimum value from either GtG or GtG (BW) tests.

4.1 Resolution & Preset Modes

Maximum Resolution 1920x1080@60Hz (analog input) 1920x1080@60Hz (digital input)

Recommended Resolution 1920x1080@60Hz (analog input)

H. freq (kHz)	Resolution	V. freq (Hz)
31.47	720 x 400	70.09
31.47	640 x 480	59.94
35.00	640 x 480	66.67
37.86	640 x 480	72.81
37.50	640 x 480	75.00
35.16	800 x 600	56.25
37.88	800 x 600	60.32
48.08	800 x 600	72.19
46.88	800 x 600	75.00
47.73	832 x 624	74.55
48.36	1024 x 768	60.00
56.48	1024 x 768	70.07
60.02	1024 x 768	75.03
44.77	1280 x 720	59.86
60.00	1280 x 960	60.00
63.89	1280 x 1024	60.02
79.98	1280 x 1024	75.03
55.94	1440 x 900	59.89
70.64	1440 x 900	74.98
65.29	1680 x 1050	59.95
67.50	1920 x 1080	60.00

Note

Please notice that your display works best at native resolution of 1920 x 1080 @ 60Hz. For best display quality,please follow this resolution recommendation.

5. Power Management

If you have VESA DPM compliance display card or software installed in your PC, the monitor can automatically reduce its power consumption when not in use. If an input from a keyboard, mouse or other input device is detected, the monitor will 'wake up' automatically. The following table shows the power consumption and signaling of this automatic power saving feature:

223V7

Power Management Definition							
VESA Mode	Video	H-sync	V-sync	Power Used	LED Color		
Active	ON	Yes	Yes	21.18 W (typ.) 29.56 W (Max.)	White		
Sleep	OFF	No	No	0.5 W (typ.)	White (blink)		
Switch Off	OFF	-	-	0.5 W (typ.)	OFF		

243V7

Power Management Definition							
VESA Mode	Video	H-sync	V-sync	Power Used	LED Color		
Active	ON	Yes	Yes	21.39 W (typ.) 26.64 W (Max.)	White		
Sleep	OFF	No	No	0.5 W (typ.)	White (blink)		
Switch Off	OFF	-	-	0.5 W (typ.)	OFF		

273V7QS, 273V7QD, 273V7QH

Power Management Definition						
VESA Mode	Video	H-sync	V-sync	Power Used	LED Color	
Active	ON	Yes	Yes	26.38 W (typ.) 34.54 W (Max.)	White	
Sleep	OFF	No	No	0.5 W (typ.)	White (blink)	
Switch Off	OFF	-	-	0.5 W (typ.)	OFF	

273V7OJ

Power Management Definition						
VESA Mode	Video	H-sync	V-sync	Power Used	LED Color	
Active	ON	Yes	Yes	25.28 W (typ.) 37.05 W (Max.)	White	
Sleep	OFF	No	No	0.5 W (typ.)	White (blink)	
Switch Off	OFF	-	-	0.3 W (typ.)	OFF	

The following setup is used to measure power consumption on this monitor.

Native resolution: 1920x1080

Contrast: 50% Brightness: 100%;

 Color temperature: 6500k with full white pattern


Note

This data is subject to change without notice.

Customer care and warranty

6.1 Philips' Flat Panel Monitors Pixel Defect Policy

Philips strives to deliver the highest quality products. We use some of the industry's most advanced manufacturing processes and practice stringent quality control. However, pixel or sub pixel defects on the TFT Monitor panels used in flat panel monitors are sometimes unavoidable. No manufacturer can guarantee that all panels will be free from pixel defects, but Philips guarantees that any monitor with an unacceptable number of defects will be repaired or replaced under warranty. This notice explains the different types of pixel defects and defines acceptable defect levels for each type. In order to qualify for repair or replacement under warranty, the number of pixel defects on a TFT Monitor panel must exceed these acceptable levels. For example, no more than 0.0004% of the sub pixels on a monitor may be defective. Furthermore, Philips sets even higher quality standards for certain types or combinations of pixel defects that are more noticeable than others. This policy is valid worldwide.



Pixels and Sub pixels

A pixel, or picture element, is composed of three sub pixels in the primary colors


of red, green and blue. Many pixels together form an image. When all sub pixels of a pixel are lit, the three colored sub pixels together appear as a single white pixel. When all are dark, the three colored sub pixels together appear as a single black pixel. Other combinations of lit and dark sub pixels appear as single pixels of other colors.

Types of Pixel Defects

Pixel and sub pixel defects appear on the screen in different ways. There are two categories of pixel defects and several types of sub pixel defects within each category.

Bright Dot Defects

Bright dot defects appear as pixels or sub pixels that are always lit or 'on'. That is, a bright dot is a sub-pixel that stands out on the screen when the monitor displays a dark pattern. There are the types of bright dot defects.



One lit red, green or blue sub pixel.



Two adjacent lit sub pixels:

- Red + Blue = Purple
- Red + Green = Yellow
- Green + Blue = Cyan (Light Blue)

6. Customer care and warranty




Three adjacent lit sub pixels (one white pixel).



A red or blue bright dot must be more than 50 percent brighter than neighboring dots while a green bright dot is 30 percent brighter than neighboring dots.


Black Dot Defects

Black dot defects appear as pixels or sub pixels that are always dark or 'off'. That is, a dark dot is a sub-pixel that stands out on the screen when the monitor displays a light pattern. These are the types of black dot defects.



Proximity of Pixel Defects

Because pixel and sub pixels defects of the same type that are near to one another may be more noticeable, Philips also specifies tolerances for the proximity of pixel defects.



Pixel Defect Tolerances

In order to qualify for repair or replacement due to pixel defects during the warranty period, a TFT Monitor panel in a Philips flat panel monitor must have pixel or sub pixel defects exceeding the tolerances listed in the following tables.

6. Customer care and warranty

BRIGHT DOT DEFECTS	ACCEPTABLE LEVEL
1 lit subpixel	3
2 adjacent lit subpixels	1
3 adjacent lit subpixels (one white pixel)	0
Distance between two bright dot defects*	>15mm
Total bright dot defects of all types	3
BLACK DOT DEFECTS	ACCEPTABLE LEVEL
1 dark subpixel	5 or fewer
2 adjacent dark subpixels	2 or fewer
3 adjacent dark subpixels	0
Distance between two black dot defects*	>15mm
Total black dot defects of all types	5 or fewer
TOTAL DOT DEFECTS	ACCEPTABLE LEVEL

■ Note

1. 1 or 2 adjacent sub pixel defects = 1 dot defect

Total bright or black dot defects of all types

- 2. This monitor is ISO9241-307 compliant.(ISO9241-307: Ergonomic requirement, analysis and compliance test methods for electronic visual displays)
- 3. ISO9241-307 is the successor of formerly known ISO13406 standard, which is withdrawn by the International Organisation for Standardisation (ISO) per: 2008-11-13.

5 or fewer

6.2 Customer Care & Warranty

For warranty coverage information and additional support requirements valid for your region, please visit www.philips.com/support website for details or contact your local Philips Customer Care Center.

For extended warranty, if you would like to extend your general warranty period, an Out of Warranty service package is offered via our Certified Service Center.

If you wish to make use of this service, please be sure to purchase the service within 30 calendar days of your original purchase date. During the extended warranty period, the service includes pickup, repair and return service, however the user will be responsible for all costs accrued

If the Certified Service Partner cannot perform the required repairs under the offered extended warranty package, we will find alternative solutions for you, if possible, up to the extended warranty period you have purchased.

Please contact our Philips Customer Service Representative or local contact center (by Consumer care number) for more details.

Philips Customer Care Center number listed below.

•	Local Standard Warranty Period	ı	Extended Warranty Period	•	Total Warranty Period
•	Depend on different Regions	•	+ 1 Year	•	Local Standard warranty period +1
		•	+ 2 Years	•	Local Standard warranty period +2
		•	+ 3 Years	•	Local Standard warranty period +3

^{**}Proof of original purchase and extended warranty purchase required.



Please refer to important information manual for regional service hotline, which is available on the Philips website support page.

Troubleshooting & FAQs

7.1 Troubleshooting

This page deals with problems that can be corrected by a user. If the problem still persists after you have tried these solutions, contact Philips customer service representative.

1 Common Problems

No Picture (Power LED not lit)

- Make sure the power cord is plugged into the power outlet and into the back of the monitor.
- First, ensure that the power button on the front of the monitor is in the OFF position, then press it to the ON position.

No Picture (Power LED is White)

- Make sure the computer is turned on.
- Make sure the signal cable is properly connected to your computer.
- Make sure the monitor cable has no bent pins on the connect side. If yes, repair or replace the cable.
- The Energy Saving feature may be activated

Screen says



 Make sure the monitor cable is properly connected to your computer. (Also refer to the Quick Start Guide).

- Check to see if the monitor cable has bent pins.
- Make sure the computer is turned on

AUTO button doesn't function

 The auto function is applicable only in VGA-Analog mode. If the result is not satisfactory, you can do manual adjustments via the OSD menu.



The Auto Function is not applicable in DVI-Digital mode as it is not necessary.

Visible signs of smoke or sparks

- Do not perform any troubleshooting steps
- Disconnect the monitor from mains power source immediately for safety
- Contact with Philips customer service representative immediately.

2 Imaging Problems

Image is not centered

- Adjust the image position using the "Auto" function in OSD Main Controls
- Adjust the image position using the Phase/Clock of Setup in OSD Main Controls. It is valid only in VGA mode

Image vibrates on the screen

 Check that the signal cable is properly securely connected to the graphics board or PC.

Vertical flicker appears



- Adjust the image using the "Auto" function in OSD Main Controls.
- Eliminate the vertical bars using the Phase/Clock of Setup in OSD

7. Troubleshooting & FAOs

Main Controls. It is valid only in VGA mode.

Horizontal flicker appears



- Adjust the image using the "Auto" function in OSD Main Controls.
- Eliminate the vertical bars using the Phase/Clock of Setup in OSD Main Controls. It is valid only in VGA mode.

Image appears blurred, indistinct or too dark

 Adjust the contrast and brightness on On-Screen Display.

An "after-image", "burn-in" or "ghost image" remains after the power has been turned off.

- Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or "ghost imaging", on your screen. "Burn-in", "after-imaging", or "ghost imaging" is a well-known phenomenon in LCD panel technology. In most cases, the "burned in" or "after-imaging" or "ghost imaging" will disappear gradually over a period of time after the power has been switched off.
- Always activate a moving screen saver program when you leave your monitor unattended.
- Always activate a periodic screen refresh application if your LCD monitor will display unchanging static content.
- Severe" burn-in" or "after-image" or "ghost image" symptoms will not disappear and cannot be repaired. The damage mentioned above is not covered under your warranty.

Image appears distorted. Text is fuzzy or blurred.

 Set the PC's display resolution to the same mode as monitor's recommended screen native resolution.

Green, red, blue, dark, and white dots appears on the screen

 The remaining dots are normal characteristic of the liquid crystal used in today's technology, Please refer the pixel policy for more detail.

The "power on" light is too strong and is disturbing

 You can adjust "power on" light using the power LED Setup in OSD main Controls.

For further assistance, refer to the Consumer Information Centers list and contact Philips customer service representative.

7.2 General FAOs

Q1: When I install my monitor what should I do if the screen shows 'Cannot display this video mode'?

Ans.: Recommended resolution for this monitor: 1920 x 1080 @ 60 Hz.

- Unplug all cables, then connect your PC to the monitor that you used previously.
- In the Windows Start Menu, select Settings/Control Panel. In the Control Panel Window, select the Display icon. Inside the Display Control Panel, select the 'Settings' tab. Under the setting tab, in box labelled 'desktop area', move the sidebar to 1920 x 1080 pixels.
- Open 'Advanced Properties' and set the Refresh Rate to 60 Hz, then click OK.

7. Troubleshooting & FAO:

- Restart your computer and repeat step 2 and 3 to verify that your PC is set at 1920 x 1080 @ 60 Hz.
- Shut down your computer, disconnect your old monitor and reconnect your Philips LCD monitor.
- Turn on your monitor and then turn on your PC.

Q2: What is the recommended refresh rate for LCD monitor?

Ans.: Recommended refresh rate in LCD monitors is 60 Hz, In case of any disturbance on screen, you can set it up to 75 Hz to see if that removes the disturbance.

Q3: What are the .inf and .icm files on the CD-ROM? How do I install the drivers (.inf and .icm)?

Ans.: These are the driver files for your monitor. Follow the instructions in your user manual to install the drivers. Your computer may ask you for monitor drivers (.inf and .icm files) or a driver disk when you first install your monitor. Follow the instructions to insert the (companion CD-ROM) included in this package. Monitor drivers (.inf and .icm files) will be installed automatically.

Q4: How do I adjust the resolution?

Ans.: Your video card/graphic driver and monitor together determine the available resolutions. You can select the desired resolution under Windows® Control Panel with the "Display properties".

Q5: What if I get lost when I am making monitor adjustments via OSD?

Ans.: Simply press the OK button, then select 'Reset' to recall all of the original factory settings.

Q6: Is the LCD screen resistant to

scratches?

Ans.:In general it is recommended that the panel surface is not subjected to excessive shocks and is protected from sharp or blunt objects. When handling the monitor, make sure that there is no pressure or force applied to the panel surface side. This may affect your warranty conditions.

Q7: How should I clean the LCD surface?

Ans.: For normal cleaning, use a clean, soft cloth. For extensive cleaning, please use isopropyl alcohol. Do not use other solvents such as ethyl alcohol, ethanol, acetone, hexane, etc.

Q8: Can I change the color setting of my monitor?

Ans.: Yes, you can change your color setting through OSD control as the following procedures,

- Press "OK" to show the OSD (On Screen Display) menu
- Press "Down Arrow" to select the option "Color" then press "OK" to enter color setting, there are three settings as below.
 - Color Temperature; The two settings are 6500K and 9300K. With settings in the 6500K range the panel appears "warm, with a red-white color tone", while a 9300K temperature yields "cool, bluewhite toning".
 - sRGB; this is a standard setting for ensuring correct exchange of colors between different device (e.g. digital cameras, monitors, printers, scanners, etc)
 - User Define; the user can choose his/her preference color setting by adjusting red, green blue color.



A measurement of the color of light radiated by an object while it is being heated. This measurement is expressed in terms of absolute scale, (degrees Kelvin). Lower Kevin temperatures such as 2004K are red; higher temperatures such as 9300K are blue. Neutral temperature is white, at 6504K.

Q9: Can I connect my LCD monitor to any PC, workstation or Mac?

Ans.: Yes. All Philips LCD monitors are fully compatible with standard PCs, Macs and workstations. You may need a cable adapter to connect the monitor to your Mac system. Please contact your Philips sales representative for more information.

Q10: Are Philips LCD monitors Plugand- Play?

Ans.: Yes, the monitors are Plug-and-Play compatible with Windows 7/ Windows 8/Windows 8.1/Windows 10, Mac OSX

Q11: What is Image Sticking, or Image Burn-in, or After Image, or Ghost Image in LCD panels?

Ans.: Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or "ghost imaging", on your screen. "Burn-in", "after-imaging", or "ghost imaging" is a well-known phenomenon in LCD panel technology. In most cases, the "burned in" or "atter-imaging" or "ghost imaging" will disappear gradually over a period of time after the power has been switched off.

Always activate a moving screen saver program when you leave your monitor unattended.

Always activate a periodic screen refresh application if your LCD monitor will display unchanging static content.

Warning


Failure to activate a screen saver, or a periodic screen refresh application may result in severe "burn-in" or "afterimage" or "ghost image" symptoms that will not disappear and cannot be repaired. The damage mentioned above is not covered under your warranty.

Q12: Why is my Display not showing sharp text, and is displaying jagged characters?

Ans.: Your LCD monitor works best at its native resolution of 1920 x 1080 @ 60 Hz. For best display, please use this resolution

Q13: How to unlock/lock my hot key?

Ans.: Please press @/OK for 10 seconds to unlock/lock the hot key, by doing so, your monitor pops out "Attention" to show the unlock/lock status as shown below illustrators.





© 2017 Koninklijke Philips N.V. All rights reserved.

Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V. and are used under license from Koninklijke Philips N.V.

Specifications are subject to change without notice.

Version: M72X3V1L