



www.philips.com/welcome

ΕN	User manual	1
	Customer care and warranty	18
	Troubleshooting & FAQs	2

Table of Contents

1.	Important
2.	Setting up the monitor
3.	Image Optimization103.1 SmartImage103.2 SmartContrast11
4.	FreeSync12
5.	Technical Specifications
6.	Power Management17
7.	Customer care and warranty18 7.1 Philips' Flat Panel Monitors Pixel Defect Policy18 7.2 Customer Care & Warranty21
8.	Troubleshooting & FAQs

1. Important

This electronic user's guide is intended for anyone who uses the Philips monitor. Take time to read this user's manual before you use your monitor. It contains important information and notes regarding the operation of your monitor.

The Philips guarantee applies provided the product is handled properly for its intended use, in accordance with its operating instructions and upon presentation of the original invoice or cash receipt, indicating the date of purchase, dealer's name and model and production number of the product.

1.1 Safety precautions and maintenance

Warnings

Use of controls, adjustments or procedures other than those specified in this documentation may result in exposure to shock, electrical hazards and/or mechanical hazards.

Read and follow these instructions when connecting and using your computer monitor.

Operation

- Please Keep the monitor out of direct sunlight, very strong bright lights and away from any other heat source. Lengthy exposure to this type of environment may result in discoloration and damage to the monitor.
- Remove any object that could fall into ventilation holes or prevent proper cooling of the monitor's electronics.
- Do not block the ventilation holes on the cabinet.

- When positioning the monitor, make sure the power plug and outlet are easily accessible.
- If turning off the monitor by detaching the power cable or DC power cord, wait for 6 seconds before attaching the power cable or DC power cord for normal operation.
- Please use approved power cord provided by Philips at all times. If your power cord is missing, please contact your local service center. (Please refer to Customer Care Consumer Information Center)
- Do not subject the monitor to severe vibration or high impact conditions during operation.
- Do not knock or drop the monitor during operation or transportation.

Maintenance

- To protect your monitor from possible damage, do not put excessive pressure on the LCD panel. When moving your monitor, grasp the frame to lift; do not lift the monitor by placing your hand or fingers on the LCD panel.
- Unplug the monitor if you are not going to use it for an extensive period of time.
- Unplug the monitor if you need to clean it with a slightly damp cloth.
 The screen may be wiped with a dry cloth when the power is off.
 However, never use organic solvent, such as, alcohol, or ammonia-based liquids to clean your monitor.
- To avoid the risk of shock or permanent damage to the set, do not expose the monitor to dust, rain, water, or excessive moisture environment.
- If your monitor gets wet, wipe it with dry cloth as soon as possible.
- If foreign substance or water gets in your monitor, please turn the power

Important

off immediately and disconnect the power cord. Then, remove the foreign substance or water, and send it to the maintenance center.

- Do not store or use the monitor in locations exposed to heat, direct sunlight or extreme cold.
- In order to maintain the best performance of your monitor and use it for a longer lifetime, please use the monitor in a location that falls within the following temperature and humidity ranges.
 - Temperature: 0-40°C 32-104°F
 - Humidity: 20-80% RH
- IMPORTANT: Always activate a moving screen saver program when you leave your monitor unattended.
 Always activate a periodic screen refresh application if your monitor will display unchanging static content. Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or "ghost imaging", on your screen.
- "Burn-in", "after-imaging", or "ghost imaging" is a well-known phenomenon in LCD panel technology.
 In most cases, the "burned in" or "after-imaging" or "ghost imaging" will disappear gradually over a period of time after the power has been switched off

Warning

Failure to activate a screen saver, or a periodic screen refresh application may result in severe "burn-in" or "afterimage" or "ghost image" symptoms that will not disappear and cannot be repaired. The damage mentioned above is not covered under your warranty.

Service

- The casing cover should be opened only by qualified service personnel.
- If there is any need for any document for repair or integration,
 please contact with your local
 service center. (please refer to the
 chapter of "Consumer Information
 Center")
- For transportation information, please refer to "Technical Specifications".
- Do not leave your monitor in a car/ trunk under direct sun light.

Note

Consult a service technician if the monitor does not operate normally, or you are not sure what procedure to take when the operating instructions given in this manual have been followed.

1.2 Notational Descriptions

The following subsections describe notational conventions used in this document.

Notes, Cautions and Warnings

Throughout this guide, blocks of text may be accompanied by an icon and printed in bold or italic type. These blocks contain notes, cautions or warnings. They are used as follows:

■ Note

This icon indicates important information and tips that help you make better use of your computer system.

Caution

This icon indicates information that tells you how to avoid either potential damage to hardware or loss of data.

Warning

This icon indicates the potential for bodily harm and tells you how to avoid the problem.

Some warnings may appear in alternate formats and may not be accompanied by an icon. In such cases, the specific presentation of the warning is mandated by the relevant regulatory authority.

1.3 Disposal of product and packing material

Waste Electrical and Electronic Equipment-WEEE



This marking on the product or on its packaging illustrates that, under European Directive 2012/19/EU governing used electrical and electronic appliances, this product may not be disposed of with normal household waste. You are responsible for disposal of this equipment through a designated waste electrical and electronic equipment collection. To determine the locations for dropping off such waste electrical and electronic, contact your local government office, the waste disposal organization that serves your household or the store at which you purchased the product.

Your new monitor contains materials that can be recycled and reused. Specialized companies can recycle your product to increase the amount of reusable materials and to minimize the amount to be disposed of.

All redundant packing material has been omitted. We have done our utmost to make the packaging easily separable into mono materials.

Please find out about the local regulations on how to dispose of your old monitor and packing from your sales representative.

. Important

Taking back/Recycling Information for Customers

Philips establishes technically and economically viable objectives to optimize the environmental performance of the organization's product, service and activities.

From the planning, design and production stages, Philips emphasizes the important of making products that can easily be recycled. At Philips, end-of-life management primarily entails participation in national takeback initiatives and recycling programs whenever possible, preferably in cooperation with competitors, which recycle all materials (products and related packaging material) in accordance with all Environmental Laws and taking back program with the contractor company.

Your display is manufactured with high quality materials and components which can be recycled and reused.


To learn more about our recycling program please visit

http://www.philips.com/a-w/about/ sustainability.html

2. Setting up the monitor

2.1 Installation

Package contents





* Different according to region.




Use only the AC/DC adapter model: Philips ADPC1936, STK025-19131T

Install base stand


 Place the monitor face down on soft and smooth surface taking care to avoid scratching or damaging the screen.



- 2. Hold the base stand with both hands and firmly insert the base stand into the base column.
 - (1) Gently attach the base to the base column until the latch locks the base.
 - (2) Use your fingers to tighten the screw located at the bottom of the base, and secure the base to the column tightly.



Connecting to your PC




- AC/DC power input
- 2 HDMI Audio out
- **3** VGA input
- 4 HDMI input
- **5** HDMI input
- 6 Kensington anti-theft lock

Connect to PC

- 1. Connect the power cord to the back of the monitor firmly.
- 2. Turn off your computer and unplug its power cable.
- 3. Connect the monitor signal cable to the video connector on the back of your computer.
- 4. Plug the power cord of your computer and your monitor into a nearby outlet.
- 5. Turn on your computer and monitor. If the monitor displays an image, installation is complete.

2.2 Operating the monitor

1 Front view product description



0	Press to switch power on. Press more than 3 seconds to switch power off.
2 -	Access the OSD menu. Confirm the OSD adjustment.
	Adjust the brightness level.
8	Adjust the OSD menu.
0 1	Change the signal input source.
	Adjust the OSD menu.
6 ←	SmartImage. There are multiple selections : FPS, Racing, RTS, Gamer 1, Gamer 2, LowBlue Mode and Off.
	Return to previous OSD level.

Description of the On Screen Display

What is On-Screen Display (OSD)?

On-Screen Display (OSD) is a feature in all Philips LCD monitors. It allows an end user to adjust screen performance or select functions of the monitors directly through an on-screen instruction window. A user friendly on screen display interface is shown as below:




Basic and simple instruction on the control keys

To access the OSD menu on this Philips Display simply use the single toggle button on the backside of the Display bezel. The single button operates like a joystick. To move the cursor, simply toggle the button in four directions. Press the button to select desired option.

The OSD Menu

Below is an overall view of the structure of the On-Screen Display. You can use this as a reference when you want to work your way around the different adjustments later on.



2. Setting up the monito


Resolution notification

This monitor is designed for optimal performance at its native resolution, 1920×1080@60Hz. When the monitor is powered on at a different resolution, an alert is displayed on screen: Use 1920×1080@60Hz for best results.

Display of the native resolution alert can be switched off from Setup in the OSD (On Screen Display) menu.

4 Physical Function

Tilt




2.3 Remove the Base Assembly for VESA Mounting


1 Remove the Base Stand

Before you start disassembling the monitor base, please follow the instructions below to avoid any possible damage or injury.

 Place the monitor face down on a smooth surface, taking care to avoid scratching or damaging the screen.



Use your fingers to loosen the screw located at the bottom of the base, and remove the base from the stand



3. Remove the hinge cover from monitor body by using your fingers.



2. Setting up the monito

4. Use a screwdriver to remove the screws on the arm, and then detach the arm/stand from the monitor.




5. Put the hinge cover back to the original position and fasten to the slots until hearing the click sound.



Note

This monitor accepts a 75mm x 75mm VESA-Compliant mounting interface. VESA Mounting Screw M4. Always contact manufacturer for wall-mount installation.



3. Image Optimization

3.1 SmartImage

1 What is it?

SmartImage provides presets that optimize display for different types of content, dynamically adjusting brightness, contrast, color and sharpness in real time. Whether you're working with text applications, displaying images or watching a video, Philips SmartImage delivers great optimized monitor performance.


2 Why do I need it?

You want a monitor that delivers optimized display all your favorite types of content, SmartImage software dynamically adjust brightness, contrast, color and sharpness in real time to enhance your monitor viewing experience.

3 How does it work?


SmartImage is an exclusive, leading edge Philips technology that analyzes the content displayed on your screen. Based on a scenario you select, SmartImage dynamically enhances the contrast, color saturation and sharpness of images to enhance the contents being displayed - all in real time with the press of a single button.

4 How to enable SmartImage?



- Toggle to the left to launch the SmartImage on screen display.
- 2. Toggle to the up or down to select between FPS, Racing, RTS, Gamer 1, Gamer 2, LowBlue Mode and Off.
- The SmartImage on screen display will remain on screen for 5 seconds or you can also toggle to the left to make confirmation.

There are multiple selections: FPS, Racing, RTS, Gamer 1, Gamer 2, LowBlue Mode and Off.



3 Image Optimization

- FPS: For playing FPS (First Person Shooters) games. Improves dark theme black level details.
- Racing: For playing Racing games.
 Provides fastest response time and high color saturation.
- RTS: For playing RTS (Real Time Strategy) games, a user-selected portion can be highlighted for RTS games (through SmartFrame). The picture quality can be adjusted for the highlighted portion.
- Gamer 1: User's preference settings saved as Gamer 1.
- Gamer 2: User's preference settings saved as Gamer 2.
- LowBlue Mode: LowBlue Mode
 for easy on-the-eyes productivity
 Studies have shown that just as
 ultra-violet rays can cause eye
 damage, shortwave length blue light
 rays from LED displays can cause
 eye damage and affect vision over
 time. Developed for wellbeing,
 Philips LowBlue Mode setting uses a
 smart software technology to reduce
 harmful shortwave blue light.
- · Off: No optimization by SmartImage.

3.2 SmartContrast

1 What is it?

Unique technology that dynamically analyzes displayed content and automatically optimizes a LCD monitor's contrast ratio for maximum visual clarity and viewing enjoyment, stepping up backlighting for clearer, crisper and brighter images or dimming backlighting for clear display of images on dark backgrounds.

2 Why do I need it?

You want the very best visual clarity and viewing comfort for every type of content. SmartContrast dynamically controls contrast and adjusts backlighting for clear, crisp, bright gaming and video images or displays clear, readable text for office work. By reducing your monitor's power consumption, you save on energy costs and extend the lifetime of your monitor.

3 How does it work?

When you activate SmartContrast, it will analyse the content you are displaying in real time to adjust colors and control backlight intensity. This function will dynamically enhance contrast for a great entertainment experience when viewing videos or playing games.

4. FreeSync



PC gaming has long been an imperfect experience because GPUs and monitors update at different rates. Sometimes a GPU can render many new pictures during a single update of the monitor, and the monitor will show pieces of each picture as a single image. This is called "tearing." Gamers can fix tearing with a feature called "v-sync," but the image can become jerky as the GPU waits on the monitor to call for an update before delivering new pictures.

The responsiveness of mouse input and overall frames per second are reduced with v-sync, too. AMD FreeSync™ technology eliminates all of these problems by letting the GPU update the monitor the moment a new picture is ready, leaving gamers with unbelievably smooth, responsive, tearing-free games.

Followed by the graphic card that are compatible.

- Operating system
 - Windows 10/8.1/8/7
- Graphic Card: R9 290/300 Series & R7 260 Series
 - AMD Radeon R9 300 Series
 - AMD Radeon R9 Fury X
 - AMD Radeon R9 360
 - AMD Radeon R7 360
 - AMD Radeon R9 295X2
 - AMD Radeon R9 290X

- AMD Radeon R9 290
- AMD Radeon R9 285
- AMD Radeon R7 260X
- AMD Radeon R7 260
- Processor A-Series Desktop and Mobility APUs
 - AMD A10-7890K
 - AMD A10-7870K
 - AMD A10-7850K
 - AMD A10-7800
 - AMD A10-7700K
 - AMD A8-7670K
 - AMD A8-7650K
 - AMD A8-7600
 - AMD A6-7400K

5. Technical Specifications

Monitor panel type Backlight W-LED system Panel size 21.5" W (54.6cm) Aspect ratio Optimum resolution Response time (typical) SmartResponse time SmartContrast Pixel pitch Viewing angle Picture enhancement Display colors Vertical refresh rate Horizontal frequency sRGB LowBlue Mode Free sync SrGB LowBlue Mode Free sync OSD Languages OSD Languages Other convenience Plug & Play compatibility Stand Tilt Vetconverticatio 16:9 W-5." W (54.6cm) W-64.6cm) W-64.6	Picture/Display	
Panel size 21.5" W (54.6cm) Aspect ratio 16:9 Optimum resolution 1920 x 1080 @ 60Hz Response time (typical) SmartResponse time (typical) SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178" (H) / 178" (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency sRGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output HDMI audio out Convenience OSD Languages Other convenience Plug & Play compatibility Stand	Monitor panel type	IPS technology
Aspect ratio 16:9 Optimum resolution 1920 x 1080 @ 60Hz Response time (typical) 14ms (GtG) SmartResponse time (typical) 5ms (GtG) SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178" (H) / 178" (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement 5martImage Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency 30KHz-85KHz \$RGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility Stand	Backlight	W-LED system
Optimum resolution 1920 x 1080 @ 60Hz Response time (typical) 14ms (GtG) SmartResponse time 5ms (GtG) SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement 5martImage Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency 30KHz-85KHz \$RGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility Stand	Panel size	21.5" W (54.6cm)
resolution Response time (typical) SmartResponse time SmartContrast Pixel pitch Vewing angle Flicker free Picture enhancement Display colors Horizontal frequency SRGB LowBlue Mode Free sync Free sync Ves Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience Other convenience Pixel pitch Display colors 16.7M Vertical refresh rate ABHZ-75Hz (Analog) 48Hz-75Hz (HDMI) ABHZ-75Hz (HDMI)	Aspect ratio	16:9
Response time (typical) SmartResponse time 5ms (GtG) SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Picture enhancement Display colors Vertical refresh rate Horizontal frequency SRGB Yes Fire sync Connectivity Signal input/output Input Signal Audio In/Out Convenience OSD Languages Pisms (MGG) SmartImage SmartImage Audio In/Out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility Stand	· ·	1920 x 1080 @ 60Hz
(typical) SmartResponse time SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle Flicker free Yes Picture enhancement Display colors Vertical refresh rate Horizontal frequency sRGB LowBlue Mode Yes Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience OSD Languages Other convenience Plug & Play compatibility Stand		
SmartResponse time SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Picture enhancement Display colors Vertical refresh rate Horizontal frequency sRGB Yes LowBlue Mode Yes Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience OSD Languages Other convenience Plug & Play compatibility Stand	the state of the s	14ms (GtG)
SmartContrast 20,000,000:1 Pixel pitch 0.248 x 0.248 mm Viewing angle 178° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency 30KHz-85KHz SRGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Kensington Lock, VESA mount (75 x 75mm) DDC/CI, Mac OSX, SRGB, Windows 10/8.1/8/7 Stand		5ms (GtG)
Pixel pitch Viewing angle I78° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement Display colors Vertical refresh rate Horizontal frequency sRGB LowBlue Mode Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience OSD Languages Other convenience Plug & Play compatibility Picture Yes Yes SmartImage SmartImage SmartImage SmartImage Allo (Typ.) SmartImage SmartImage SmartImage SmartImage SmartImage SmartImage Allo (Typ.) SmartImage SmartImage SmartImage SmartImage Allo (Analog) Allo (Analog) Allo (Analog) Allo (Digital) Separate Sync, Sync on Green Audio In/Out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, SRGB, Windows 10/8.1/8/7 Stand		
Viewing angle 178° (H) / 178° (V) @ C/R > 10 (typ.) Flicker free Yes Picture enhancement		
Flicker free Yes Picture enhancement Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency 30KHz-85KHz sRGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	-	
Picture enhancement Display colors 16.7M Vertical refresh rate Horizontal frequency sRGB LowBlue Mode Free sync Connectivity Signal input/output Input Signal Audio In/Out HDMI audio out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility SmartImage 16.7M 48Hz-75Hz (Analog) 48Hz-75Hz (HDMI) 30KHz-85KHz 50KHz 48Hz-75Hz (Analog) 48Hz-75Hz (HDMI) 10 JOHNII 10 JOHNII 10 JOHNII 10 JOHNII 11 JOHNII 12 JOHNII 13 JOHNII 14 JOHNII 16 JOHNII 16 JOHNII 16 JOHNII 17 JOHNII 18 JOHNII 20 J		178° (H) / 178° (V) @ C/R > 10 (typ.)
enhancement Display colors 16.7M Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency \$RGB Yes LowBlue Mode Yes Free sync Connectivity Signal input/output Input Signal Audio In/Out HDMI audio out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility Stand		Yes
Vertical refresh rate 48Hz-76Hz (Analog) 48Hz-75Hz (HDMI) Horizontal frequency 30KHz-85KHz sRGB Yes LowBlue Mode Yes Free sync Connectivity Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand		SmartImage
Vertical refresh rate Horizontal frequency \$RGB Yes LowBlue Mode Yes Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility Stand	Display colors	16.7M
frequency SRGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7	Vertical refresh rate	9.
SRGB Yes LowBlue Mode Yes Free sync Yes Connectivity Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand		30KHz-85KHz
Free sync Connectivity Signal input/output Input Signal Audio In/Out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand		Yes
Connectivity Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	LowBlue Mode	Yes
Signal input/output VGA (Analog), HDMI (Digital)x2 Input Signal Separate Sync, Sync on Green Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Kensington Lock, VESA mount (75 x 75mm) Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7	Free sync	Yes
Input Signal Audio In/Out HDMI audio out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	Connectivity	
Audio In/Out Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	Signal input/output	VGA (Analog), HDMI (Digital)x2
Convenience English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	Input Signal	Separate Sync, Sync on Green
OSD Languages English, German, Spanish, Greek, French, Italian, Hungarian, Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	Audio In/Out	HDMI audio out
OSD Languages Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified Chinese, Traditional Chinese, Japanese, Korean Other convenience Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	Convenience	
Plug & Play compatibility DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7 Stand	OSD Languages	Dutch, Portuguese, Brazil Portuguese, Polish, Russian, Swedish, Finnish, Turkish, Czech, Ukranian, Simplified
compatibility Stand	Other convenience	Kensington Lock, VESA mount (75 x 75mm)
Stand		DDC/CI, Mac OSX, sRGB, Windows 10/8.1/8/7
		-5° / +20°

(Non-operation)

Power			
	AC Input	AC Input	AC Input
Consumption	Voltage at	Voltage at	Voltage at
·	100VAC , 50Hz	115VAC , 60Hz	230VAC , 50Hz
Normal operation	20.59 W (typ.)	20.31 W (typ.)	20.23 W (typ.)
Sleep (Standby)	<0.5 W (typ.)	<0.5 W (typ.)	<0.5 W (typ.)
Off	<0.3 W (typ.)	<0.3 W (typ.)	<0.3 W (typ.)
	AC Input	AC Input	AC Input
Heat dissipation	Voltage at	Voltage at	Voltage at
	100VAC , 50Hz	115VAC , 60Hz	230VAC , 50Hz
Normal operation	70.28 BTU/hr	69.33 BTU/hr	69.06 BTU/hr
	(typ.)	(typ.)	(typ.)
Sleep (standby)	<1.71 BTU/hr	<1.71 BTU/hr	<1.71 BTU/hr
	(typ.)	(typ.)	(typ.)
Off	<1.02 BTU/hr	<1.02 BTU/hr	<1.02 BTU/hr
	(typ.)	(typ.)	(typ.)
Power LED indicator		Standby/Sleep mo	ode: white
Power supply	(blinking) External, 100-240VAC, 50-60Hz		
	Externat, 100 240	7VAC, 30 00112	
Dimensions			
Product without stand	487 x 293 x 36 mm		
(WxHxD)			
Product with stand (WxHxD)	487 x 385 x 176 mm		
Packaging in mm (WxHxD)	565 x 444 x 131 mm	<u> </u>	
Weight	303 X 444 X 131 11111	1	
Product without stand	2.05 kg		
Product with stand	2.52 kg		
Product with packaging	3.99 kg		
Operating conditions			
Temperature range			
(operation)	0°C to 40 °C		
Relative humidity	200/ 1 622/		
(operation)	20% to 80%		
Atmospheric pressure	700 to 1000hDa		
(operation)	700 to 1060hPa		
Temperature range	-20°C to 60°C		
(Non-operation)	-20 C 10 60 C		
Relative humidity	10% to 90%		
(Non-operation)	10 /0 (0 30 /0		
Atmospheric pressure	re 500 to 1060hPa		
(Non-operation)	JOO LO TOUOTIPA		

5. Technical Specifications

Environmental and energy				
ROHS	YES			
Packaging	100% recyclable			
Specific substances	100% PVC BFR free housing			
Energy star	YES			
Compliance and standards				
Regulatory approvals	MEPS, FCC, RCM, BSMI, PC Re-cycle, E-standby, KCC, J-MOSS, VCCI, CE			
Cabinet				
Color	Black			
Finish	Glossy			



- 1. This data is subject to change without notice. Go to www.philips.com/support to download the latest version of leaflet.
- 2. Smart response time is the optimum value from either GtG or GtG (BW) tests.

5.1 Resolution & Preset Modes

- Maximum Resolution
 1920x1080@60Hz (analog input)
 1920x1080@60Hz (digital input)
- 2 Recommended Resolution 1920x1080@60Hz (digital input)

H. freq (kHz)	Resolution	V. freq (Hz)
31.47	720x400	70.09
31.47	640x480	59.94
35.00	640x480	66.67
37.86	640x480	72.81
37.50	640x480	75.00
35.16	800x600	56.25
37.88	800x600	60.32
48.08	800x600	72.19
46.88	800x600	75.00
47.73	832x624	74.55
48.36	1024x768	60.00
56.48	1024x768	70.07
60.02	1024x768	75.03
44.77	1280x720	59.86
60.00	1280x960	60.00
63.89	1280x1024	60.02
79.98	1280x1024	75.03
55.94	1440x900	59.89
65.29	1680x1050	59.95
67.50	1920x1080	60.00

Note

Please notice that your display works best at native resolution of 1920x1080@60Hz. For best display quality, please follow this resolution recommendation.

6. Power Management

If you have VESA DPM compliance display card or software installed in your PC, the monitor can automatically reduce its power consumption when not in use. If an input from a keyboard, mouse or other input device is detected, the monitor will 'wake up' automatically. The following table shows the power consumption and signaling of this automatic power saving feature:

P	Power Management Definition				
VESA Mode	Video	H-sync	V-sync	Power Used	LED Color
Active	ON	Yes	Yes	20.6 W (typ.) 20.9 W (Max.)	White
Sleep	OFF	No	No	0.5 W (typ.)	White (blink)
Switch Off	OFF	-	-	0.3 W (typ.)	OFF

The following setup is used to measure power consumption on this monitor.

Native resolution: 1920x1080

Contrast: 50%Brightness: 100%

Color temperature: 6500k with full

white pattern


Note

This data is subject to change without notice.

7. Customer care and warranty

7.1 Philips' Flat Panel Monitors Pixel Defect Policy

Philips strives to deliver the highest quality products. We use some of the industry's most advanced manufacturing processes and practice stringent quality control. However, pixel or sub pixel defects on the TFT Monitor panels used in flat panel monitors are sometimes unavoidable. No manufacturer can guarantee that all panels will be free from pixel defects, but Philips guarantees that any monitor with an unacceptable number of defects will be repaired or replaced under warranty. This notice explains the different types of pixel defects and defines acceptable defect levels for each type. In order to qualify for repair or replacement under warranty, the number of pixel defects on a TFT Monitor panel must exceed these acceptable levels. For example, no more than 0.0004% of the sub pixels on a monitor may be defective. Furthermore, Philips sets even higher quality standards for certain types or combinations of pixel defects that are more noticeable than others. This policy is valid worldwide.



Pixels and Sub pixels

A pixel, or picture element, is composed of three sub pixels in the primary colors of red, green and blue. Many pixels together form an image. When all sub pixels of a pixel are lit, the three colored sub pixels together appear as a single white pixel. When all are dark, the three colored sub pixels together appear as a single black pixel. Other combinations of lit and dark sub pixels appear as single pixels of other colors.

Types of Pixel Defects

Pixel and sub pixel defects appear on the screen in different ways. There are two categories of pixel defects and several types of sub pixel defects within each category.

Bright Dot Defects

Bright dot defects appear as pixels or sub pixels that are always lit or 'on'. That is, a bright dot is a sub-pixel that stands out on the screen when the monitor displays a dark pattern. There are the types of bright dot defects.



One lit red, green or blue sub pixel.




Two adjacent lit sub pixels:

- Red + Blue = Purple
- Red + Green = Yellow
- Green + Blue = Cyan (Light Blue)

7. Customer care and warrant






Three adjacent lit sub pixels (one white pixel).



A red or blue bright dot must be more than 50 percent brighter than neighboring dots while a green bright dot is 30 percent brighter than neighboring dots.

Black Dot Defects

Black dot defects appear as pixels or sub pixels that are always dark or 'off'. That is, a dark dot is a sub-pixel that stands out on the screen when the monitor displays a light pattern. These are the types of black dot defects.



Proximity of Pixel Defects

Because pixel and sub pixels defects of the same type that are near to one another may be more noticeable, Philips also specifies tolerances for the proximity of pixel defects.

7. Customer care and warranty

Pixel Defect Tolerances

In order to qualify for repair or replacement due to pixel defects during the warranty period, a TFT Monitor panel in a Philips flat panel monitor must have pixel or sub pixel defects exceeding the tolerances listed in the following tables.

BRIGHT DOT DEFECTS	ACCEPTABLE LEVEL
1 lit subpixel	2
2 adjacent lit subpixels	1
3 adjacent lit subpixels (one white pixel)	0
Distance between two bright dot defects*	>10mm
Total bright dot defects of all types	3
BLACK DOT DEFECTS	ACCEPTABLE LEVEL

BLACK DOT DEFECTS	ACCEPTABLE LEVEL
1 dark subpixel	5 or fewer
2 adjacent dark subpixels	2 or fewer
3 adjacent dark subpixels	0
Distance between two black dot defects*	>10mm
Total black dot defects of all types	5 or fewer
TOTAL DOT DEFECTS	ACCEPTABLE LEVEL

TOTAL DOT DEFECTS	ACCEPTABLE LEVEL
Total bright or black dot defects of all types	5 or fewer



1 or 2 adjacent sub pixel defects = 1 dot defect

7.2 Customer Care & Warranty

For warranty coverage information and additional support requirements valid for your region, please visit www.philips.com/support website for details or contact your local Philips Customer Care Center.

For extended warranty, if you would like to extend your general warranty period, an Out of Warranty service package is offered via our Certified Service Center.

If you wish to make use of this service, please be sure to purchase the service within 30 calendar days of your original purchase date. During the extended warranty period, the service includes pickup, repair and return service, however the user will be responsible for all costs accrued.

If the Certified Service Partner cannot perform the required repairs under the offered extended warranty package, we will find alternative solutions for you, if possible, up to the extended warranty period you have purchased.

Please contact our Philips Customer Service Representative or local contact center (by Consumer care number) for more details.

Philips Customer Care Center number listed below.

Local Standard Warranty Period	Extended Warranty Period	Total Warranty Period		
Depend on different Regions	+ 1 Year	Local Standard warranty period +1		
	+ 2 Years	Local Standard warranty period +2		
	+ 3 Years	Local Standard warranty period +3		

^{**}Proof of original purchase and extended warranty purchase required.



Please refer to important information manual for regional service hotline, which is available on the Philips website support page.

8. Troubleshooting & FAQs

8.1 Troubleshooting

This page deals with problems that can be corrected by a user. If the problem still persists after you have tried these solutions, contact Philips customer service representative.

1 Common Problems

No Picture (Power LED not lit)

- Make sure the power cord is plugged into the power outlet and into the back of the monitor.
- First, ensure that the power button on the front of the monitor is in the OFF position, then press it to the ON position.

No Picture (Power LED is White)

- Make sure the computer is turned on.
- Make sure the signal cable is properly connected to your computer.
- Make sure the monitor cable has no bent pins on the connect side. If yes, repair or replace the cable.
- The Energy Saving feature may be activated

Screen says

Check cable connection

 Make sure the monitor cable is properly connected to your computer. (Also refer to the Quick Start Guide).

- Check to see if the monitor cable has bent pins.
- Make sure the computer is turned on.

AUTO button doesn't function

 The auto function is applicable only in VGA-Analog mode. If the result is not satisfactory, you can do manual adjustments via the OSD menu.

Note

The Auto Function is not applicable in DVI-Digital mode as it is not necessary.

Visible signs of smoke or sparks

- Do not perform any troubleshooting steps
- Disconnect the monitor from mains power source immediately for safety
- Contact with Philips customer service representative immediately.

2 Imaging Problems

Image is not centered

- Adjust the image position using the "Auto" function in OSD Main Controls.
- Adjust the image position using the Phase/Clock of Setup in OSD Main Controls. It is valid only in VGA mode

Image vibrates on the screen

 Check that the signal cable is properly securely connected to the graphics board or PC.

Vertical flicker appears



- Adjust the image using the "Auto" function in OSD Main Controls.
- Eliminate the vertical bars using the Phase/Clock of Setup in OSD

B. Troubleshooting & FAOs

Main Controls. It is valid only in VGA mode.

Horizontal flicker appears



- Adjust the image using the "Auto" function in OSD Main Controls.
- Eliminate the vertical bars using the Phase/Clock of Setup in OSD Main Controls. It is valid only in VGA mode.

Image appears blurred, indistinct or too dark

 Adjust the contrast and brightness on On-Screen Display.

An "after-image", "burn-in" or "ghost image" remains after the power has been turned off.

- Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or "ghost imaging", on your screen. "Burn-in", "after-imaging", or "ghost imaging" is a well-known phenomenon in LCD panel technology. In most cases, the "burned in" or "after-imaging" or "ghost imaging" will disappear gradually over a period of time after the power has been switched off.
- Always activate a moving screen saver program when you leave your monitor unattended.
- Always activate a periodic screen refresh application if your LCD monitor will display unchanging static content.
- Failure to activate a screen saver, or a periodic screen refresh application may result in severe "burn-in" or "after-image" or "ghost image" symptoms that will not disappear

and cannot be repaired. The damage mentioned above is not covered under your warranty.

Image appears distorted. Text is fuzzy or blurred.

 Set the PC's display resolution to the same mode as monitor's recommended screen native resolution.

Green, red, blue, dark, and white dots appears on the screen

 The remaining dots are normal characteristic of the liquid crystal used in today's technology, Please refer the pixel policy for more detail.

8.2 General FAQs

Q1: When I install my monitor what should I do if the screen shows 'Cannot display this video mode'?

Ans.: Recommended resolution for this monitor: 1920x1080@60Hz.

- Unplug all cables, then connect your PC to the monitor that you used previously.
- In the Windows Start Menu, select Settings/Control Panel. In the Control Panel Window, select the Display icon. Inside the Display Control Panel, select the 'Settings' tab. Under the setting tab, in box labelled 'desktop area', move the sidebar to 1920x1080 pixels.
- Open 'Advanced Properties' and set the Refresh Rate to 60Hz, then click OK.
- Restart your computer and repeat step 2 and 3 to verify that your PC is set at 1920x1080@60Hz.
- Shut down your computer, disconnect your old monitor and reconnect your Philips LCD monitor.
- Turn on your monitor and then turn on your PC.

Q2: What is the recommended refresh rate for LCD monitor?

Ans.: Recommended refresh rate in LCD monitors is 60Hz, In case of any disturbance on screen, you can set it up to 75Hz to see if that removes the disturbance

Q3: What are the .inf and .icm files on the user manual? How do I install the drivers (.inf and .icm)?

Ans.: These are the driver files for your monitor. Follow the instructions in your user manual to install the drivers. Your computer may ask you for monitor drivers (.inf and .icm files) or a driver disk when you first install your monitor.

Q4: How do I adjust the resolution?

Ans.: Your video card/graphic driver and monitor together determine the available resolutions. You can select the desired resolution under Windows® Control Panel with the "Display properties".

Q5: What if I get lost when I am making monitor adjustments via OSD?

Ans.: Simply press the OK button, then select 'Reset' to recall all of the original factory settings.

Q6: Is the LCD screen resistant to scratches?

Ans.: In general it is recommended that the panel surface is not subjected to excessive shocks and is protected from sharp or blunt objects. When handling the monitor, make sure that there is no pressure or force applied to the panel surface side. This may affect your warranty conditions.

Q7: How should I clean the LCD surface?

Ans.: For normal cleaning, use a clean, soft cloth. For extensive cleaning, please use isopropyl alcohol. Do not use other solvents such as ethyl alcohol, ethanol, acetone, hexane, etc.

Q8: Can I change the color setting of my monitor?

Ans.: Yes, you can change your color setting through OSD control as the following procedures.

- Press "OK" to show the OSD (On Screen Display) menu
- Press "Down Arrow" to select the option "Color" then press "OK" to enter color setting, there are three settings as below.
 - 1. Color Temperature; With settings in the Native range the panel

. Troubleshooting & FAOs

appears "warm, with a redwhite color tone", while a 11500k temperature yields "cool, bluewhite toning".

- 2. sRGB; this is a standard setting for ensuring correct exchange of colors between different device (e.g. digital cameras, monitors, printers, scanners, etc)
- User Define; the user can choose his/her preference color setting by adjusting red, green blue color.

Note

A measurement of the color of light radiated by an object while it is being heated. This measurement is expressed in terms of absolute scale, (degrees Kelvin). Lower Kevin temperatures such as 2004K are red; higher temperatures such as 9300K are blue. Neutral temperature is white, at 6504K.

Q9: Can I connect my LCD monitor to any PC, workstation or Mac?

Ans.: Yes. All Philips LCD monitors are fully compatible with standard PCs, Macs and workstations. You may need a cable adapter to connect the monitor to your Mac system. Please contact your Philips sales representative for more information.

Q10: Are Philips LCD monitors Plugand- Play?

Ans.: Yes, the monitors are Plug-and-Play compatible with Windows 10/8.1/8/7, Mac OSX.

Q11: What is Image Sticking, or Image Burn-in, or After Image, or Ghost Image in LCD panels?

Ans.: Uninterrupted display of still or static images over an extended period may cause "burn in", also known as "after-imaging" or

"ghost imaging", on your screen.
"Burn-in", "after-imaging", or
"ghost imaging" is a well-known
phenomenon in LCD panel
technology. In most cases, the
"burned in" or "atter-imaging"
or "ghost imaging" will disappear
gradually over a period of
time after the power has been
switched off.
Always activate a moving screen
saver program when you leave

saver program when you leave your monitor unattended.
Always activate a periodic screen refresh application if your LCD monitor will display unchanging static content.

Warning

Severe"burn-in" or "after-image" or "ghost image" symptoms will not disappear and cannot be repaired. The damage mentioned above is not covered under your warranty.

Q12: Why is my Display not showing sharp text, and is displaying jagged characters?

Ans.: Your LCD monitor works best at its native resolution of 1920x1080@60Hz. For best display, please use this resolution.

Q13: How to unlock/lock my hot key?

Ans.: Please press (OK for 10 seconds to unlock/lock the hot key, by doing so, your monitor pops out "Attention" to show the unlock/lock status as shown below illustrators.

Monitor controls unlocked

Monitor controls locked



© 2018 Koninklijke Philips N.V. All rights reserved.

This product was manufactured and brought to the market by or on behalf of Top Victory Investments Ltd. or one of its affiliates. Top Victory Investments Ltd. is the warrantor in relation to this product. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V. used under license.

Specifications are subject to change without notice.

Version: M9221EE1L